

Name of work

Annual Operation and Maintenance Contract (AOMC) of 1 no.33/11 KV substation, 13 no's 11/0.433 KV substations and PLC Panel, AMF panels & LT panels of all DG set and petty electrical works of substations, underground distribution system, feeder pillars installed in the campus including supply of day to day manpower for maintenance of street light & for metering works at campus of IIT Kanpur & Outreach Centre NOIDA.

BID DOCUMENT



Superintending Engineer,
& Head, IWD
Indian Institute of Technology, Kanpur

Indian Institute of Technology Kanpur

Contents

Sl. No.	Description	Page No.
1.	Notice Inviting E-tenders	5-6
2.	Information and Instructions for Bidders for E-Tendering	7-14
2.1	Instructions for Online BID Submission	14
2.2.1	Registration	15
2.2.2	Searching for tender documents	15
2.2.3	Preparation of bids	15
2.2.4	Submission of bids	16
2.2.5	Assistance to bidders	17
2.2.6	General instruction to bidders	17
2.3	List of documents to be scanned and uploaded within the period of bid submission	
2.3.1	Envelope - 1: Technical Bid	18
2.3.2	Envelope - 2: Financial Bid	19
3	Eligibility Criteria	
3.1	Eligibility criteria for contractors	19
4	Bid Evaluation and Award	
4.1	Technical Bid Evaluation	20
4.2	Financial Bid Evaluation	21
4.3	Selection Criteria	21
5	Various Forms and Formats	
5.1	Affidavit for not being blacklisted/debarred/restrained	22
5.2	Performance report on work executed	23
5.3	Structure and Organization of the Agency	24
5.4	Declaration on Details of the Bidders	25-26
5.5	Details of Similar Nature of Works Completed	27
5.6	Declaration About Site Inspection	28
5.7	Letter of Transmittal	29

5.8	Tender Certificate	30
5.9	Tender Acceptance Letter	31
5.10	CPWD-7	32-33
5.11	Financial information	34
5.12	Banker's Certificate from a scheduled Bank	35
5.13	Net Worth Certificate by certified Chartered Accountant	36
6	Proforma of Schedules	
6.1	SCHEDULE 'A': Schedule of Quantities	37
6.2	SCHEDULE 'B': Schedule of materials to be issued to the contractor	37
6.3	SCHEDULE 'C': Tools and plants to be hired to the contractor	37
6.4	SCHEDULE 'D': Extra schedule for specific requirements / document for the work, if any	37
6.5	SCHEDULE 'E': Reference to General Conditions of Contract	37
6.6	SCHEDULE 'F': General Rules and Directions	37
6.6.1	Definitions	38
6.6.2	Clauses	39-42
7	Scope of work , Specifications & Special conditions of contract	
7.1	Brief Scope of Work	43
7.2	Specifications for electrical works	44-93
7.3	List of Approved Make	94-98
8	Terms & Conditions of Contract	
8.1	Special Conditions for the minor works under the contract	99
8.2	Timely Completion	99
8.3	Rates	99-101
8.4	Quality and Workmanship	101-103
8.5	Natural calamity	103
8.6	Safety and Security	103-104
8.7	Approach to Site	104
8.8	Acts and Laws	104
8.9	Labour and Laws	105

8.10	Nondisclosure Agreement	105
8.11	Indemnification	105
8.12	Force Majeure	105
8.13	Dispute resolution	106
8.14	Arbitration	106
8.15	Jurisdiction of Courts	107
8.16	E&M Works	108-111
8.17	Scope of works for O&M of Substation	112-113
8.18	Special Condition for Material	114-151
8.19	Special Condition of Contract	152-158
8.20	Integrity pact	159-168
8.21	Circular CPWD Testing Charges	169

It is certified that this document contains 169 pages

Superintending Engineer

1. Notice Inviting e-Tenders

The Superintending Engineer, IWD, IIT Kanpur on behalf of Board of Governors of IIT Kanpur invites online percentage rate tender from enlisted contractors in CPWD and / or the eligible firms / agencies satisfying criteria mentioned in the document for the following electrical work in two bid system.

NIT No: **58/EE/Elect/2026-27**

1	Name of work	:	Annual Operation and Maintenance Contract (AOMC) of 1 no.33/11 KV substation, 13 no's 11/0.433 KV substations and PLC Panel, AMF panels & LT panels of all DG set and petty electrical works of substations, underground distribution system, feeder pillars installed in the campus including supply of day to day manpower for maintenance of street light & for metering works at campus of IIT Kanpur & Outreach Centre NOIDA.
2	Estimated cost (inclusive of GST)	:	Rs. 1,76,51,038/-
3	Earnest Money Deposit (Rs.)	:	Rs. 3,53,021/- (The Director, IIT `Kanpur)
4	Duration of contract	:	Twelve (12) months
5	Last Time & date of submission of bids (Up to)	:	As per CPP portal data (https://eprocure.gov.in/eprocure/app)
6	Opening of bids	:	As per CPP portal data (https://eprocure.gov.in/eprocure/app)
7	Time allowed for submission of requisite documents by lowest bidder	:	Within One week of opening of financial bids

The bid forms and other details may be downloaded from Central Public Procurement Portal (<http://eprocure.gov.in/eprocure/app>). Aspiring bidders who have not enrolled / registered in e-procurement should enroll / register themselves before participating through web site <http://eprocure.gov.in/eprocure/app>. The portal enrolment is free of cost. Bidders are advised to go through instructions provided at "Instructions for online bid submission."

Bidders can access quotation /tender documents on the website (for searching in the NIC site), kindly go to quotation search option and type 'IIT'. Thereafter, click on "GO" button to view all IIT quotations. Select the appropriate quotation / tender and fill them with all relevant information and submit the completed Quotation / Tender document online on the website <http://eprocure.gov.in/eprocure/app> as per the schedule given in the next

page.

Note: No manual bids will be accepted. All bids (both Technical & Financial) should be submitted in the e-procurement portal.

Applicants are advised to keep visiting the above-mentioned websites from time to time (till the deadline for bid submission) for any updates in respect of the tender documents, if any. Failure to do so shall not absolve the applicant of his liabilities to submit the applications complete in all respect including updates thereof, if any. An incomplete application may be liable for rejection.

Superintending Engineer

2. Information and Instructions for Bidders for E-Tendering

The Superintending Engineer, IWD, IIT Kanpur on behalf of Board of Governors of IIT Kanpur invites online percentage rate tender from enlisted contractors in CPWD and / or the eligible firms / agencies satisfying criteria mentioned in the document for the following electrical work in two bid system.

1	Name of organization	:	Indian Institute of Technology, Kanpur
2	NIT No.	:	58/EE/Elect/2026-27
3	Location	:	Indian Institute of Technology, Kanpur
4	Tender / Quotation type (open / limited /EOI / Auction / Single)	:	Open
5	Tender / Quotation category (services / works)	:	Services
6	Type of Contract (work / supply / auction/ service / buy / empanelment / sell)	:	Service
7	Form of contract (CPWD-7/8)	:	CPWD-7
8	Work Category (civil / electrical / fleet / management / computer system)	:	Electrical
9	Is multi-currency allowed?	:	No
10	Date of publishing / issue / start	:	As per CPP portal
11	Document download start date	:	As per CPP portal
12	Document download end date	:	As per CPP portal
13	Date & time of pre-bid meeting	:	As per CPP portal
14	Venue of pre-bid meeting	:	As per CPP portal
15	Last date & time of uploading of bids	:	As per CPP portal
16	Date & time of opening of technical bids	:	As per CPP portal
17	Bid Validity Days	:	90 days after opening of technicalbid
18	Earnest Money Deposit (EMD)	:	Rs. 3,53,021/- scanned copy as a proof of EMD deposition to be uploaded with e-Tendering website by the bidder within the period of bid submission. This should be in the form of a bank guarantee (including e-bank Guarantee) or Banker's Cheque or Demand Draft (DD) or Fixed

			Deposit receipt issued by Scheduled Commercial Bank or Nationalized Bank in favour of "The Director, IIT Kanpur" Payable at Kanpur shall be scanned and uploaded to the e-tendering website by the bidder within the period of bid submission. The hard copy of earnest despite receipt (EMD) shall be submitted in the office of Superintending Engineer, Central Office IWD, IIT Kanpur (except in case of e-bank Guarantee) before the date and time of opening of technical bids as specified in the bid document.
20	No. of Bids / Covers (1 / 2 / 3 / 4)	:	2
21	Address for communication	:	Office of Superintending Engineer, IWD, IIT Kanpur-208016 Contact no. 0512-259-7725
22	Email address	:	seiwd@iitk.ac.in , kpradeep@iitk.ac.in

The intending bidder must read the terms and conditions of CPWD-6 carefully. He should only submit his bid if he considers himself eligible and he is in possession of all the documents required.

1. Information and instructions for bidders posted on website shall form part of bid document.
2. The bid document consisting of drawings, specifications, schedule of quantities of items to be executed, schedule of stages for payment as applicable and the set of terms & conditions of the contract to be complied with and other necessary documents can be seen and downloaded free of cost from www.eprocure.gov.in
3. But the bid can only be submitted after deposition of proof of submission of EMD. (except in case of e-bank Guarantee).
4. Those contractors not registered on the website mentioned above, are required to get registered beforehand. Only e-bids shall be accepted in CPPP portal through e-tendering processes.
5. The intending bidder must have valid Class-III digital signature to submit the bid.
6. On opening date, the contractor can login and see the bid opening process. After opening of bids, Contractor will receive the competitor bid sheets.
7. Contractor can upload documents in the form of JPG format and PDF format.

8. Contractor must ensure to quote rate of each item. The column meant for quoting rate in figures appears in pink colour and the moment rate is entered, it turns sky blue.

In addition to this, while selecting any of the cells a warning appears that if any cell is left blank the same shall be treated as "0". Therefore, if any cell is left blank and no rate is quoted by the bidder, rate of such item shall be treated as "0" (ZERO).

However, if a tenderer quotes nil rates against each item in item rate, the tender shall be treated as invalid and will not be considered as lowest tenderer.

9. The "Eligibility/technical Bid" shall be opened first on due date and time as per the evaluation scheme. The "Financial Bid" of bidders qualifying the technical bid shall be opened on a later date as to be announced in CPP portal.
10. The bidders are advised to visit the site before submission of bids to have more clarity about the site conditions and availability of space for execution of the work.
11. All modifications/addendums/corrigendum's issued regarding this bidding process shall be uploaded on website only.
12. The department reserves the right to reject any or all bids without assigning any reason thereof and may restrict the list of qualified bidders to any number deemed suitable by it, if too many bids are received satisfying the minimum laid down criteria.
13. The rates for all items of work, shall unless clearly specified otherwise, include cost of all operations and all inputs of labour, material, T&P, scaffolding, wastages, watch and ward, other inputs, all incidental charges, all other taxes (inclusive of GST), cess, duties, levies etc. required for execution of the work.
14. If claimed, the enlistment of the contractors should be valid on the last date of submission of bids. In case the last date of submission of bid is extended, the enlistment of contractor should be valid on the original date of submission of bids.
15. The description of the work is as follows: **"Annual Operation and Maintenance Contract (AOMC) of 1 no.33/11 KV substation, 13 no's 11/0.433 KV substations and PLC Panel, AMF panels & LT panels of all DG set and petty electrical works of substations, underground distribution system, feeder pillars installed in the campus including supply of day to day manpower for maintenance of street light & for metering works at campus of IIT Kanpur & Outreach Centre NOIDA.**
16. The work is estimated to cost **Rs. 1,76,51,038/-**. However, this estimate given is mere approximation for guide.
17. Agreement shall be drawn with the successful bidders on prescribed Form No. CPWD 7 which is available as a Govt. of India Publication and also

available on website www.cpwd.gov.in. Bidders shall quote his rates as per various terms and conditions of the said form which will form part of the agreement.

18. The site for the work will be handed over as per the special terms and conditions of the document.
19. An approval programme of completion submitted by the contractor after award of work based on the milestone given in the tender.
20. The bid document consisting of NIT, the schedule of quantities of various types of items to be executed and the set of terms and conditions of the contract to be complied with and other necessary documents can be seen and downloaded from website www.eprocure.gov.in free of cost.
21. After submission of the bid the contractor can re-submit revised bid any number of times but before last time and date of submission of bid as notified.
22. While submitting the revised bid, contractor can revise the rate of one or more item(s) any number of times (he/she need not re-enter rate of all the items) but before last time and date of submission of bid as notified.
23. Earnest Money Deposit receipt scanned copy shall be uploaded to the e-Tendering website within period of submission (except in case of e-bank Guarantee).
24. Copy of documents as specified in the bid shall be scanned and uploaded to the e-tendering website within the period of bid submission.
25. The bid submitted shall be opened as per the details provided in the CPP portal at IWD office. The date of opening of Financial Bid shall be informed through web site after the opening of financial bid.
26. The bid submitted shall become invalid if:
 - (i) The bidder is found ineligible.
 - (ii) **If the bidder does not deposit original EMD to the office of Executive Engineer, Electrical Division, IWD, IIT Kanpur within the due date of submission (except in case of e-bank Guarantee).**
 - (iii) The bidder does not upload scanned copies of all the documents stipulated in the bid document.
 - (iv) If a tenderer quotes nil rates against each item in item rate tender (if applicable), the tender shall be treated as invalid and will not be considered as lowest tenderer.
27. Performance Guarantee (PG) shall be 5% of the Estimated cost put to tender (ECPT) or contract amount whichever is higher, valid up to stipulated date of completion and Six (6) months beyond that. Following conditions shall also be applicable:
 - a) A bid will be treated abnormally low if the quoted amount is lesser

than 80% of estimated cost put to tender.

- b) Requirement of Additional proforma Guarantee (APG): In case of abnormally low bids as defined above, the bidder shall be required Additional Performance Guarantee (APG) in addition to the Standard Performance Guarantee (PG).
 - c) The amount of Additional Performance Guarantee (APG) shall be equivalent to the difference between the 80% amount of ECPT and quoted amount. (e.g. if ECPT is A and quoted amount is 0.7A then the amount of APG shall be $0.8A - 0.7A$).
 - d) The Additional Performance Guarantee (APG) shall be in the prescribed format of Performance Guarantee and has to be submitted within the time frame prescribed for submission of Performance Guarantee. The other terms and conditions of release etc. of APG shall be same as that of PG.
28. In case the contractor fails to deposit the said performance guarantee within the period as indicated in Schedule 'F' including the extended period if any, the contractor shall be suspended for two years and shall not be eligible to bid for IITK tenders from the date of issue of suspension order.
29. The contractor whose bid is accepted will also be required to furnish either copy of applicable licenses/ registrations or proof of applying for obtaining licenses, registration with EPFO, ESIC and BOCW Welfare Board including Provident Fund Code No. If applicable and also ensure the compliance of afore said provisions by the sub-contractors, if any engaged by the contractor for the said work and program chart (Time and Progress) within the period specified in Schedule 'F'.
30. Intending Bidders are advised to inspect and examine the sites and its surroundings and satisfy themselves before submitting their bids as to the nature of the ground and sub-soil (so far as is practicable), the form and nature of the site, the means of access to the site, making proper arrangements to the site for smooth operation, the accommodation they may require and in general shall themselves obtain all necessary information as to risks, contingencies and other circumstances which may influence or affect their bid. Bidder shall be deemed to have full knowledge of the sites whether he inspects it or not and no extra charge consequent on any misunderstanding or otherwise shall be allowed. The bidder shall be responsible for arranging and maintaining at his own cost all materials, tools & plants, water, electricity access, facilities for workers and all other services required for executing the work unless otherwise specifically provided for in the contract documents. Submission of a bid by a bidder implies that he has read this notice and all other contract documents and has made himself aware of the scope and specifications of the work to be done and of conditions and rates at which stores, tools and plant, etc. will be issued to him by the Institute and local conditions and other factors having a bearing on the execution of the work.

31. Intending Bidders are advised to get familiarized with the specifications /rules related (i.e., **"Annual Operation and Maintenance Contract (AOMC) of 1 no.33/11 KV substation, 13 no's 11/0.433 KV substations and PLC Panel, AMF panels & LT panels of all DG set and petty electrical works of substations, underground distribution system, feeder pillars installed in the campus including supply of day to day manpower for maintenance of street light & for metering works at campus of IIT Kanpur & Outreach Centre NOIDA"**) to the work as approved by the competent authority and various policies related to C&D waste and other environmental guidelines of the institute pertaining to the. Bidder shall be deemed to have full knowledge of such rules and regulations whether he has read it or not and no extra charge consequent on any misunderstanding or otherwise shall be allowed. In case of reduction of scope of work or no work is possible to carry out on account of such issues, no cost shall be payable to them. Submission of a bid by the bidder implies that he has read this notice and all other documents and has made himself aware of the Institute Regulations and other factors having a bearing on the execution of the work.
32. The competent authority on behalf of the Board of Governors does not bind itself to accept the lowest or any other bid and reserves to itself the authority to reject any or all the bids received without assigning any reason. Bids in which any of the prescribed conditions is not fulfilled or any condition including that of conditional rebate is put forth by the bidders shall be summarily rejected.
33. Canvassing whether directly or indirectly, in connection with bids is strictly prohibited and the bids submitted by the bidders who resort to canvassing will be liable to rejection.
34. The competent authority on behalf of the Board of Governors reserves to himself the right of accepting the whole or any part of the bid and the bidders shall be bound to perform the same at the rate quoted.
35. The contractor shall not be permitted to bid for works in the Institute Works Department responsible for award and execution of contracts, in which his near relative is posted as Divisional Accountant or as an officer in any capacity between the grades of Superintending Engineer and Junior Engineer (both inclusive) in IWD. He shall also intimate the names of persons who are working with him in any capacity or are subsequently employed by him and who are near relatives to any gazetted officer in the Office of IWD/ Institute Works Department. Any breach of this condition by the contractor would render him liable to be removed from the approved list of contractors of this Department.
36. No Engineer of Gazetted Rank or other Gazetted Officer employed in Engineering or Administrative duties in an Engineering Department of the Government of India is allowed to work as a contractor for a period of one year after his retirement from Government services without the prior permission of the Government of India in writing. This contract is liable to be canceled if either the contractor or any of his employees is found any time

to be such a person who had not obtained the permission of the Government of India as aforesaid before submission of the bid or engagement in the contractor's services.

37. The bids for the work shall remain open for acceptance for a period of Ninety (90) days from the date of opening of bids. If any bidder withdraws its bid before the said period or issue of Letter of Acceptance, whichever is earlier, or makes any modifications in the terms and conditions of the bid which are not acceptable to the department, then the Institute shall, without prejudice to any other right or remedy, be at liberty to suspend the bidder for one year.
38. This notice inviting Bid shall form a part of the contract document. The successful bidders/contractor, on acceptance of its bid by the Accepting Authority shall within 7 days from the stipulated date of start of the work, will sign the contract consisting of the Notice Inviting Bid, all the documents including additional conditions, specifications and drawings, if any, forming part of the bid as uploaded at the time of invitation of bid and the rates quoted online at the time of submission of bid and acceptance thereof together with any correspondence leading thereto.
39. Standard C.P.W.D. Form 7 or other Standard C.P.W.D. Form as applicable.
40. The bid document will include the following components:
 - (a) CPWD-7 and CPWD-6 including Schedule A to F for all the components of the work, Standard General Conditions of Contract for CPWD 2023 as amended/modified up to last date of submission of the bid.
 - (b) General / specific conditions, specifications applicable to all components of the work.
41. The eligible bidders shall quote percentage rates after considering all the components of the work.
42. After acceptance of the bid by competent authority, the Superintending Engineer, IWD shall issue letter of award on behalf of the Board of Governors to the contractor. After the work is awarded, the contractor will have to enter into one agreement with Superintending Engineer, IWD. One such signed set of agreement shall be handed over to Engineer-In-Charge as applicable.
43. Entire work under the scope of bid shall be executed under one agreement.
44. The requirement of technical staff given in various specialized works is as per requirements given in clause 32 of NIT document. The actual deployment of these technical staff will be as per execution of work and direction of the Executive Engineer, IITK.
45. The bill for work components shall be facilitated by Engineer-in-Charge to the contractor.
46. The work shall be treated as complete when all the components of the

work are complete.

47. It will be obligatory on the part of bidder to sign the contract document for all components before the first payment is released.
48. In case of reduction in scope of work claim on account of reduction in value of work, loss of expected profit, consequential overheads etc. shall not be entertained.
49. A team of officers from Indian Institute of Technology Kanpur may visit the office/ site of work of bidders for establishing their credibility and verification of submitted documents
50. The mentioned work is urgent as requested by client/Institute and to be completed strictly in given time schedule as per special terms and conditions. The contractor has to deploy the labour and supervisory staff in shifts to meet the targeted completion date. The work may be executed in extended shifts or two shifts. The rates quoted by the contractor will be deemed to be inclusive of any extra expenditures on account of this reason. Nothing shall be paid on this account.
51. The competent authority on behalf of the Board of Governors reserves the right to terminate the contract if,
 - a) Any violation of labour law has been observed.
 - b) Any of the construction workers engaged in the works under this contract is found also engaged in Service Contracts of the Institute at the same time.
52. The competent authority on behalf of the Board of Governors reserves the right to disqualify an agency for
 - (a) Non-compliance of Institute orders
 - (b) Violation of Institute policies as established by the Competent Authority in the best interests of the Institute.
53. Payment shall be regulated as under:
 - (a) Payment shall be made on submission of monthly running bill.

2.2 Instructions for Online BID Submission

This tender document has been published on the Central Public Procurement Portal (URL: <http://eprocure.gov.in/eprocure/app>). The bidders are required to submit softcopies of their bids electronically on the CPP portal, using valid Digital Signature Certificates (DSC). The instructions given below are meant to assist the bidders in registering on the CPP portal, prepare their bids in accordance with the requirements and submitting their bids online on the CPP portal.

More information useful for submitting online bids on the CPP portal may be obtained at <http://eprocure.gov.in/eprocure/app>

2.2.1 Registration

1. Bidders are required to enroll on the e-procurement module of the Central Public Procurement portal ([URL:http://eprocure.gov.in/eprocure/app](http://eprocure.gov.in/eprocure/app)) by clicking on the link, "click here to enroll". Enrolment on the CPP portal is free of charge.
2. As part of the enrolment process, the bidders will be required to choose a unique username and assign a password for the accounts.
3. Bidders are advised to register their valid e-mail address and mobile number as part of the registration process. These would be used for any communication from the CPP portal.
4. Upon enrolment, the bidders will be required to register their valid Digital Signature Certificate (class 2 or class 3 certificates with signing key usage) issued by any certifying authority recognized by CCA India (e.g. Sify / TCS / nCode/ eMudhra etc.) with their profile.
5. Only one valid DSC should be registered by a bidder. Please note that bidders are responsible to ensure that they do not lend their DSCs to others which may lead to misuse.
6. Bidder then logs in to the site through the secured log-in by entering their user ID Password and the password of the DSC / eToken.

2.2.2 Searching for tender documents

1. There are various search options built in the CPP portal to facilitate bidders to search active tenders by several parameters. These parameters could include tender ID, organization name, location, date, value, etc. There is also an option of advanced search for tenders, wherein the bidders may combine a number of search parameters such as organization name, form of contract, location, date, other keywords etc. to search for a tender published on the CPP portal
2. Once the bidders have selected the tenders they are interested in, they may download the required documents / tender schedules. The tenders can be moved to the respective "My Tenders" folder. This would enable the CPP portal to intimate the bidders through SMS / e-mail in case there is any corrigendum issued to the tender document.
3. The bidder should make a note of the unique Tender ID assigned to each other; in case they want to obtain any clarification/help from the Helpdesk.

2.2.3 Preparation of bids

1. Bidder should take into account any corrigendum published on the tender document before submitting their bids.
2. Please go through the tender advertisement and the tender document

carefully to understand the documents required to be submitted as part of the bids. Please note the number of covers in which the bid documents have to be submitted. Any deviations from these may lead to rejection of the bids.

3. Bidder, in advance, should get ready the bid documents to be submitted as indicated in the tender document / schedule and generally, they can be in PDF / XLS / RAR / DWF formats. Bid documents may be scanned with 100 dpi with black & white option.
4. To avoid the time and effort required in uploading the same set of standard documents which are required to be submitted as a part of every bid, a provision of uploading such standard documents (e.g., PAN card copy, annual reports, auditor's certificates, etc.) has been provided to the bidders. Bidders can use "My Space" area available to them to upload such documents. These documents may be directly submitted from the "My Space" area while submitting a bid, and need not be uploaded again and again. This will lead to a reduction in the time required for bid submission process.

2.2.4 Submission of bids

1. Bidder should log into the site well in advance for bid submission so that he / she upload the bid in time i.e. on or before the bid submission time. Bidder will be responsible for any delay due to other issues.
2. The bidder has to digitally sign and upload the required bid documents one by one as indicated in the tender document.
3. A standard BOQ Format has been provided with the tender document to be filled by all the bidders. Bidders are requested to note that they should necessarily submit their financial bids in the format provided and no other format is acceptable. Bidders are required to download the BOQ file, open it and complete the white colored [unprotected] cells with their respective financial quotes and other details (such as name of the bidder). No other cells should be changed. Once the details have been completed, the bidder should save it online, without changing the filename. If the BOQ file is found to be modified by the bidder, the bid will be rejected.
4. The server time (which is displayed on the bidders' dashboard) will be considered as the standard time for referencing the deadlines for submission of the bids by the bidders, opening of bids etc. The bidders should follow this time during bid submission.
5. All the documents being submitted by the bidders would be encrypted using PKI encryption techniques to ensure the secrecy of the data. The data entered cannot be viewed by unauthorized persons until the time of bid opening. The confidentiality of the bids is maintained using the secured Socket Layer 128-bit encryption technology. Data storage encryption of sensitive fields is done.
6. The uploaded tender documents become readable only after the tender

opening by the authorized bid openers.

7. Upon the successful and timely submission of bids, the portal will give a successful bid submission message & a bid summary will be displayed with the bid no. and the date & time of submission of the bid with all other relevant details.
8. Add scanned PDF of all relevant documents in a single PDF file of compliance sheet.

2.2.5 Assistance to bidders

1. Any queries relating to tender document and the terms and conditions contained therein should be addressed to the tender inviting authority for a tender or the relevant contact person indicated in the tender.
2. Any queries relating to the process of online bid submission or queries relating to CPP portal in general may be directed to the 24 x 7 CPP Portal Help Desk.

2.2.6 General instruction to bidders

1. The tenders will be received online through portal <https://eprocure.gov.in/eprocure/app>. In the technical bids, the bidders are required to upload all the documents in PDF format.
2. Possession of a valid class II / III Digital Signature Certificate (DSC) in the form of smart card / e-token in the company's name is a prerequisite for registration and participating in the bid submission activities through <https://eprocure.gov.in/eprocure/app>. Digital Signature Certificates can be obtained from the authorized certifying agencies, details of which are available in the website <https://eprocure.gov.in/eprocure/app> under the link "Information about DSC".

Tenderers are advised to follow the instructions provided in the "Instructions to the tenderer" for the e-submission of the bids online through the Central Public Procurement Portal for e-procurement at <https://eprocure.gov.in/eprocure/app>.

Superintending Engineer

2.3 List of documents to be scanned and uploaded within the period of bid submission

The following mandatory documents to be submitted with online bid submission:

The Online bids (complete in all respect) must be uploaded online in two Envelops as explained here: -

2.3.1 Envelope - 1: Technical Bid

The following mandatory documents to be provided as **a single PDF** file in the same sequence as listed for an eligible bid:

1. EMD scanned copy shall be submitted along with the technical bid**
2. GST Registration Certificate
3. Copy of EPF & ESI Registration
4. Copy of PAN card
5. Affidavit for not being blacklisted/debarred/restrained as per 5.1
6. Performance report of works executed as per 5.2 or Completion certificate issued by competent Authority.
7. Structure and Organization of the Agency as per 5.3
8. Declaration on Details of the Bidder(s) as per 5.4
9. Details of Similar Nature of Works Completed as per 5.5
10. Declaration about Site Inspection as per 5.6
11. Letter of Transmittal as per 5.7
12. Tender Certificate as per 5.8
13. Tender Acceptance Letter as per 5.9
14. CPWD-7 5.10
15. Financial Information as per 5.11
16. Bankers certificate as per 5.12 (minimum 40% of estimated cost put to tender) Or Net Worth Certificate (minimum 10% from certified Chartered Accountant with UDIN) as per 5.13
17. Scanned copy of "A" class electrical license.
18. Registration details with the Govt. Department (CPWD, BSNL, MES, State Govt. Bodies, State /Central PSUs, Central Govt. Bodies).
19. Integrity pact should be signed, and scanned copy of the same shall be uploaded along with technical bid. At the time of award of the work the hard copy of the same on a non-judicial Stamp paper of Rs. 100/- shall be submitted which shall be the part of the contract agreement.

****The bidder must provide an Earnest Money Deposit (EMD) for the amount specified in the tender document. This should be in the form of a bank guarantee (including e-bank Guarantee) or Banker's Cheque or Demand Draft (DD) or Fixed Deposit receipt issued by Scheduled Commercial Bank or Nationalized Bank in favour of "The Director, IIT Kanpur" Payable at Kanpur shall be scanned and uploaded to the e-tendering website by the bidder within the period of bid submission. The hard copy of earnest despite receipt (EMD) shall be submitted in the office of Superintending Engineer, Central Office IWD, IIT Kanpur (except in case of e-bank Guarantee) before the date and time of opening of technical bids as specified in the bid document.**

Due date for EMD hardcopy submission is 14.10.2026 @ 15.30Hrs

2.3.2 Envelope - 2: Financial Bid

Price bid should be submitted in BOQ format

1. Eligibility Criteria*

3.1 Eligibility criteria for contractors

Contractors who fulfill the following criteria shall be eligible to apply.

Eligible Bidders

Eligible bidders should satisfy the following criteria for an eligible bid:

1. Average annual financial turn over:

Average annual financial turnover of works should be at least 30% of the estimated cost of work put to tender during the last 5 consecutive financial years by the certified Chartered Accountant.

Audited turnover statements to be furnished as proof of the same duly certified by chartered accountant along with Profit & Loss Statements.

2. Bankers Certificate- 40% of the estimated cost put to tender as per 5.12 Or

Net-Worth certificate of minimum 10% of the estimated cost put to tender issued by certified chartered Accountant with UDIN as per 5.13

3. Experience:

Firms/Contractors must have completed satisfactorily

i) One similar work of 80% value of the estimated cost put to tender

Or

ii) Two similar work of 60% value of the estimated cost put to tender

Or

iii) Three similar work of 40% value of the estimated cost put to tender

Works completed during last 7 years ending last day of the month previous to the one which application are invited.

And

One completed work of similar nature costing not less than the amount equal to 40% of the estimated cost put to tender (either part of above or a separate one) with Central Government Department/ Central Autonomous Body/ Central Public Sector Undertaking/ State Government Department/ State Autonomous Body/ State Public Sector Undertaking.

4. **Definition of similar work:** Similar type of work means "**Construction or Annual Operation & Maintenance of 33 /11 KV Substations & 11/0.433KV substations.**"
5. The value of executed works shall be brought to current costing level by enhancing the actual value of work at simple rate of 7% per annum; calculated from the date of completion to the previous day of last date of submission of bids.
6. **Having valid "A" Class Electrical License**

Eligible bidders must also satisfy the following conditions and ensure submission of all documents mentioned in 2.3

1. **Legal:** Unregistered Partnership Firm and Joint Venture or Consortium are not eligible.
2. **Registration:** Bidder should be registered with the Income Tax Department (PAN), Employees Provident Fund (EPF) Organization, Employees State Insurance (ESI) Corporation & GST. Bidders are not eligible in absence of these documents.

3. Bid Evaluation and Award

The following process will be followed for the Technical and Financial Bids Evaluation:

4.1 Technical Bid Evaluation

- Technical bids received complete in all respects covering the entire scope of work, will only be opened
- The technical bid evaluation is done only for bidders who satisfy the minimum criteria by submitting documentary proof supporting eligibility criteria and the bids of agencies who have not submitted these documents are liable to be rejected without notice.

4.2 Financial Bid Evaluation

For financial bids, the following points shall be followed:

- After evaluation of Pre-Qualification/technical bid Documents, a list of short-listed agencies will be prepared.
- Thereafter the financial bids of only the qualified and technically acceptable bidders shall be opened at the notified time, date and place in the presence of the qualified bidders or their representatives, if present.
- The bid shall remain valid for Ninety (90) days from date of opening of eligibility bids/Technical bid.

NOTE

The institute reserves the right, without being liable for any damages or obligation to inform the bidder, to:

- Amend the scope and value of contract to the bidder.
- Reject any or all the applications without assigning any reason.

Any effort on the part of the bidder or his agent to exercise influence or to pressurize the employer would result in rejection of his bid. Canvassing of any kind is prohibited.

4.3 Selection Criteria :

Contract award shall be based on the lowest financial bid (L1) among all technically qualified bidders.

Notes:

1. In case of tie during evaluation, the highest audited average turnover of the last three (03) financial years as a criterion to award the contract to avoid ambiguity or conflict among the bidders.

5. Various Forms and Formats

5.1 Affidavit for not being blacklisted/debarred/restrained

Proforma for AFFIDAVIT for not being blacklisted/debarred/restrained

(AFFIDAVIT to be submitted on a 'Non-Judicial' stamp paper worth Rs.100/)
(Scanned copy of this notarized affidavit to be uploaded at the time of submission of bid)

I/we undertake and confirm that our firm/partnership firm has not been blacklisted and/or debarred/restrained by any Central Govt./ State Govt. Agency/ Autonomous body of the Central or State govt./ PSU etc. Further that, if such information comes to the notice of the Institute, then I/we shall be debarred for bidding in the Institute in future forever. Also, if such information comes to the notice of the Institute on any day before date of start of work, the competent authority shall be free to cancel the agreement and to forfeit the entire amount of Earnest Money Deposit/Performance Guarantee.

Signature of bidder

OR

(An authorized Officer of the firm with stamp)

Signature of Notary with Seal

5.2 Performance report on work executed

Proforma of Performance report on works referred to in Financial Information

(To be printed in Company's Letterhead)

(Scanned copy of the Performance Reports to be uploaded at the time of submission of bid)

1. Name of work/project & location:
2. Agreement no.:
3. Estimated cost:
4. Tendered cost:
5. Date of start:
6. Date of completion:
7. Stipulated date of completion:
8. Actual date of completion:
9. Amount of compensation levied for delayed completion, if any:
10. Amount of reduced rate items, if any:
11. Performance Report:
 - (a) Quality of work: Outstanding / Very Good / Good /Poor
 - (b) Technical Proficiency: Outstanding / Very Good / Good /Poor
 - (c) Resourcefulness: Outstanding / Very Good / Good /Poor
 - (d) General Behavior: Outstanding / Very Good / Good /Poor

Signature of Superintending Engineer or Equivalent

Dated:

5.3 Structure and Organization of the Agency

Proforma of providing Structure and Organization of the Bidding Agency (To be printed in Company's Letterhead)

(Scanned copy of the Structure and Organization Document to be uploaded at the time of submission of bid)

1. Name & address of the bidder:
2. Telephone no./Telex no./Fax no.:
3. Email address for Communication:
4. Legal status of the bidder (attach copies of original document defining the legal status):
 - (a) An Individual:
 - (b) A proprietary firm:
 - (c) A firm in partnership:
 - (d) A limited company or Corporation:
5. Particulars of registration with various Government Bodies (attach attested photocopy)

Organization / Place of registration No.

- 1.
- 2.
- 3.
6. Names and titles of Directors & Officers with designation to be concerned with this work.
7. Designation of individuals authorized to act for the organization
8. Has the bidder, or any constituent partner in case of partnership firm, ever been convicted by the court of law? If so, give details.
9. Any other information considered necessary but not included above.

Signature of bidder

5.4 Declaration on Details of the Bidders

Proforma of Declaration on Details of the Bidders

(To be printed in Company's Letterhead)

(Scanned copy of the Performance Reports to be uploaded at the time of submission of bid)

DECLARATION

I/We,..... hereby declare that all the information and data furnished by our organization with regard to this tender specification are true and complete to the best of our knowledge. I/we have gone through the specification, conditions and stipulations in details and agree to comply with the requirements and intent of specification.

Particulars of the bidder as per following details:

1.	Name of the firm / organization	:	
2.	Type of the firm / organization: Public Ltd, / Private Ltd./ Registered firm	:	
3	Registered office	:	
4	Address of office	:	
5	Contract people	:	
6	Name & designation	:	
7	Land line & mobile no.	:	
8	Email	:	
9	PAN No.	:	
10	GST No.	:	
11	EPF Registration No.	:	
12	ESI Registration No.	:	
13	EMD/FDR/DD No. & Date	:	
14	Has the applicant ever been required to suspend any project for a period of more than six months continuously after Commencement of work?	:	If so, give the name of the project and reasons of suspension of project
15	Has the applicant ever been convicted by a court of law?	:	YES / NO, If yes give details of the case
16	Details of any litigation in which the applicant is / was involved.	:	

17	All forms submitted as desired in the bid	:	Yes / No
18	Undertaking regarding no subletting of work.	:	

We further declare that our organization has not been blacklisted /delisted or put to any holiday by any Institutional agency / Govt. Department / Public Sector Undertaking in the last three years.

Signature of Bidder(s) with seal

Dated:

5.5 Details of Similar Nature of Works Completed

Proforma for submission of Details of Eligible Similar Nature of Works Completed* during the Last Seven Years ending previous day of the last date of submission of tenders (Scanned copy of the Performance Reports to be uploaded)

The contractor needs to submit the supporting documents

Sr. No	Name of work / project and location	Owners or sponsoring organization	Cost of work in crores of rupees	Date of commencement as per contract	Stipulated date of completion	Actual date of completion	Litigation / arbitration cases pending /in Progress with details*	Name and address / telephone number of officers to whom reference may be made	Whether the work was done on back to back basis Yes/No
1	2	3	4	5	6	7	8	9	10
1									

* Indicate gross amount claimed and amount awarded by the Arbitrator.

Signature of bidder with seal

Dated:

5.6 Declaration about Site Inspection

Declaration about Site Inspection

(By Bidder)

To
The Superintending Engineer,
IWD, IIT,
Kanpur

Subject: Submission of Tender for the work of “Annual Operation and Maintenance Contract (AOMC) of 1 no.33/11 KV substation, 13 no’s 11/0.433 KV substations and PLC Panel, AMF panels & LT panels of all DG set and petty electrical works of substations, underground distribution system, feeder pillars installed in the campus including supply of day to day manpower for maintenance of street light & for metering works at campus of IIT Kanpur & Outreach Centre NOIDA.”

Dear Sir/Madam,

It is hereby declared that as per terms and conditions of this tender document, I / We the bidder inspected and examined the subject site and its surrounding and satisfy myself / ourselves as to the nature of the ground and sub-soil (so far as is practicable), the forms and nature of the site./ ourselves before submitting the bid, the accommodation which may require and all necessary information as to risks, contingencies and other circumstances which may influence or affect our bid have been obtained. I/We the bidder shall have full knowledge of the site and no extra charge consequent upon any misunderstanding or otherwise shall be claimed in later date. I /We bidder shall be responsible for arranging and maintaining at own cost all materials, tools & plants, water, electricity access, facilities for workers and all other services required for executing the work unless otherwise specifically provided for in the contract documents. Submission of a bid by me/us implies that I / We have read this notice and all other contract documents and has made myself /ourselves aware of the scope and specifications of the work to be done and local conditions and other factors having a bearing on the execution of the work.

Sincerely

(Duly authorized signatory of the Bidder)

5.7 Letter of Transmittal

To
The Superintending Engineer,
IIT, Kanpur - 208016

Name of Work: Annual Operation and Maintenance Contract (AOMC) of 1 no.33/11 KV substation, 13 no's 11/0.433 KV substations and PLC Panel, AMF panels & LT panels of all DG set and petty electrical works of substations, underground distribution system, feeder pillars installed in the campus including supply of day to day manpower for maintenance of street light & for metering works at campus of IIT Kanpur & Outreach Centre NOIDA.

Dear Sir/Madam

Having examined details given in Notice and bid document for the above work, I/we hereby submit the relevant information.

- 5.9.1 I/We hereby certify that all the statements made and information supplied in the enclosed forms and accompanying statement are true and correct.
- 5.9.2 I/we have furnished all information and details necessary for eligibility and have no further pertinent information to supply.
- 5.9.3 I/We also authorize the Executive Engineer, IWD, Indian Institute of Technology Kanpur or his representative(s) to approach individuals, employers, firms and corporation to verify our competence, work experience, and general reputation.
- 5.9.4 I/we submit the following certificates in support of our suitability, technical knowledge and capability for having successfully completed the following eligible completed works:

Sl. No.	Name of work	Amount	Certificate issued by
1			
2			

CERTIFICATE

It is certified that the information given in the enclosed eligibility bid are correct. It is also certified that I/We shall be liable to be debarred, disqualified/ cancelation of enlistment in case any information furnished by me/us found to be incorrect.

Signature(s) of Bidder with seal

Enclosures:

Date:

5.8 Certificate for Tender

(To be given on Company Letter Head)

Dated:

To,
The Superintending Engineer
IIT Kanpur-208016

Sub: Certificate of compliance as per Rule 144 (xi) GFR's 2017 Tender Reference

No:

Name of Tender / Work:

.....

I have read the clause regarding restrictions on procurement from a bidder of a country which shares a land border with India; I certify that this bidder is not from such a country or, if from such a country, has been registered with the Competent Authority. I hereby certify that this bidder fulfils all requirements in this regard and is eligible to be considered. [Where applicable, evidence of valid registration by the Competent Authority shall be attached.]"

I have read the clause regarding restrictions on procurement from a bidder of a country which shares a land border with India and on sub-contracting to contractors from such countries; I certify that this bidder is not from such a country or, if from such a country, has been registered with the Competent Authority and will not sub-contract any work to a contractor from such countries unless such contractor is registered with the Competent Authority. I hereby certify that this bidder fulfils all the requirements in this regard and is eligible to be considered. [Where applicable, evidence of valid registration by the Competent Authority shall be attached.]"

(Signature of the Bidder, with Official Seal)

5.9 Tender Acceptance Letter

(To be given on Company Letter Head)

Date:

To,
The Superintending Engineer
IIT, Kanpur-208016

Sub: Certificate of compliance as per Rule 144 (xi) GFR's 2017
Tender Reference No:

.....

Name of Tender / Work:

.....

Dear Sir,

1. I/ We have downloaded / obtained the tender document(s) for the above mentioned 'Tender/Work' from the web site(s) namely: as per your advertisement, given in the above-mentioned website(s).
2. I / We hereby certify that I / we have read the entire terms and conditions of the tender documents from Page No..... to (including all documents like annexure(s), schedule(s), etc .), which form part of the contract agreement and I / we shall abide hereby by the terms / conditions / clauses contained therein.
3. The corrigendum(s) issued from time to time by your department/ organisation too have also been taken into consideration, while submitting this acceptance letter.
4. I / We hereby unconditionally accept the tender conditions of above mentioned tender document(s) / corrigendum(s) in its totality / entirety.
5. I / We do hereby declare that our Firm has not been blacklisted/ debarred/ terminated/ banned by any Govt. Department/Public sector undertaking.
6. I / We certify that all information furnished by our Firm is true & correct and in the event that the information is found to be incorrect/untrue or found violated, then your department/ organization shall without giving any notice or reason therefore or summarily reject the bid or terminate the contract, without prejudice to any other rights or remedy including the forfeiture of the full said earnest money deposit absolutely.

Yours Faithfully,

(Signature of the Bidder, with Official Seal)

5.10 CPWD-7

CPWD-7

PERCENTAGE RATE TENDER & CONTRACT FOR WORKS

Tender for the “**Annual Operation and Maintenance Contract (AOMC) of 1 no.33/11 KV substation, 13 no’s 11/0.433 KV substations and PLC Panel, AMF panels & LT panels of all DG set and petty electrical works of substations, underground distribution system, feeder pillars installed in the campus including supply of day to day manpower for maintenance of street light & for metering works at campus of IIT Kanpur & Outreach Centre NOIDA**”

1. To be uploaded as per details uploaded in CPP portal at www.eprocure.gov.in
2. To be opened in the presence of tenderers who may be present at the time of opening in the Executive Engineer, IWD, IIT Kanpur.
3. The pre-qualification/Technical bid shall be opened first on due date and time as mentioned above. The time and date of opening of financial bid of contractors qualifying the technical bid shall be communicated to them at a later date.

TENDER

(To be signed in Company’s Letterhead)

I/We have read and examined the notice inviting tender, schedule, A, B, C, D, E & F Specifications applicable, Drawings & Designs, General Rules and Directions, General Conditions of Contract (For construction works) 2023, clauses of contract, Special conditions, Schedule of Rate & other documents and Rules referred to in the conditions of contract and all other contents in the tender document for the work.

I/We hereby tender for the execution of the work specified for the Board of Governors within the time specified in Schedule ‘F’ viz., schedule of quantities and in accordance in all respect with the specifications, designs, drawing and instructions in writing referred to in Rule-1 of General Rules and Directions and in Clause 11 of the Conditions of contract and with such materials as are provided for, by, and in respect of accordance with, such conditions so far as applicable.

We agree to keep the tender open for Ninety (90) days from the due date of its opening and not to make any modification in its terms and conditions.

I/We have deposited EMD for the prescribed amount in the office of concerned Executive Engineer as per the bid document.

If I/We, fail to furnish the prescribed performance guarantee within prescribed period, I/We agree that the said Board of Governors or his successors, in office shall without prejudice to any other right or remedy, be at liberty to take action

as per GCC 2023. Further, if I/We fail to commence work as specified, I/We agree that Board of Governors or the successors in office shall without prejudice to any other right or remedy available in law, be at liberty to forfeit the said performance guarantee absolutely. The said Performance Guarantee shall be a guarantee to execute all the works referred to in the tender documents upon the terms and conditions contained or referred to those in excess of that limit at the rates to be determined in accordance with the provision contained in Clauses 12.2 and 12.3 of the tender form.

Further, I/We agree that in case of forfeiture of Earnest Money or Performance Guarantee as aforesaid, I/We shall be debarred for participation in the re-tendering process of the work.

I/We undertake and confirm that eligible similar work(s) has/have not been got executed through another contractor on back-to-back basis. Further that, if such a violation comes to the notice of Department, then I/we shall be debarred for tendering in Indian Institute of Technology Kanpur in future forever. Also, if such a violation comes to the notice of Indian Institute of Technology Kanpur before date of start of work, the Executive Engineer, IWD shall be free to forfeit the entire amount of Performance Guarantee.

I/We hereby declare that I/We shall treat the tender documents drawings and other records connected with the work as secret/confidential documents and shall not communicate information / derived there from to any person other than a person to whom I/We am/are authorized to communicate the same or use the information in any manner prejudicial to the safety & integrity of IIT Kanpur.

Signature(s) of Contractor(s) with seal

Dated:

Address

Occupation

5.11 Financial Information

Proforma for providing Financial Information

(Scanned copy of the completed information sheet to be uploaded at the time of submission of bid)

Financial Analysis: Details to be furnished duly supported by figures in balance sheet/ profit & loss account for the last five financial years duly certified by the Chartered Accountant, as submitted by the applicant to the Income Tax Department (Copies to be attached).

Financial Years	2020-21	2021-22	2022-23	2023-24	2024-25
Gross Annual Turnover					
Profit/Loss					

Signature of Chartered Accountant with Seal

Signature of bidder

5.12 Banker's Certificate from a scheduled Bank

Proforma of Banker's Certificate from a Scheduled Bank

(To be printed in Bank's Letterhead)

(Scanned copy of the Certificate to be uploaded at the time of submission of bid)

This is to certify that to the best of our knowledge and information that M/s./Sh..... having marginally noted address, a customer of our bank are/is respectable and can be treated as good for any engagement up to a limit of Rs (Rupees). This certificate is issued without any guarantee or responsibility on the bank or any of the officers.

.....
(Signature for the Bank)

NOTE:

1. Bankers certificates should be on letter head of the Bank, addressed to tendering authority.
2. In case of partnership firm, certificate should include names of all partners as recorded with the Bank.

5.13 Net Worth Certificate by certified Chartered Accountant

Proforma of Net Worth Certificate by certified Chartered Accountant

(To be printed in Letterhead of Chartered Accountant)

(Scanned copy of the Certificate to be uploaded at the time of submission of bid)

This is to certify that as per the audited Balance Sheet and Profit & Loss statement of the account during the financial year

the net worth of

M/s./Sh.....(Name &

Registered Ad-

dress of individual/firm/company) as on 31.3.2025 is Rs.(Rupees.

.....) after considering all

liabilities.. It is further certified that the net worth of the company has not

eroded by more than 30% in the last three years ending on 31.3.2025.

.....
(Signature of the Chartered Accountant)

.....
(Name of the Chartered Accountant)

.....
(Membership No. of ICAI)

.....
(Date & Seal)

6. Proforma of Schedules

Operative schedules shall be supplied separately to each intending tenderer

SCHEDULE "A"	Schedule of Qty	Uploaded separately
---------------------	-----------------	---------------------

SCHEDULE 'B'

Schedule of materials to be issued to the contractor:

S. No.	Description of item	Quantity	Rates in figures & words at which the material will be charged to the contractor	Place of issue
1	2	3	4	5
NIL				

SCHEDULE 'C'

Schedule of Tools and Plants to be hired to the contractor

S. No.	Description	Hire charges per day	Place of issue
1	2	3	4

-----NIL -----

SCHEDULE "D"	Extra schedule for specific requirements/document for the work, if any:	As attached in tender form.
SCHEDULE "E"	Schedule of component of other Materials, Labour, POL etc. for price escalation	N. A.
SCHEDULE "F"	Reference to General Conditions of contract.	
Name of Work:	Annual Operation and Maintenance Contract (AOMC) of 1 no.33/11 KV substation, 13 no's 11/0.433 KV substations and PLC Panel, AMF panels & LT panels of all DG set and petty electrical works of substations, underground distribution system, feeder pillars installed in the campus including supply of day to day manpower for maintenance of street light & for metering works at campus of IIT Kanpur & Outreach Centre NOIDA	
Estimated cost of the work:	Rs. 1,76,51,038/- (i/c GST)	
Earnest money	Rs. 3,53,021/-	
Performance	Performance Guarantee (PG) shall be 5% of the estimated cost put	

Guarantee	to tender (ECPT) or contract amount whichever is higher, valid up to stipulated date of completion and Six (6) months beyond that. Following conditions shall also be applicable: a) A bid will be treated abnormally low if the quoted amount is lesser than 80% of estimated cost put to tender. b) Requirement of Additional proforma Guarantee (APG): In case of abnormally low bids as defined above, the bidder shall be required Additional Performance Guarantee (APG) in additional to the Standard Performance Guarantee (PG). c) The amount of Additional Performance Guarantee (APG) shall be equivalent to the difference between the 80% amount of ECPT and quoted amount. (e.g. if ECPT is "A and quoted amount is 0.7A then the amount of APG shall be 0.8A-0.7A)." d) The Additional Performance Guarantee (APG) shall be in the prescribed format of Performance Guarantee and has to be submitted within the time frame prescribed for submission of Performance Guarantee. The other terms and conditions of release etc. Of APG shall be same as that of PG.
Security Deposit	2.5% of the tendered value of the work will be deducted from each bill. Same would be released after successful completion of One-year defect liability period and as per special conditions of the contract

General rules and direction:

Officer inviting tender	Superintending Engineer, IWD, IIT, Kanpur.
-------------------------	---

Definitions:

2(v)	Engineer-in-charge	
	For Electrical works	Executive Engineer, IWD, IIT Kanpur
2(vi)	Accepting authority	Dy. Director, IIT Kanpur
2(vii)	Percentage on cost of materials and labour to cover all overheads and profits	15% (percent)
2(viii)	Standard Schedule of Rates:	Minimum central labour wage rates (central Govt. and Market rates for other items-if

ii)	Mile stone	Not applicable
Authority to decide	Extension of time	Superintending Engineer, IWD, IIT, Kanpur
Clause 6A	Computerized Measurement of bills	APPLICABLE
Clause 7		APPLICABLE
Clause 10A	Material to be provided by the contractor	APPLICABLE
Clause 10B (ii), (iii)	Whether clause 10-B (ii) and 10-B (iii) shall be applicable.	NOT APPLICABLE
Clause 10 C	Component of labour expressed as percentage of value of work	NOT APPLICABLE
Clause 10 CA		NOT APPLICABLE
Clause 10 CC	Increase/Decrease in Price of materials/wages	APPLICABLE
Clause 11		CPWD Specifications of all Electrical items (CPWD 2023), with correction Slips/ amendments /revisions issued up to the last date of receipt of tenders and as per NIT for E & M electrical Works .
Clause 12: Type of work		Operation and minor maintenance work
Clause 12.2 & 12.3: Deviation limit beyond which clause 12.2 & 12.3 shall apply for Building works		Applicable as per GCC 2023 Maintenance
Clause 16	Competent Authority for deciding reduced rates: For Civil items and For Electrical items of work	As per table 7
Clause 17	Defect liability period completion of contract	One Year and those listed in Special Conditions of Contract

Clause 18	List of mandatory machinery, tools & plants to be deployed by the contractor at site	As per the scope of work		
Clause 32 -	Requirement of Technical Representative(s)	As per table 9		
If the Contractor commits default in commencing the execution of the work as aforesaid, the performance guarantee shall be forfeited.				
Table 6 Major milestones of the project				
Sl. No.	Description of Milestone (Physical)	Time allowed from date of start	Maximum duration of work	Amount to be withheld in case of non-achieve of the milestones (% of composite tendered amount)
1.	Not Applicable			
The detailed program chart approved by the engineer-in-charge shall indicate how the resources will be deployed by the contractor to maintain desired progress and for the completion of the work within the specified period. If the submitted program is approved, the milestone shall be redefined accordingly by the Executive Engineer, IWD Indian Institute of Technology Kanpur. The amount to be withheld in such a case, for non-achievement of milestone(s), shall remain unaltered i.e., 1% of tendered amount				
Table 7 Authority to decide				
1.	Extension of time (EOT)	Executive Engineer-II (Elect.) / Superintending Engineer, IWD, IIT, Kanpur		
2.	Rescheduling of milestones	Superintending Engineer, IWD, IIT, Kanpur		
3.	Shifting of start in case of delay in handing over of site.	Superintending Engineer, IWD, IIT, Kanpur		
Table 8: Materials for which all India Wholesale Price Index to be followed				
Nearest Materials (other than cement, reinforcement bars and the structural steel) for which All India Wholesale Price Index to be followed)				
Sl. No.	Material covered under this clause	Base Price of Materials, covered under clause 10 CA		
1.	Not applicable			

Table 9: Requirement of Technical staff as per Clause 32

Sl. No.	Qualification	Number	Minimum Experience in years	Designation	Rate at which the recovery shall be made from the contractor in the event of not fulfilling provision of Clause 32
1.	Graduate / Diploma	1	5	Project / Planning / construction / billing Engineer (Electrical)	Rs. 25000/- (Rupees Twenty Five Thousand only) per month, per person

Note: Assistant Engineers retired from Government services who are holding Diploma will be treated at par with Graduate Engineers. Diploma holder with minimum 10 years relevant experience with a reputed construction company can be treated at par with Graduate Engineers for the purpose of such deployment subject to the condition that such diploma holders should not exceed 50% of requirement of degree engineer.

The details of appointed engineers/technical staffs have to be verified and approved by Engineer- in-charge

7. Scope of work

7.1 Project Brief: “Annual Operation and Maintenance Contract (AOMC) of 1 no.33/11 KV substation, 13 no’s 11/0.433 KV substations and PLC Panel, AMF panels & LT panels of all DG set and petty electrical works of substations, underground distribution system, feeder pillars installed in the campus including supply of day to day manpower for maintenance of street light & for metering works at campus of IIT Kanpur & Outreach Centre NOIDA.” as specified BOQ.

The scope of work is to execute some minor electrical repair works of urgent nature within the cost and time limits as specified in Schedule F, Table 6. These works shall be carried out based on the pre-approved Quantity take off sheet in Institute formats by Executive Engineer through Engineer-in-Charge. It can also be used for any works of restoration because of a disaster in campus causing damage to institute infrastructure. This contract is also applicable for works related to emergency services/ works of institute importance/ works concerned to safety health and environment of campus community.

The contractor should always keep his establishment ready to commence the work as per the schedule of the contract. Work requests of urgent nature shall be started at the earliest after receiving orders from the Engineer in charge. But it should be documented with photo and video evidence for all hidden items. Submission of this evidence is mandatory for all works executed without a pre-approved quantity take off sheets.

The typical minor works taken up through these contracts within the buildings/ houses and their surroundings are as follows. But the list is not exhaustive. The agency must be prepared to take on any assigned works within the allotted time. A sample list is provided below:

1. Minor modification in electrical and civil components for setting up rooms/ common areas of the buildings/ houses/ quarters.
2. Earthing works.
3. Providing additional power points and network points in allotted spaces etc.
4. Replacement of defective cables, switch gears, light and electrical fittings, data points, fire alarm sensors or cables, LT cabling works etc.

Note: The scope of the works listed above is indicative only. The work must be done strictly as per the items decided for each individual work. This must be done as per item specifications listed in the BOQ and as per tender clauses.

7.2 Specifications for Electrical Works

7.2.1.1 Specifications Medium Voltage Switchgear

1. STANDARDS AND CODES

The following Indian Standard Specifications and Codes of Practice will apply to the equipment and the work covered by the scope of this contract. In addition the relevant clauses of the Indian Electricity Act 1910 and Indian Electricity Rules 1956 as amended upto date shall also apply. Wherever appropriate Indian Standards are not available, relevant British and/or IEC Standards shall be applicable.

BIS certified equipment shall be used as a part of the Contract in line with Government regulations. Necessary test certificates in support of the certification shall be submitted prior to supply of the equipment.

It is to be noted that updated and current Standards shall be applicable irrespective of those listed below.

Low voltage Switchgear and Control gear specifications IS 13947 :
1993 IS 61439

Part I – General

Part 2 – Circuit

Breakers Part 3 – Switch

Fuse Units

Part 4 – Contactors and Motor Starters

Part 5 – Control Circuit Devices

Electrical Relays for power system protection IS 3231 : 1986

Low voltage Switchgear and Control gear assemblies IS 8623 : 1993

Marking of Switchgear busbars IS 11353 : 1985

Degree of Protection of Enclosures for

low voltage switchgear IS 2147 : 1962

Code of Practice for selection, installation and
maintenance of Switchgear IS 10118 : 1982

2. SWITCH FUSE UNITS

2.1 Switch fuse units, incorporated in switchboards wherever required shall conform in all respects to IS 13947 : 1993. Switch fuse units shall be suitable for 415 Volts 3 Phase 50 HZ AC supply and shall be suitable for AC - 23 A duty.

Unit housing shall be of robust construction designed to withstand arduous conditions. Sheet steel used shall be given rigorous rust proofing treatment before fabrication and painting. Units shall have double break per phase in order to isolate fuse links when the switch is in OFF position.

Operating mechanism of units shall be crisp and positive in action with quick-make and quick-break silver plated contacts. Operating handle shall be suitable for rotary operation unless otherwise specified. Position of handle such as ON and OFF shall be clearly indicated.

All live parts inside the switch fuse units shall be shrouded to prevent any accidental contact.

All the terminals shall be liberally designed. All units above 100 A shall be provided with integral cable sockets.

All switch units shall be provided with suitable interlocks such that the door of the switchboard panel shall not open unless the switch is in OFF position. Provision for padlocking the switch in OFF position shall also be provided.

Routine and type tests as per IS 13947 : 1993 shall be conducted at works and test certificates furnished.

3. MOULDED CASE CIRCUIT BREAKERS

i) Moulded case circuit breakers (MCCB) or fuse free breakers, incorporated in switchboards wherever required, shall conform to IS 13947 : 1993 in all respects. MCCBs shall be suitable either for single phase 240 Volts or 3 Phase 415 Volts AC 50 HZ supply.

ii) MCCB cover and case shall be made of high strength heat resisting and flame retardant thermosetting insulating material. Operating handle shall be quick make/break, trip - free type. Operating handle shall have suitable ON, OFF and TRIPPED indicators. Three phase MCCBs shall have a common handle for simultaneous operation and tripping of all the three phases. Suitable arc extinguishing device shall be provided for each contact. Tripping unit shall be of thermal/magnetic type provided on each pole and connected by a common tripe bar such that tripping of any one pole causes three poles to open simultaneously. Thermal/magnetic tripping device shall have IDMT characteristics for sustained over loads and short circuits.

iii) Contact trips shall be made of suitable arc resistant sintered alloy. Terminals shall be of liberal design with adequate clearances.

iv) MCCBs shall be provided with following accessories, if specified in drawings/schedule of quantities :

- Under voltage trip
- Shunt trip
- Alarm switch
- Auxiliary switch

v) MCCBs shall be provided with following interlocking devices for interlocking the door a switch board.

- Handle interlock to prevent unnecessary manipulations of the breaker.

- Door interlock to prevent door being opened when the breaker is in ON position
- Deinterlocking device to open the door even if the breaker is in ON position.

MCCBs shall have rupturing capacity as specified in drawings/schedule of quantities.

4. METERING, INSTRUMENTATION AND PROTECTION.

The switchboard shall have required current and potential transformers as per schedule of quantities for metering and protection. The transformers shall comply to relevant ISS and class of accuracy required for metering and protection. Separate sets of CTs shall be provided for metering and protection.

4.1 Current Transformers

C/Ts shall conform to IS 2705 (part -I, II and III) in all respects. All C/Ts used for medium voltage application shall be rated for 1 kV. C/Ts shall have rated primary current, rated burden and class of accuracy as specified in schedule of quantities/drawings. Rated secondary current shall be 5A unless otherwise stated. Minimum acceptable class for measurement shall be class 0.5 to 1 and for protection class SP 10. C/Ts shall be capable of withstanding magnetic and thermal stresses due to short circuit faults of 31 MVA on medium voltage. Terminals of C/Ts shall be paired permanently for easy identification of poles. C/Ts shall be provided with earthing terminals for earthing chassis, frame work and fixed part of metal casing (if any). Each C/T shall be provided with rating plate indicating:

- Name and make
- Serial number
- Transformation ratio
- Rated burden
- Rated voltage
- Accuracy class

CTs shall be mounted such that they are easily accessible for inspection, maintenance and replacement. Wiring for CT shall be with copper conductor PVC insulated wires with proper termination works and wiring shall be bunched with cable straps and fixed to the panel structure in a neat manner.

4.2 Potential Transformer

PTs shall conform to IS 3156 (Part-I,II and III) in all respects.

4.3 Measuring Instruments

Direct reading electrical instruments shall conform to IS 1248 or in all respects. Accuracy of direct reading shall be 1.0 of voltmeter and 1.5 for ammeters. Other instruments shall have accuracy of 1.5. Meters shall be suitable for continuous operation between -10^o C and +50^oC. Meters shall be flush mounting and shall be enclosed in dust tight housing. The housing shall be of steel or phenolic mould. Design and manufacture of meters shall ensure prevention of fogging of instrument glass. Pointer shall be black in colour and shall have Zero position adjustment device operable from outside. Direction of deflection shall be from left to right. Suitable selector switches shall be provided for ammeters and volt meters used in three phase system. The rating type and quantity of meters, instruments and protective

device shall be as per Schedule of Quantities /drawings

4.3.1 Ammeters

Ammeters shall be of moving iron type. Moving part assembly shall be with jewel bearings. Jewel bearings shall be mounted on a spring to prevent damage to pivot due to vibrations and shocks. Ammeters shall be manufacture and calibrated as per IS 1248

Ammeters shall normally be suitable for 5 A secondary of current transformers.

Ammeters shall be capable of carrying substantial over loads during fault conditions.

4.3.2 Voltmeters

Voltmeters shall be moving iron type range of 3 phase 415 volt voltmeters shall be 0-500. Volt meters shall be provided with protection fuse.

4.3.3 Watt meter

Wattmeter shall be of 3 phase electro dynamic type and shall be provided with a maximum demand indicator if required.

4.3.4 Power factor meters

3 phase power factor meters shall be of electro dynamic type with current and potential coils suitable for operation with current and potential transformers provided in the panel. Scale shall be calibrated for 50% lag - 100% - 50% readings. Phase angle accuracy shall be $\pm 4^\circ$.

4.3.5 Energy and reactive power meters

Trivector meters shall be two element, integrating type, KWH, KVA, KVARH meters. Meters shall conform to IEC 170 in all respects. Energy meters, KVA, and KVARH meters shall be provided with integrating registers. The registers shall be able to record energy conception of 500 hours corresponding to maximum current at rated voltage and unity power factor. Meters shall be suitable for operation with current and potential transformers available in the panel.

4.4 Relays

Protection relays shall be provided with flag type indicators to indicate cause of tripping. Flag indicators shall remain in position till they are reset by hand reset. Relays shall be designed to make or break the normal circuit current with which they are associated. Relay contacts shall be of silver or platinum alloy and shall be designed to withstand repeated operation without damage. Relays shall be of draw out type to facilitate testing and maintenance. Draw out case shall be dust tight. Relays shall be capable of disconnecting faulty section of network without causing interruption to remaining sections. Analysis of setting shall be made considering relay errors, pickup and overshoot errors and shall be submitted to Engineer-in-Charge for approval.

4.4.1 Over current relays

Over current relays shall be induction type with inverse definite minimum time lag characteristics. Relays shall be provided with adjustable current and time settings. Setting for current shall be 50 to 200 % insteps of 25%. The IDMT relay shall have time lag (delay) of 0 to 3 seconds. The time setting multiplier shall be adjustable from 0.1 to unity. Over

current relays shall be fitted with suitable tripping device with trip coil being suitable for operation on 5 Amps.

4.4.2 Earth fault relay

Same as over current relay excepting the current setting shall be 10% to 40% in steps of 10%.

4.4.3 Under voltage relay

Under voltage relays shall be of induction type and shall have inverse limit operation characteristics with pickup voltage range of 50 to 90% of the rated voltage.

4.5 Power factor correction capacitors

Power factor correction capacitors shall conform to IS 2834 in all respects. Approval of insurance association of India shall be obtain if called for. Capacitors shall be suitable for 3 phase 415 volts 50 HZ supply and shall be available in single and three phase units of 5,10,15,20,25

and 50 kVAR sizes as per requirements. Capacitor shall be usable for indoor use, permissible overloads being as below.

- Voltage overloads shall be 10% for continuous operation and 15% for six hours in a 24 hours cycle.
- Current overloads shall be 15 % for continuous operations and 50% for six hours in a 24 hours cycle.
- Over load of 30% continuously and 45% for six hours in a 24 hours cycle.

Capacitors shall be hermetically sealed in sturdy corrosion proof sheet steel containers and impregnated with non-inflammable synthetic liquid. Every element of each capacitory unit shall be provided with its own built in silvered fuse. Capacitors shall have suitable discharge device to reduce the residual voltage from crest value of the rated voltage to 50 volts or less within one minute after capacitor is disconnected from the source of supply. The loss factor of capacitor shall not exceed 0.005 for capacitors with synthetic impregnates The capacitors shall withstand power frequency test voltage of 2500 volts AC for one minute. Insulation resistance between capacitors terminals and containers when a test voltage of 500 volts DC is applied shall not be less than 50 meg.ohms.

5. MEDIUM VOLTAGE SWITCH BOARDS

5.1 GENERAL

- All medium voltage switchboards shall be suitable for operation at three phase/three phase 4 wire, 415 volt, 50 Hz, neutral grounded at transformer system with a short circuit level withstand of 31 MVA at 415 volts or as per schedule of quantities.
- The Switch Boards shall comply with the latest edition with upto date amendments of relevant Indian Standards and Indian Electricity Rules and Regulations.

5.2 SWITCH BOARD CONFIGURATION

- The Switch Board shall be configured with Air Circuit Breakers, MCCB's, and other equipment as called for in the Schedule of Quantities.
- The MCCB's shall be arranged in multi-tier formation whereas the Air Circuit Breakers shall be arranged in Single or Double tier formation only to facilitate operation and

maintenance.

- The Switch Boards shall be of adequate size with a provision of 25% spare space to accommodate possible future additional switch gear.

5.3 EQUIPMENT SPECIFICATIONS

All equipment used to configure the Switch Board shall comply to the relevant Standards and Codes of the Bureau of Indian Standards and to the detailed technical Specifications as included in this tender document.

5.4 CONSTRUCTIONAL FEATURES

- The Switch Boards shall be metal enclosed, sheet steel cubicle pattern, extensible, dead front, floor mounting type and suitable for indoor mounting.
- The Switch Boards shall be totally enclosed, completely dust and vermin proof. Synthetic rubber gaskets between all adjacent units and beneath all covers shall be provided to render the joints dust and vermin proof to provide a degree of protection of IP 42. All doors and covers shall also be fully gasketed with synthetic rubber and shall be lockable.
- The Switch Board shall be fabricated with CRCA Sheet Steel of thickness not less than 2.0 mm and shall be folded and braced as necessary to provide a rigid support for all components. The doors and covers shall be constructed from CRCA sheet steel of thickness not less than 1.6 mm. Joints of any kind in sheet metal shall be seam welded and all welding slag ground off and welding pits wiped smooth with plumber metal.
- All panels and covers shall be properly fitted and square with the frame. The holes in the panel shall be correctly positioned.
- Fixing screws shall enter holes tapped into an adequate thickness of metal or provided with hank nuts. Self-threading screws shall not be used in the construction of the Switch Boards.

5.5 SWITCHBOARD DIMENSIONAL LIMITATIONS

- A base channel 75 mm x 5 mm thick shall be provided at the bottom.
- A minimum of 200 mm blank space between the floor of switch board and bottom most unit shall be provided.
- The overall height of the Switch Board shall be limited to 2300 mm
- The height of the operating handle, push buttons etc shall be restricted between 300 mm and 1800 mm from finished floor level.

5.6 SWITCH BOARD COMPARTMENTALIZATION

The Switch Board shall be divided into distinct separate compartments comprising

- A completely enclosed ventilated dust and vermin proof bus bar compartment for the horizontal and vertical busbars.
- Each circuit breaker, and MCCB shall be housed in separate compartments enclosed on all sides.
- Sheet steel hinged lockable doors for each separate compartment shall be provided and duly interlocked with the breaker/switch fuse unit in "on" and "off" position.

- For all Circuit Breakers separate and adequate compartments shall be provided for accommodating instruments, indicating lamps, control contactors and control fuses etc. These shall be accessible for testing and maintenance without any danger of accidental contact with live parts of the circuit breaker, busbars and connections.
- A horizontal wire way with screwed cover shall be provided at the top to take interconnecting control wiring between vertical sections.
- Separate cable compartments running the height of the Switch Board in the case of front access Boards shall be provided for incoming and outgoing cables.
- Cable compartments shall be of adequate size for easy termination of all incoming and outgoing cables entering from bottom or top.
- Adequate and proper support shall be provided in cable compartments to support cables.
- Following minimum clearances to be maintained after taking into consideration connecting bolts, clamps etc.
 - i) Between phases 32 mm
 - ii) Between phases and neutral 26 mm
 - iii) Between phases and earth 26 mm
 - vi) Between neutral and earth 26 mm

5.7 SWITCH BOARD BUS BARS

- The Bus Bar and interconnections shall be of electrolytic Copper/Aluminum and of rectangular cross sections suitable for full load current for phase bus bars and half rated current for neutral bus bar. The maximum current density for copper shall be 1.2 amps per sq. mm. and for Aluminum shall be 0.8 amp per Sq. mm. and suitable to withstand the stresses of a 31 MVA fault level or at 415 volts for 1 second or as per schedule of quantities.
- The bus bars and interconnections shall be insulated with insulation tape/ fiber glass.
- The bus bars shall be extensible on either side of the Switch Board.
- The bus bars shall be supported on non-breakable, non-hygroscopic insulated supports at regular intervals, to withstand the forces arising from a fault level of 31 MVA at 415 volts for 1 second.
- All bus bars shall be colour coded.
- All bus bar connections in Switch Boards shall be bolted with brass bolts, washers and nuts.

5.8 SWITCH BOARD INTERCONNECTIONS

- All connections between the bus bars/Breakers/ shall be through solid copper strips of adequate size to carry full rated current and PVC/fiber glass insulated.

5.9 DRAW-OUT FEATURES

Air Circuit Breakers shall be provided in fully draw out cubicles. These cubicles shall be such that draw out is possible without disconnection of the wires and cables. The power and control circuits shall have self-aligning and self-isolating contacts. The fixed and moving contacts shall

be easily accessible for operation and maintenance. Mechanical interlocks shall be provided on the draw out cubicles to ensure safety and compliance to relevant Standards. The MCCB's shall be provided in fixed type cubicles.

5.10 INSTRUMENT ACCOMMODATION

- Instruments and indicating lamps shall not be mounted on the Circuit Breaker Compartment door for which a separate and adequate compartment shall be provided and the instrumentation shall be accessible for testing and maintenance without danger of accidental contact with live parts of the Switch Board.
- For MCCB's instruments and indicating lamps can be provided on the compartment doors.
- The current transformers for metering and for protection shall be mounted on the solid copper/aluminum busbars with proper supports.

5.11 WIRING

All wiring for relays and meters shall be with PVC insulated copper conductor wires. The wiring shall be coded and labelled with approved ferrules for identification. The minimum size of copper conductor control wires shall be 1.5 sq. mm.

5.12 CABLE TERMINATIONS

- The cable terminations of the Circuit Breakers shall be brought out to terminal cable sockets suitably located at the rear of the panel.
- The cable terminations for the MCCB's shall be brought out to the rear in the case of rear access switchboards or in the cable compartment in the case of front access Switch Boards.
- The Switch Boards shall be complete with gland plates

5.13. SPACE HEATERS

The Switch Board shall have in each panel thermostatically controlled space heaters with a controlling 15 amp 230 volt switch socket outlet to eliminate condensation

5.14 EARTHING

A main earth bar of G.I shall be provided throughout the full length of the Switch Board with a provision to make connections to earth stations on both sides.

5.15 SHEET STEEL TREATMENT AND PAINTING

- Sheet Steel materials used in the construction of these units should have undergone a rigorous rust proofing process comprising of alkaline degreasing, descaling in dilute sulphuric acid and a recognised phosphating process or by using sand blasting method. The steel work shall then receive two coats of oxide filler primer before final painting. Castings shall be scrupulously cleaned and fettled before receiving a similar oxide primer coat.
- All sheet steel shall after metal treatment be spray or powder painted with two coats of shade 692 to IS 5 on the outside and white on the inside. Each coat of paint shall be properly stoved and the paint thickness shall be adequate.

5.16 NAME PLATES AND LABELS

Suitable engraved white on black name plates and identification labels of metal for all Switch Boards and Circuits shall be provided. These shall indicate the feeder number and feeder designation.

6. INSTALLATION

The foundations prepared as per the manufacturers drawings shall be levelled, checked for accuracy and the Switch Board installed. All bus bar connections shall be checked with a feeler gauge after installation. The cable end boxes shall be sealed to prevent entry of moisture. The main earth bar shall be connected to the sub-station earths.

A 15 mm thick rubber matting of approved make on a 100 mm high timber platform shall be provided in front of and along the full length of the Switch Board. The width of the matting shall be 1000 mm. The rubber mat shall withstand 15 KV for 1 minute and leakage current shall not exceed 160 mA/sq. meter.

After installation the Switch Board shall be tested as required prior to commissioning.

7. OUTDOOR TYPE DISTRIBUTION FEEDER PILLARS

The feeder pillar shall be of the floor mounting type, totally enclosed, and weather proof, conforming to ISI IP 54 incorporating phenolic moulded fuse fittings with high rupturing capacity cartridge fuse links having a certified rupturing capacity of not less than 35 MVA at 433 volts. The feeder pillar shall be suitable for 440 volts 3 phase 4 wires, 50 cycles AC supply.

The cubicle should be fabricated out of heavy gauge sheet steel of thickness not less than 2 mm thick with suitable side frame and stiffeners. Hinged doors of not less than 1.6 mm thick should be provided at the front and rear of the cubicle to provide access for installation, operation, tests and inspection. The rear door is provided to facilitate cable termination and the front door for inspection of fuses, to switch „ON“ and „OFF“ the switch as and when required. All doors should be fitted with dust excluding neoprene gaskets. The doors should also be fitted with suitable locking arrangement with lock to prevent unauthorized opening. The cubicle should be designed for mounting over cement concrete plinths by the roadside, and should be of substantial construction capable of withstanding the vibrations normally experienced due to vehicular traffic. The top of the feeder pillar is of slanting construction in all directions to prevent any collection of water due to rain. A gland plate is provided at the bottom of the feeder pillar (removable) for mounting the cable glands. The feeder pillar shall be fitted on an angle iron pedestal at the bottom covered with sheet metal from all the four sides which facilitates cable bending etc. specially with aluminum cables. Two lifting hooks shall be provided at the top. A door switch shall be provided in the feeder pillar so as to switch „ON“ and „OFF“ the lamp fixed in the brass batten holder below the top sheet of the pillar.

The sheet steel materials used in the construction of the cubicle should have undergone a rigorous rust proofing process comprising alkaline degreasing, descaling in dilute sulfuric acid solution and recognized phosphating process. After metal treatment, the interior of the cubicle should be painted with two coats of air-drying red lead primer followed by two coats of air drying anti-condensation paint. The exterior of the cubicle should be painted with two coats of staving red oxide primer followed by one coats of epoxy finishing paint. One final spray of epoxy paint shall be applied at the time of handing over the installation.

All the nuts, bolts shall be cadmium plated with spring washers. A minimum spacing from cable connection to the bottom of gland plate shall be 300mm.

The bus bars should be of electrical grade copper. They should be air insulated with adequate clearances between conductors and between conductors and earth. These should be colour coded to enable immediate identification of the phases and neutral. The current density for bus bars shall not be more than 1.0 amps per square mm. All bus bar joints and tapings should be of the clamped type as far as possible thereby avoiding drilling of holes on bus bars. The bus bars should be carried on supports made out of a suitable non-inflammable and non-hygroscopic material such as Hylam, Permali or Formics. Suitable insulating phase barriers should be provided to prevent accidental short-circuits during operation.

The fuse base contacts should be of copper comprising one top contact for bolting to the bus bar, one bottom contact for terminating the incoming or outgoing cable and a cable lug. The bottom contacts should be so designed that the cable tail from the cable gland to the cable lug is vertical and does not foul with any live parts in its run. The spacing between the respective fuse bases should not be less than 40mm.

The fuse carriers should be fitted as standard to all fuses to minimize accidental contact with live metal during inspection or maintenance. The carriers should be phenolic moulded, designed to accommodate HRC fuse-links and should incorporate a wedge action device for tightening the fuse-link to the base contact. This wedge action should be operated externally by insulated thumb screws giving uniformly high pressure contact and ensuring cool running under full load conditions, with positive location of the fuse-link tags on the base contact. The fuse-link shall not work loose due to vibration occurring from vehicular traffic.

A viewing aperture should be provided on the carrier to facilitate location of a „blown“ fuse. The fuse carriers should also be easily withdrawable in service. The design of the carrier should be such that carrier components do not carry any current and the contact is decidedly between fuse-link tag and base contact.

When incoming links are called for it should be possible to fit the carriers with solid links in lieu of fuses.

7.1 Specifications for LT Panel/ Switchgear

7.1.1 CONSTRUCTION:-

- Switchgear enclosure shall conform to the degree of protection IP4x minimum thickness of sheet metal used shall be 2 mm.
- The switchgear shall comprise a continuous line up of single / Multi-tire cubicles. The installations of circuit breakers however shall be limited to the bottom two tires only.
- The design shall be of fully compartmentalized execution with metal/ insulating portions. Working height shall be limited between 750 mm to 1800 mm from the floor level.
- Each breaker shall be housed in a separate cubicle, complete with an individual front access door; each vertical section shall have a removable back cover. All doors & covers shall be gasketed.
- Switchgear cubicle shall be so sized as to permit closing of the front access door when the breaker is pulled out to ISOLATED position.
- All switchgear, lamps & indicating instruments shall be flush mounted on the respective cubicle door whereas relays & other auxiliary devices of any may be mounted on a separate cubical.

7.1.2 BUS AND BUS TAPS

- The main buses & connections shall be of high conductivity aluminum alloy, as per IS : 5082 sized for specification current rating with maximum temperature limited to 85 degree C (i.e., 35 degree C rise over 50 degree C ambient). Bus bars shall be designed for a maximum current density of 0.8A/ sq.mm.
- All bus connections shall have adequate contact pressure which should be ensure by means of two bolt connections with plain & spring washers locknuts. Bimetallic connections between dissimilar metals.

- Bus connections shall be fully insulated for working voltage with adequate phase / ground clearances.
- Insulating sleeves for bus bars & surrounds for joints shall be provided.
- Bus insulator shall be flame-retardant, track resistant type with high creep age surface.
- All buses & connections shall be supported & braced to withstand the stresses due to maximum short circuit current & also to take care of any thermal expansion.
- Bus-bars shall be sleeved in colour coded manner for easy identification & so located that the sequence RYB shall be from left to right, top to bottom of front to rear, when viewed from the front of switchgear assembly.
- Bolted disconnected links shall be provided from all incoming & outgoing feeders for isolation of neutral, if necessary.

7.1.3 CIRCUIT BREAKER

- Circuit breaker shall be three poles, single throw, air breaker type with stored energy, trip free mechanism & shunt trip. The circuit breaker of the outgoing feeder shall have an in built microprocessor base release, short circuit, over current & earth fault protection release.
- Circuit breakers shall be draw out type, having SERVICE, TEST & ISOLATED position with positive indication for each position along with in built relay unit.
- Circuit breaker of identical rating shall be physically & electrically interchangeable.
- Circuit breaker shall be motor wound spring charged mechanism, motor voltage should be 240 V AC. For motor wound mechanism, spring charging shall take place automatically after each breaker closing operation. One open close-open operation of the circuit breaker shall be possible after failure of power supply to the motor. Power supply for this motor shall be taken from the output of auto changeover.
- Mechanical safety interlocking shall be provided to prevent the circuit breaker from being racked in or out of the service position when the breaker is closed.
- Automatic safety shutters shall be provided to fully cover the female primary disconnects when the breaker is withdrawn.
- Each breaker shall be provided with an emergency manual trip, mechanical ON-OFF indicator, an operation counter & mechanism charge/ discharge indicator.
- In addition to the auxiliary contacts required for normal breaker operation & indication, each breaker shall be provided with following for interlocking purpose:-

- a) Position/ cell switch with 4 NO. + 4 NC contacts. These shall be available as spare for automation work.

Control Supply:- 230V AC for closing,

Tripping & indication lamps.

Auxiliary switch, with 6 NO+ NC contact, mounted on the stationary portion of the switchgear & operated mechanically by a sliding level from the breaker, in SERVICE position. These shall be available as spare for automation work.

7.1.3.1 Limit / auxiliary switches shall be convertible type, that is, suitable for changing NO contact to NC & Vice-Versa.

7.1.3.2 Moulded Case Circuit Breakers

Moulded case circuit breakers (MCCB) or fuse free breakers, incorporated in switchboards wherever required, shall conform to IS 13947: 1993 & IEC 61439 in all respects. MCCBs shall be suitable either for single phase 240 Volts or 3 Phase 415 Volts AC 50 HZ supply.

MCCB cover and case shall be made of high strength heat resisting and flame retardant thermosetting insulating material. Operating handle shall be quick make/break, trip - free type. Operating handle shall have suitable ON, OFF and TRIPPED indicators. Three phase MCCBs shall have a common handle for simultaneous operation and tripping of all the three phases. Suitable arc extinguishing device shall be provided for each contact. Tripping unit shall be of microprocessor based electronic type provided on each pole and connected by a common tripe bar such that tripping of any one pole causes three poles to open simultaneously. Electronic tripping device shall have IDMT characteristics for sustained over loads and short circuits.

Contact trips shall be made of suitable arc resistant sintered alloy. Terminals shall be of liberal design with adequate clearances.

MCCBs shall be provided with following accessories, if specified in drawings/schedule of quantities:

- Shunt trip
- Alarm switch
- Auxiliary switch

MCCBs shall be provided with following interlocking devices for interlocking the door a switch board.

- Handle interlock to prevent unnecessary manipulations of the breaker.
 - Door interlock to prevent door being opened when the breaker is in ON position
 - De interlocking device to open the door even if the breaker is in ON position. MCCBs shall have rupturing capacity as specified in drawings/schedule of quantities.
- i) MCCB shall be triple pole air break.
 - ii) The MCCB shall have a quick - make, quick - break mechanism operated by a suitable external rotary handle, complete with position indicator this handle shall have provision for pad locking in ON & OFF position.
 - iii) MCCB should have microprocessor base electronic release with over current, earth fault & short circuit protection equivalent to L&T „D“ since with RC-10 release.

7.1.3.3 CONTROL & INDICATION :-

The circuit breaker shall be wired up for both local & remote operation. A local-remote selector switch shall be provided for this purpose. Each breaking cubicle shall be equipped with following:-

7.1.3.3.1 One (1) Test- neutral - service selector switch stay put type with test/ service position pistol grip handle & key interlock for breaker marked 'E'.

7.1.3.3.2 Two (2) heavy duty, oil tight push buttons for TRIP & CLOSE.

7.1.3.3.3 Three (7) LED indicating lights on front of compartment:-

GREEN : Breaker open & spring charged

RED : Breaker close

AMBER : Trip / circuit healthy condition WHITE :

Control supply failure

Phase indication : One Red, One Blue & One Yellow

O & 1 NC should be provided for status monitoring of the remote / local position.

7.1.3.3.4 Lamps shall be low watt, LED type lamp & lens shall be replaceable from the front.

7.1.3.3.5 The general scheme of connections for control, interlock & protection shall got approved before fabrication of panel.

7.1.3.4 FUSES :-

7.1.3.4.1 Fuses shall be HRC, preferably link type with a minimum interrupting capacity equal to the short circuit current.

7.1.3.4.2 Fuses shall be furnished complete with fuse base & fittings of such as to permit easy & safe replacement of fuse element. Visible indicated indication shall be provided on blowing of the fuse.

7.1.3.5 CURRENT TRANSFORMER :-

Current transformer shall be cast- resin type. All secondary connections shall be brought out to terminal blocks where or delta connection will be made.

7.1.3.5.1 Ratings :

- for incomers and bus coupler

1500-750/5+5 : 3 sets

- For out goings :

800-400/5+5 : 4 sets

600-300/5+5 : 4 sets

400-200/ 5+5 : 2 sets

7.1.3.5.2 Accuracy class of the current transformers shall be :-

- a. Class 5 P10 for other relaying (protection).
- b. Class 1.0, ISF < 5 for metering.

7.1.3.6 RELAYS :-

7.1.3.6.1 Relays shall be of draw out design with built in testing facilities. Small auxiliary relays may be in non-draw out execution.

7.1.3.6.2 Relay shall be rated for operation on 5 Amp secondary current & 110 / 220 V secondary voltage; number & rating of relay contacts shall suit the job requirements.

7.1.3.6.3 The contractor shall furnish, install & co-ordinate all relays to suit the requirements of protection & interlock & as broadly indicated in the annexure & drawings.

7.1.3.7 METERS (digital display):-

7.1.3.7.1 Indicating instruments shall be switch board type & accuracy class of 2% .

7.1.3.7.2 All Digital Watt-hour meter shall be provided, alternatively, they may have test block to facilitate testing of meter without disturbing C.T. or V.T. secondary connections.

7.1.3.7.3 Each breaker shall be with volt meter, amp meter with selector switches & KWH meters. Only outgoing feeders will be relaxed from voltmeters.

7.1.3.8 SECONDARY WIRING :-

- i. The switchgear shall be fully wired at the factory to ensure proper functioning of control, protection, & interlocking schemes.
- ii. Fuses & links shall be provided to permit individual circuit isolation from bus wires without disturbing other circuits. All spare contacts of relays, switches & other devices shall be wired upto terminal blocks.
- iii. Wiring shall be done with FRLS PVC flexible, 650V grade, PVC insulated switchboard wires with solid copper conductors of 2.5 sq.mm for voltage circuits along with numbered ferrules.
- iv. Each wire shall be identified, at both ends, with permanent markers bearing wire numbers as per contractors wiring diagrams.
- v. Wire terminations shall be made with crimping type connectors with insulating sleeves. Wire shall not be spliced between terminals.

11 TERMINAL BLOCKS

- i) Terminal blocks shall be 660V grade box clamp type with marking strips, similar to ELMEX 10 sq.mm of equal. Terminals for C.T. secondary leads shall have provision for shorting.
- ii) Not more than two wires shall be connected to any terminals equal in number to 20% active terminals shall be furnished.

- iii) Terminal blocks shall be located to allow easy access. Wiring shall be so arranged that individual wires of an external cable can be connected to consecutive terminals.

12 CABLE TERMINATION :-

- i) Switchgear shall be designed for cable entry from the bottom. Sufficient space shall be provided for each of termination & connection.
- ii) All provision & accessories shall be furnished for termination & connection of cables, including removable gland plates, cable supports, crimp type tinned copper/ aluminum lugs, brass compression gland with tapered washer (power cable only) & terminal block.
- iii) Gland plate shall be minimum 4 mm thick.

13 BUS DUCT CONNECTION :-

- i) Bus duct connections, where specified shall be furnished along with transportation of panel. Bus duct connections shall be generally from the top.
- ii) All connecting bus work shall have the same continuous rating as associated switchgear bus & shall be fully braced for the listed short circuit current.
- iii) All provision such as matching flange & other accessories shall be furnished for connection to bus duct if any, being supplied by this purpose will be furnished by contractor.

14 GROUND BUS :-

- i) A ground bus, rated to carry maximum fault current, shall extend full length of the switchgear.
- ii) The ground bus shall be provided with two bolt drilling with GI bolts & nuts at each to receive 50 x 6mm GI flat.
- iii) Each stationary unit shall be connected directly to the ground bus. The frame of each circuit breaker & draw out VT unit shall be grounded through heavy multiple contacts at all times except when the primary disconnecting devices are separated by a safe distance.
- iv) Whenever the schematic diagrams indicate a definite ground at the switchgear, a single wire for each circuit thus grounded shall be run independently to the ground bus & connected thereto.
- v) C.T. & V.T. secondary neutrals shall be earthed through removable links so removed without disturbing others.

15 NAME PLATES :-

- i) Nameplates of approved design shall be furnished at each cubicle & at each instrument & device mounted on or inside the cubicle.
- ii) The material shall be lamicoid or approved equal, 3mm thick with white letter on black background.
- iii) The name plate shall be held self-tapping screws. Nameplate size shall be minimum 20

x 75 mm for instrument device & 40 x 150mm for panels.

iv) Caution notice suitable metal plate shall be affixed at the back of each vertical panel.

16. SPACE HEATERS PLUG SOCKETS :-

i) Each vertical section shall be provided with thermostat controlled space heater & 5A, 3 pin plug socket.

ii) Cubical heater, plug-socket circuit shall have individual switch fuse units.

17. A.C. / D.C. POWER SUPPLY :-

i) The following power supplied will be made available to the switchgear :

240 A.C. Supply : Two Feeders From these two single-phase feeders a reliable 240V, 1 Ph. AC bus shall be obtained using auto changeover scheme. The necessary equipment's for this scheme should be indicated.

The DC supply required for control purposes is to be obtained in each module through a rectifier arrangement, which will convert the 250V AC supply to 110V DC. The equipment necessary for this rectification including protective relaying as per the approved drawing are also to be included.

ii) Isolating switch fuse units shall be provided at each switchgear for the incoming supplies, 2-pole, single throw for A.C. & 2-pole, double throw for D.C. Bus-wires of adequate capacity shall be provided to distribute the incoming supplies to different cubicles. Isolating switch- fuse units shall be provided at each cubicle for AC/DC supplies.

iii) AC load shall be so distributed as to present a balance loading on three-phase supply system.

18. PAINTING :-

i) All surfaces shall be sand blasted, pickled & grounded as required to produce a smooth, clean surface free of scale, grease & rust.

ii) After cleaning, the surface shall be given a phosphate coating followed by 2 coats of high quality prime & stove after each coat.

iii) The switchgear shall be finished in light gray (IS shade # 631) with two coats of synthetic enamel paint.

iv) Sufficient quantity of touch- up paint shall be furnished for application at site.

19. SPECIAL TOOLS & TACKLES :-

i) A set of special tools & tackle (manual charging handle & operating handle trolley for lifting outside breaker for maintenance) which are necessary or convenient for erection, commissioning, maintenance & overhauling of the equipment shall be supplied.

ii) The tools shall be shipped in separate containers (Tool Box) clearly marked with the name of the equipment for which they are intended.

20. SPARES:-

- i) The bidder shall submit list of recommended spare parts for three (3) years satisfactory & trouble-free operation indicating the itemized price of each item of the spares.

21. DRAWINGS, DATA & MANUALS :-

- i) To be furnished for approval after award of work.
 - a. General arrangement drawing showing constructional features, space required in front for withdrawals, power & control cable entry points etc.
 - b. Details of materials with specifications.
 - c. Typical foundation plan & loading.
 - d. Typical breaker control schematic.
 - e. Matching flanges & terminals for the bus termination.
 - f. Type test reports on circuit breaker.
 - g. Technical leaflet on
 - h. Circuit breaker
 - i. Instrument transformer
 - j. Relays, meters, switches etc.
 - k. Single line diagram
 - l. Control schematic
 - m. Wiring diagram

22. Instruction manuals of switchgear & individual equipment:-

The manual shall clearly indicate the installation method, checkup & tests to be carried out before commissioning of the equipment.

- 23.** The bidder may note that the drawings, data & manuals listed here in are minimum requirements only the bidder shall ensure that the other necessary write-ups, curves & information required to fully describe the equipment are submitted with his bid.

CIRCUIT BREAKER

Make - As per approved make.

Type - Microprocessor release air-circuit breaker

Rated voltage - 415 Volts

Rated frequency - 50 Hz

Rated current - **1600/(Icu=Icf=1sec 50 kA)**

800A(Icu=Icf=1sec 50 kA)

No. of pole - 3

Aux. Voltage for trip/close coil - 110 V DC

Motor for spring charging Voltage- 240 V AC

Protection unit - Equivalent to SR-18G with fault indication & thermal masonry.

Interlocking arrangement electrically & mechanically with bus coupler & incomer.

PROTECTION (FOR LT SUPPLY 415V PANEL)

The minimum protections to provided for different type of circuit are listed below:-

INCOMING FEEDER:-

2 over current +E/F relay microprocessor based along with the element of instantan- eous o/c & E/F protection.

BUS COUPLER:-

3 O/C relay microprocessor based

All inverse time O/C relay shall be 3 sec. Version.

All definite time O/C relay shall have adjustable time range of 0-6 Sec.

Apart from protection relays each breaker shall be provided with auxi. Contact multiplier relay, anti-pumping relay, trip supervision relay, lockout relay test terminal block. These relay shall be hand reset.

7.1.4 Specifications for LT Bus Duct

7.1.4.1 Design Criteria

- The LT non phase segregated bus duct serve as a interconnection between the LT switchgear and outdoor LT transformer.
- The LT bus ducts will be installed partially indoor and partially outdoor in a hot, humid and tropical atmosphere. All panels associated.
- Bus duct associated equipment and wiring shall be provided with tropical finish to prevent fungus growth. All ventilation openings shall be screened and drains shall be filtered to prevent entrance of dust and insects.
- For continuous operation at specified ratings, temperature rise of the bus duct and auxiliary equipment shall be limited to the site permissible values stipulated in relevant standards and / or this specification.

- Bus duct and auxiliary equipment shall be capable of withstanding the mechanical forces and thermal stresses of the short circuit currents listed in the annexure without any damage or deterioration of material.
- The bus ducts shall be self-cooled and shall not be equipped with blower or any other type of forced ventilation.
- Bus duct enclosure shall be of sheet steel.

1. Specific Requirements.

- **General**
- The LT bus duct shall be non-phase segregated enclosure type.
- The layout of the bus ducts shall be generally in accordance with enclosed drawings. The details shown however are only typical. Bidder may propose changes to suit his particular design.
- All parts and accessories shall have appropriate match mark and part numbers for easy identification and installation at site.

2. Enclosure

- Phase shall be enclosed in weather proof, dust-tight, enclosure of sheet steel fabricated type conforming to degree of protection of IP 55.
- Circumferential neoprene rubber gaskets shall be provided for dust tight joints with adjacent enclosure section.
- The bus enclosure shall have extended bellows or equivalent means to allow for temperature changes and vibrations. Flexible joints shall be provided in enclosures at all points where the bus duct terminates at equipment to withstand vibration, expansion/contraction and at suitable intervals in any straight run of the bus duct where expansion and contraction would otherwise result in stress in the supporting structures.
- All outdoor bus enclosures shall be so designed & constructed as to prevent accumulation of rain water on top sheet. Similarly all gasketed flanged joints shall be suitably protected against direct splashing of rain water in case of outdoor runs.
- Suitable inspection openings shall be provided for access to support insulators, bus joints, transformer terminals, switchgear terminals etc. All inspection openings shall have reliable sealing arrangement with neoprene gaskets.
- Seal-off bushings complete with wall frame and support plates shall be provided where the bus duct penetrates the building wall. The seal is to prevent free exchange of air between indoor and outdoor portions of the bus duct.
- Silica-gel breather shall be provided on both indoor and outdoor portions of the bus duct.
- Filtered drains for drainage of condensate shall be provided at the lowest points and at such locations where accumulation of condensate can be expected.

- Shipping length of the bus duct shall be not more than three (3) meters in length.

4. Bus Conductor

- The bus conductor shall be of high conductivity, aluminium alloy, supported on wet process porcelain insulators.
- The bus conductor shall be designed for bolted connections throughout the run.
- Flexible connections shall be provided between bus sections to allow for expansion and contraction of the conductor. Flexible connections shall also be provided at all equipment terminations.
- All contact surfaces shall be silver plated to ensure an efficient and trouble-free connection. All connection hardware shall be non-magnetic and shall have high corrosion resistance.

5. Disconnect Link

- Removable bolted disconnect link shall be provided in the bus where shown on the drawing for the purpose of isolation.
- Disconnect link shall consist of a removable section of conductor and shall be so constructed as to permit easy removal or reinsertion without alignment difficulties.
- The bus on both sides of the link shall be rigidly supported so that the disconnect link is equal in mechanical strength to any other section of the bus.
- A minimum clearance of 300mm (12") shall be provided between the disconnected bus sections with the link removed.

6. Insulators

- Bus support insulators shall be interchangeable, high creep, high strength, wet process, fine glazed porcelain. Alternatively good quality cast resin insulators.
- Insulator shall be mounted in such a way so as to permit easy removal or replacement without disassembly of the bus. The insulator mounting plate shall be designed for cantilever loading to withstand the short circuit.
- The conductor shall be fastened on the insulator through fixed and slip joints so as to allow conductor expansion or contraction without straining the insulator.
- Space heater shall be provided preferably located near to each insulator to avoid moisture condensation within bus-duct. No and wattage rating of space heater shall be decided by the tenderer.

7. Connections & Terminations

- All matching flanges seal off bushings, gaskets, fittings, hardware and supports required for termination of the bus duct at the switchgears, transformers shall be furnished.
- In this connection the contractor is required to coordinate through the Engineer in Charge with the suppliers of the switchgear, transformers with regard to connection details, mechanical and thermal stresses.

- Flexible connections both for conductor and enclosure shall be furnished.
 - At all equipment termination to provide for misalignment upto 25mm (1”) in all directions.
8. Between bus duct supported from building steel to prevent transmission of vibration.
- The equipment terminal connections shall be readily accessible and shall provide sufficient air gap for safe isolation of equipment during testing.
 - If the material of bus conductor and that of the equipment terminal connectors are different then suitable bi-metallic connectors shall be furnished.

9. Grounding

- A separately run 50x6mm GI flat suitably clamped along the enclosure shall be used as the ground bus. All parts of the bus enclosure supporting structures and equipment frames shall be bonded to above ground bus.
- Ground pad shall be bolted type to accommodate 50x6mm galvanized steel flats. Complete with suitable tapped holes, bolts and washers.

10. Supporting Structures

- All supporting structures required for hanging and/or supporting the complete bus duct shall be furnished. These include all members, indoor/outdoor posts, bolts, shims, base plate, beams, hangers, brackets, bracings and hardware.
- All buses shall be adequately supported and braced to successfully withstand normal operation, vibration, thermal expansion, short circuit forces and all specified design loads.
- Supports shall be designed to provide tolerance of plus/minus 12mm (1/2”) in the horizontal and vertical directions.
- All steel members shall be hot dip galvanized after fabrication. All hardware shall be of high strength steel with weather resistant finish.
- Concrete foundation, building steel, concrete, inserts/plates will be provided by the owner.
- The contractor shall co-ordinate with the owner for this purpose giving well in advance the details of his requirements so as to enable the owner to arrange for the same in time.

11. Wiring

- All wiring for space heaters shall be done with insulated stranded copper conductor of not less than 2.5 sqmm cross section. Each wire shall be identified at both ends with wire designation as per contractor’s wiring diagram and shall be brought out to a terminal box outside the bus duct.
- Terminal blocks shall be box-clamp type Elemex 10 sq.mm with marking strips or approved equal.
- At least 20% spare terminals shall be furnished in the terminal block.

3. *Name Plate*

- Suitable name plate shall be furnished with each piece of equipment.
- Materials for name plate shall be plastic/lamicoid, 3mm thick, using white letters on black background.

5. *Finish*

- Except for supporting steel structures which shall be galvanized, all equipment shall be finished with an undercoat of high quality primer followed by two coats of synthetic enamel paints.
- The interior surface finish shall be as per manufacturer's standard. The shade of exterior surface finish will be battle ship gray shade 632 as per IS-5.
- Pre-treatment consisting of degreasing, de-rusting etc. shall be done on all fabricated parts before painting or galvanizing.
- Paints shall be carefully selected to withstand heat and weather conditions. The paint shall not scale-off or crinkle or get removed by abrasion due to normal handling.
- Sufficient quantities of all paints and preservatives required for touching up at sites shall be furnished.

4. *Handling of cable drum and cable:*

- Rolling of drum shall be avoided as far practicable. For short distance, the drums may be rolled they are rolled slowly and in proper direction as marked on the drum. In absence of any identification. The drums may be rolled in the same direction as it was rolled during taking up the cable.
- For unreeling the cable, the drum shall be mounted on jacks or on cable well. The spindle shall be strong enough to carry the weight without bending. The drum shall be rolled on the spindle slowly, so that cable should come out over the drum & not below the drum.
- While laying cable, cable shall be used at an interval of 2 meters. The cable shall be pushed over the roller by a gang of people positioned in between rollers. The cable shall not be pulled from the end without laying intermediate pushing arrangement. Bending radius shall not be less than what is specified by manufacturer.

15. *Cable laying:*

- Cables shall generally be installed in cable trays except for some short runs in buried formation or in conduit / pipe for protection or crossing. Multi core power cable laid on trays & riser shall be neatly dressed & clamped with fabricated 25 x 3 mm G.S flat or cable tray at an interval of maximum 1 meter for vertical / inclined run & 1.50 meter for horizontal run. Control cables may be laid in single layer with touching formation. Power & control cables shall be claimed in separate group. Power & control cables shall not be laid in a common tray excepting in very special case where a gap of 150 mm shall be maintained between power & control cables.
- H.T & L.T power cables shall be laid in cable trays in single layer & with spacing equal to

the diameter of cable.

- Control cable can be laid up to a maximum of three layers in each tray.
- Both power & control cables shall be clamped to the trays rungs by means of clamp made up to 25 x 3 mm fabricated G.S flat at an interval of 1500 mm for horizontal run & 1000 mm for vertical / inclined cable run.
- The cable trays shall be run with a vertical spacing of 300 mm cable trenches. A minimum of 300 mm clearance shall be provided between the top of tray & beams, cold piping, 500 mm clearance for hot piping / object to facilitate installation of cables in tray.
- Adequate pull boxes shall be provided in conduit run to facilitate. Cable pulling in long runs & also to ensure that there will be no more than 270 degree bend between the pull points.
- Cable tray shall be installed to accommodate cable manufacture's recommended maximum pulling tension & minimum bending radius.
- All opening in the floor & wall for cable access shall be sealed after installation of the cable system with non-inflammable materials.
- All floor/ wall for cable entry to the electrical equipment & accessories shall be sealed with non- inflammable material, after completion of cable installation. Thickness of such materials shall be equal to the thickness of floor / wall.

16. Cable power & control:

- The tender shall install & connect all power & control cable required for complete installation with in his scope of work. Type and size of power& control cable shall be as specified & as supplied under a separate sub section for power and control cable.
- In general all power and control cable shall be run in cable trays in cable trenches. Isolated runs of control cables shall be run in rigid conduit.
- Jointing of power cable should be avoided as per as possible. However, if any splicing of control cable is required to carry out interlock it will be done junction boxes not in the conduit or in the trays. Such junction boxes shall be in scope of tenderer.
- The contractor shall not install cables with different voltage in the same cable tray.
- During cable installation care shall be taken so that actually binding radius of each cable is not less than the one recommended by the cable manufacturer.
- For cable buried directly underground their shall be a stone free sand cushion both above and below the cable run being held by brick wall support on two (2) sides. The excavated portion above the top sand cushion shall be covered by concrete precast slab supported on the side walls & finally filled up with standard back fill.
- Cables shall be pulled into the trenches in strict accordance with the cable manufacture's instruction.
- Tender shall furnish & install suitable solder less crimping type cable lugs at the termination of all wires & cables if not already furnished with the equipment.

- All exposed conduits & armored cables shall be tagged with numbers that appear in the conduit & cable schedules as prepared by the tenderer. All conduits & armored cable shall be tagged at their entrance and / or exist from any piece of apparatus, junction box or pull box. Aluminum tags shall be used with the number engraved / punched on the tag. Tag shall suitable secured to the conduit or armored cable.
- The cable tags shall also be provided at all bends and at interval of 30 M on straight run of cable in order to facilitate the identification.
- Laying termination & connection of all control cables for interlock, protection, indication & annunciation.

The tender shall prepare cable schedule & interconnection diagram & submit the same for approval of the Authority. Cable laying shall be started with the approval cable schedule & interconnection diagrams. Separate cables for each type of following services/ functions as applicable shall be used & laid along the run for each feeders.

- a) Power - designate as „P“
- b) Control protection interlock, meeting, indication & annunciation designate as “C”.

17. Filed Testing:

- Filed testing shall be required for all the equipment & accessories furnished, installed or connected by the tenderer to ensure proper installation, setting, connection & in accordance with the plans, specification and manufacturer’s recommendations.
- Testing shall be conducted in presence of Owner’s Engineer (i.e., Engineer in Charge) with prior notice at least 2 weeks before commencement of any test.
- Filed testing work shall be done as per the latest edition of the relevant standards. All tests recommended by the equipment manufacturer shall be conducted. The tenderer shall submit the list of all filed tests to be conducted for all equipment & accessories for review / approval by the owner.
- Testing shall include any additional tests suggested by the owner that the deems necessary because of filed condition to determine that equipment, materials & system meet requirements of the specification.
- The tender shall depute qualified personal to conduit all testing & shall provide all labour and testing equipment required for & incidental to testing.
- The tender shall be responsible for any damage to equipment & material due to improper test procedure or test apparatus & shall replace to original condition of any damaged equipment or material.
- The tender shall maintain in quadruplicate a written record of all tests showing date, personal making the tests, equipment or material tested performed & result. Two copies of test records shall be given to the authority.

18. Commissioning:

After the satisfactory test is performed the equipment & material shall be put on trial

operation by the tenderer. After successful trial operation, the equipment shall be put on performance tests initially at no load condition & finally with different loading conditions

7.2 Figure 2: Modified provisions in CPWD works manual 2019 regarding testing charges to be borne by contractor

SPECIFICATION FOR 11000 V SWITCHGEAR

1.00.00 DESIGN CRITERIA

- 1.01.00 The switchgear will be used to receive the supply at 11KV & feed 1 No. Step down transformers 11KV /0.433&.660 kV for catering to misc. load and for drives. This drives shall be assisted start type.
- 1.02.00 Switchgear rating and quantities are detailed in the enclosed bill of quantity. Equipment shall be furnished in strict accordance with the same type of switchgear.
- 1.03.00 For continuous operation at specified ratings, temperature rise of the various switchgear components shall be limited to the permissible values stipulated in the relevant standards and/or this specification.
- 1.04.00 The switchgear and components there of shall be capable of withstanding the mechanical forces and thermal stress of the short circuit current without any damage or deterioration of material.
- 1.05.00 The feeders should have appropriate relays and indications for transformer protection from high winding temperature, high oil temperature, tripping and alarming from bucholz relay etc.

2.00.00 SPECIFIC REQUIREMENTS

2.01.00 Construction

- 2.01.01 The switchgear shall be indoor, metal-clad, floor mounted, draw out type. Design and construction shall be such as to allow extension at either end.
- 2.01.02 The switchgear enclosure shall confirm to the degree of protection IP 42. The minimum thickness of sheet steel used shall be 2mm front doors & partitions.
- 2.01.03 The switchgear assembly shall comprise continuous, dead-front line up of free sanding, vertical cubicles. Each cubicle shall have a front hinged door with latches and a removable back cover. All covers and shall be provided with neoprene gaskets.
- 2.01.04 Switchgear cubicle shall be so sized as to permit closing of the front access door when the breaker is pulled out to TEST position. The working zone shall be restricted within 250 mm to 2000 mm from floor level.

2.01.05 Circuit breakers, instrument transformers, busbars, cable compartment etc. shall be housed in separate compartments within the cubicle. The design shall be such that failure of one shall not affect the adjacent unit / equipment.

2.01.06 All relays, meters, switches and lamps shall be flush mounted on the respective cubicle door or on control cabinet built on the front of the cubicle.

2.02.00 BUS AND BUS TAPS

2.02.01 The main buses and connection shall be of high conductivity aluminum/aluminum alloy, sized for specified current rating with maximum temperature limited to 85⁰C i.e. 35⁰C rise over 50⁰C ambient suitable for 1250 Amps.

Bus bars shall be designed for a maximum current density of 0.8A/sqmm.

2.02.02 All bus connection shall be antioxide greased. Adequate contact pressure which should be ensure by mean of two bolt connections with plain & spring washers and locknuts.

Bimetallic connectors shall be furnished for connections between similar metals.

2.02.03 Bus-bars and connections shall be fully insulated for working voltage with adequate phase/ground clearances. Insulating sleeves for bus-bars and cast-resin shrouds for joints shall be provided.

Bus insulator shall be flame-retardant, track resistant type with high creepage surface.

2.02.04 All buses and connections shall be supported and braced to withstand stress due to maximum short circuit and also to take care of any thermal expansion.

2.02.05 Bus-bars shall be sleeved in colour coded manner for easy identification and so located that the sequence R-Y-B shall be from left to right, top to bottom or front to rear, when viewed from front of the switchgear assembly.

2.02.06 The bus-bar chamber shall be provided with inter panel barrier with epoxy cast seal-off bushing through which the buses will pass through so as to prevent fire from one panel to another.

2.02.07 All buses and connections shall be supported and braced to withstand stress due to maximum short circuit and also to take care of any thermal expansion.

2.03.00 CIRCUIT BREAKER

2.03.01 Circuit breaker shall be triple pole VCB Type.

- 2.03.02 Circuit breaker shall be draw out type, having SERVICE, TEST AND DISCONNECTED position with positive identification for each position.
- 2.03.03 Circuit breakers of identical rating shall be physically and electrically interchangeable.
- 2.03.04 Circuit breaker shall have motor wound spring charged trip mechanism with anti-pumping feature and shunt trip. In addition, facility for manual charging of spring shall be provided along with manual charging handle & operating handle.
- 2.03.05 For motor wound mechanism, spring charging shall take place automatically after each breaker closing operation. One open-closed-open operation of the circuit breaker shall be possible after failure of power supply to the motor.
- 2.03.06 Mechanical safety interlock shall be provided to prevent:-
- a.) The circuit breaker from being racked in or out of the service position when the breaker is closed.
 - b.) Racking in the circuit breaker unless the control plug is fully engaged.
- 2.03.07 Automatic safety shutters shall be provided to fully cover the female primary disconnects when the breaker is withdrawn.
- 2.03.08 Each breaker shall be provided with an emergency manual trip, mechanical ON/OFF, indication, an operation counter and mechanism charge/discharge indicator.
- 2.03.09 Each breaker shall be provided with following:-
- a.) Auxiliary switch, with 6 NO +6 NC contacts, mounted on the draw out portion of the switchgear.
 - b.) Position/cell switch with 4 NO + 4 NC contacts one each for TEST and SERVICE position.

2.04.00 CONTROL INDICATION

The circuit breaker shall be wired up for local operation. Each breaker cubical shall be equipped with following:-

- 2.04.01 One (1) TEST-NORMAL-SERVICE selector switch stay put type with pistol grip handle and key interlock.
- 2.04.02 Two (2) heavy duty oil tight, push buttons for trip & close.

- 2.04.03 Three (7) indicating lights on front of compartments:-
 GREEN: Breaker open and spring charged
 RED: Breaker closed
 AMBER discrepancy: Trip/Trip circuit trouble & in closing arrangement.
 WHITE: Control supply available/ failure.
 Phase Indication One Red, One Blue & One Yellow
- 2.04.04 Lamps shall be LED type; lamp and lens shall be replaceable from the front.
- 2.04.05 The general scheme of connection for control, interlock and protection will be intimated later to the successful bidder, who shall develop and furnish the schemes accordingly.
- 2.05.00 CURRENT TRANSFORMER**
- 2.05.01 Current transformers shall be cast resin type. All secondary connections shall be brought out to terminal blocks where wye or delta connections will be made.
- 2.05.02 Accuracy class of the current Transformers shall be:-
- Rating As per BOQ
 - Class 5P10 for other relaying (protection).
 - Class 1.0 and ISF< 5 for metering.
- 2.05.03 The burden of CT shall be of 15 VA.
- 2.06.00 VOLTAGE TRANSFORMER**
- 2.06.01 Voltage transformer shall be of cast- resin 50VA burden, draw out type and shall have an accuracy class of 1.0 Voltage Transformer mounted on breaker carriage is not acceptable.
- 2.06.02 High voltage windings of voltage transformer shall be protected to current limiting fuses. The Voltage transformer and fuses shall be completely disconnected and visibly grounded in fully draw-out position.
- 2.06.03 Low Voltage fuses, sized to prevent overload, shall be installed in all ungrounded secondary leads. Fuses shall be suitably located to permit easy replacement while the switchgear is energized.

2.07.00 RELAYS

- 2.07.01 Relays shall be of draw-out design with built-in testing facilities. Small auxiliary relays may be in non-draw-out execution and mounted within the cubicle.
- 2.07.02 Relays shall be rated for operation on **24 V DC** secondary voltage and 5A secondary current as shown on drawing. Number and rating of relays contacts shall suit the job requirements.
- 2.07.03 The contractors shall furnish, install & co-ordinate all relays to sum the requirements of protection, as broadly indicated in bill of quantity and specifications.

2.08.00 METERS (Digital Display)

- 2.08.01 Indicating instruments of shall be digital switchboard type and accuracy class of +/-2%.
- 2.08.02 Digital Watt-hour meter shall be provided. Alternatively, they may have test block to facilities testing of meter without disturbing C.T. or P.T. secondary connections.
- 2.08.03 Each breaker shall be with digital volt meter, digital amp meter with selector switches & digital KWH meters.

2.09.00 SECONDARY WIRING

- 2.09.01 The switchgear shall be fully wired at the factory to ensure proper functioning of control, protection, transfer and interlocking schemes.
- 2.09.02 MCB links shall be provided to permit individual circuit isolation from bus wires without disturbing other circuits. All spare contacts of relays, switches and other devices shall be wired upto terminal blocks.
- 2.09.03 Wiring shall be done with flexible, 650V grade, PVC insulated switchboard wires with stranded copper conductors of 2.5 sqmm for control and current circuits and 1.5sqmm for voltage circuits.
- 2.09.04 Each wire shall be identified, at both ends, with permanent markers bearing wire numbers as per contractor's wiring diagrams.
- 2.09.05 Wire termination shall be made with crimping type connectors with insulating sleeves. Wires shall not be spliced between terminals.

2.10.00 TERMINAL BLOCKS:-

- 2.10.01 Terminal blocks shall be 660V grade box-clamp type with marking strips ELMEX 10 sqmm or equal. Terminals for C.Y. secondary leads shall have provision for shorting.
- 2.10.02 Not more than two wires shall be connected to any terminal. Spare terminals equal in number to 20% active terminals shall be furnished.
- 2.10.03 Terminal blocks shall be located to allow easy access. Wiring shall be so arranged that individual wires of an external cable can be connected to consecutive terminals.

2.11.00 CABLE TERMINATION:-

- 2.11.01 Switchgear shall be designed for cable entry from the bottom. Sufficient space shall be provided for case of termination and connection.
- 2.11.02 Power cables shall be XLPE insulated, armoured, overall PVC sheathed with stranded aluminium conductor. Control cables shall be PVC insulated armoured, overall PVC sheathed with 2.5 sqmm stranded copper conductor.
- 2.11.03 All provision and accessories shall be furnished for termination and connection of cables, including removable gland, plates, cables supports, crimp type tinned copper/aluminium lugs, brass compression glands with tapered washer (power cables only) and terminal blocks.
- 2.11.04 The gland plates to be minimum 4 mm thick. The gland plate cable and supporting arrangement for I/C power cables shall be such as to minimize flow of eddy current.
- 2.11.05 Sufficient space shall be provided between the power cable termination (end boxes) and gland plate, core balance C.T.s, wherever specified, shall be accommodated within this space.

2.12.00 GROUND BUS:-

- 2.12.01 A ground bus, rated to carry maximum fault current, shall extend full length of the switchgear.
- 2.12.02 The ground bus shall be provided with two-bolt drilling with GI bolts & nuts at each end to receive 50x6mm GI flat.
- 2.12.03 Each stationary unit shall be connected directly to the ground bus. The frame of each circuit breaker and drawout V.T. unit shall be grounded through heavy multiple contacts at all time except when the primary disconnecting drives are separated by a safe distance.

2.12.04 Whenever the schematic diagrams indicate a definite ground at the switchgear, a single wire for each circuit thus grounded shall be ran independently to the ground bus and connected there to.

2.12.05 C.T. and V.T. secondary neutrals shall be earthed through removable links so that earth of one circuit may be removed without disturbing other.

2.13.00 NAMEPLATES:-

2.13.01 Nameplates of approved design shall be furnished at each cubicle and at each instruments & design mounted on or inside the cubicle.

2.13.02 The material shall be lamicaid or approved equal, 3mm thick with white letter on black background.

2.13.03 The nameplates shall be held by self-tapping screws. Nameplates size shall be minimum 20x75mm for instrument/device and 40x150mm for panels.

2.13.04 Caution notice on suitable metal shall be affixed at the back of each vertical panel.

2.14.00 SPACE HEATERS AND PLUG SOCKETS:-

2.14.01 Each cubicle shall be provided with thermostat controlled space heaters & 5A, 3 pin plug socket.

2.14.02 In addition, motor feeder cubicle shall be wired-up for feeding the motor space heater through suitable rated breaker auxiliary NC contact and/or contactor.

2.14.03 Cubicle heater, motor heater, plug/socket circuits shall have individual MCB units.

2.15.00 AC/DC POWER SUPPLY:-

2.15.01 The following power will have to be made available to each switch gear:
A.C. supply; Two single phase feeders

From these two single-phase feeder a reliable 240V, 1 ph AC bus shall be obtained by providing auto change over switch scheme & bus will be run all along the switchgear. The necessary equipment for this scheme is to be supplied by the contractor.

The DC supply required for control purposes is to be obtained from main DC rectifier arrangement which will convert the 240V AC supply to 24 V DC. The necessary equipment for this scheme is to be supplied by the contractor.

2.15.02 Isolating MCB units shall be provided at each switchgear for the incoming supplies, 2-pole, single throw for A.C. & 2-pole, double throw for D.C.

2.15.03 Bus-wires of adequate capacity shall be provided to distribute the incoming supplies to different cubicles. Isolating MCB units shall be provided at each cubicle for A.C./D.C. supplies.

2.15.04 A.C. load shall be so distributed as to present a balance loading on three-phase supply system.

2.16.00 PAINTING:-

2.16.01 All surfaces shall be sand blasted, pickled & grounded as required to produce a smooth, clean surface free of scale, grease & rust.

2.16.02 After cleaning, the surface shall be given a phosphate primer & stoved after each coat. 6.18.03. The switchgear shall be finished in light gray (IS shade # 631) with two coats of synthetic enamel paint.

2.16.03 Sufficient quantity of touch-up paint shall be furnished for application at site.

2.17.00 ACCESSORIES:-

Earthing equipment suitable for earthing the bus or outgoing cable shall be furnished alongwith the switchgear.

3.00.00 TEST:-

3.01.00 The switchgear shall be completely assembled, wired, adjusted & tested at the factory as per the relevant standards.

3.02.00 Routine Test:-

The tests shall include but not necessarily limited to the following:-

- a.) Operation under simulated service condition to ensure accuracy of wiring, correctness of control scheme & proper functioning of the equipment.
- b.) All wiring & current carrying part shall be given appropriate high voltage test.
- c.) Primary current & voltage shall be applied to all instrument transformers.
- d.) Routine test shall be carried out on all equipment such as circuit breakers, instrument transformers, relays, meters etc.

3.03.00 Type Test:-

A copy of the following type test certificate shall be supplied before offering the equipment.

- a.) Impulse test
- b.) Temperature rise test
- c.) Short circuit test.

3.04.00 Test Witness:-

All acceptance tests shall be performed in presence of Authority's representatives, if so desired by the Authority. The contractor shall give at least fifteen (15) days advance notice of the date when tests are to be carried out.

3.05.00 Test Certificate:-

- 3.05.01 Certified reports of all the tests carried out at the works shall be furnished in three (3) copies for approval of the authority.
- 3.05.02 The equipment shall be dispatched from works only after receipt of Authority' s written approval of the test reports,
- 3.05.03 Type test certificate on any equipment , if so desired by the authority, shall be furnished,. Otherwise the equipment shall have to be type tested, free of charge, to prove the design.

4.00.00 SPECIAL TOOLS & TACKELS

- 4.01.00 A set of special tools and tackles which are necessary or convenient for erection, commissioning, maintenance and overhauling of the equipment shall be supplied.
- 4.02.00 The tools shall be shipped in separate container , clearly marked with the name of the equipment for which they are intended.

5.00.00 DRAWING , DATA & MANUALS:-

- 5.01.00 To be furnished for approval after award of work
 - a.) General arrangement drawing showing constructional features , space required in front for withdrawals, power & control cable entry points etc.
 - b.) Details of materials with specifications.
 - c.) Typical foundation plan and loading.
 - d.) Typical breaker control schematic diagram..
 - e.) Matching flange & terminals for the bus termination.

- f.) Type test reports on circuit breaker.
- g.) Technical leaflets on
 - i) Circuit Breaker
 - ii) Instrument transformers
 - iii) Relays, meters, switches etc.
- h.) Single line diagram
- i.) Control schematics
- j.) Wiring diagrams

5.02.00 Instructions manuals of switchgear & individual equipment.

The manual shall clearly indicate that the installation method, checkup & tests to be carried out before commissioning of the equipment.

5.03.00 The bidder may note that the drawings, data & manuals listed herein are minimum requirements only. The bidder shall ensure that all other necessary write-ups, curves & information required to fully describe the equipment are submitted with his bid.

CIRCUIT BREAKER

Make	:	As per approved make
Type	:	VCB
Rated Voltage	:	12 kV
Rated Frequency	:	50 Hz
Rated Current	:	1250 Amp
No. of pole	:	3
Aux. Voltage for trip/ close coil	:	24 V DC
Voltage for spring charging motor	:	240 V AC
Incoming and outgoing panel	:	1

6.00.00 PROTECTION (FOR H.T. SUPPLY 12 KV PANEL)

The protection to be provided for different type of circuits are listed below-

- 6.00.01 SPAJ 140 C (INC-1& FDR-1)
- 6.00.02 VAX31 Trip circuit supervision relay (INC-1& FDR-1)
- 6.00.03 VAA11 Auxiliary relay-DC supply supervision
- 6.00.04 VAJH13 Tripping relay (INC-1& FDR-1)
- 6.00.05 Transformer aux relay (WTI, OTI, Buchholz, Oil level) (FDR-1)

All inverse time O/C relay shall be of 3 sec. Version. All definite time O/C relay shall have adjustable time range of 0-6 sec.

A part from protection relay's each & every breaker shall be provided with auxi. Contact multiplier relay, anti-pumping relay, trip supervision relay, lockout relay, test terminal block. These relay shall be hand reset.

SPECIFICATION FOR POWER AND CONTROL CABLES

1.00.00 DESIGN CRITERIA

- 1.01.00 The cable will be used for connection of power and control circuits of the owner's electrical system.
- 1.02.00 Cable will be either laid on ladder type trays or directly buried in ground.
- 1.03.00 For continuous operation at specified rating, maximum conductor temperature shall be limited to the permissible value as per relevant standard and/or this specification.
- 1.04.00 The insulation and sheath materials shall be resistant to oil, acid and alkali and shall be enough to withstand mechanical stresses during handling.
- 1.05.00 Armoring shall be single round wire of galvanized steel for multicore cables and aluminium for single core cable.
- 1.06.00 Core identification for multicore cable shall be provided by colour coding.

2.00.00 SPECIFIC REQUIREMENTS

2.01.00 L.V. Power cables

1100 Volt grade, heavy duty armoured power cables with stranded aluminium conductors, XLPE insulation and extruded PVC overall sheath.

2.02.00 Control Cables

1100 Volt grade, 70°C rating, control cables with standard copper conductor, PVC insulation, round wire armour and extruded PVC overall sheath.

2.03.00 Drum Length & Tolerance

Each size of the control cable shall be supplied in one length.

2.04.00 Cable Identification

Cable identification shall be provided by embossing on the outer sheath the following:

- a. Manufacture's name or trade mark
- b. Voltage grade

- c. Year of manufacture
- d. Type of insulation e.g. PVC etc.

3.00.00 Joints and Termination

Material of construction for joints / termination shall perfectly match with the dielectric chemical and physical characteristics of the associated cables. The material and design concept shall incorporate a high degree of operating compatibility between the cable and the joints. The protective outer covering (jacket) used on the joints / terminations shall have the same qualities as that of the cable over sheath in terms of ambient / operating temperature and fire retardant properties withstand capability and resistance of hazardous environment and corrosive elements.

4.00.00 TESTS

4.01.00 Shop tests

The cables shall be subject to shop tests in accordance relevant standards to prove the design and general qualities of the cables as below:-

- 4.01.01 Routine tests on each drum of cables
- 4.01.02 Acceptance tests on each drum chosen at random for acceptance of the lot.
- 4.01.03 Type tests on each type of cable, inclusive of measurement of insulation resistance through megger.

4.02.00 Test witness

Tests shall be performed in presence of engineer-in-charge if so desired by the Institute. The contractor shall give at least thirty (30) days advance notice of the date when the tests are to be carried out.

4.03.00 Test Certificates

- 4.03.01 Certified reports of all the tests carried out at the works shall be furnished in six (6) copies for approval of the owner
- 4.03.02 Test reports shall be completed with all details and shall also contain IS specified limit values, wherever applicable to facilities review.

4.03.03 The cable shall be dispatched from works only after receipt of owner's written approval of the test reports.

5.00.00 SPECIAL TOOLS & TACKLES

5.01.00 A set of special tools and tackles which are necessary or convenient for splicing, jointing and termination of different types of cables.

5.02.00 These special tools and tackles shall include but not limited to:-

- a. Splice-cum-insulation remover for control cable 1 No
- b. Hand operated compression tools with a set of
dies for different cable sizes 1 No
- c. Hydraulically operated compression tools with
a set of dies for different cable sizes. 1 No

5.03.00 The tools shall be shipped in separate containers, clearly marked with the service for which they are intended.

6.00.00 SPARES

The bidder shall submit a list of recommended spare parts for three (3) years satisfactory and trouble free operation, indicating the itemized price of each item of the spare.

7.00.00 DRAWING, DATA & MANUALS

7.01.00 Drawing data manuals shall be submitted and in quantities and procedures as specified in general conditions of contract and / or else where in this specification on approval & subsequent distribution after the issue of letter of intent.

7.02.00 To be submitted with the bid:

- a. Manufacture's catalogues giving cable construction details and characteristics.
- b. Cable current rating for different type of installation inclusive of operating factors for ambient temperature, grouping etc.
- c. Write-up on manufacture's recommended method of splicing, jointing, termination etc. of the cables.
- d. Type test report on H.V power cable.

7.03.00 To be furnished for Approval and distribution:

- a. Confirmed cable data.
- b. Shop test reports.

SPECIFICATION FOR ELECTRICAL ERECTION

1.00.00 GENERAL

- 1.01.00 The tenderer shall furnish & install all materials & equipment which are obviously a part of the completed installation but have not been specifically mentioned in this specification without any additional charge to the Authority.
- 1.02.00 All ladders, platforms, scaffolding, temporary supports, any other facility required for erection at site shall also be provided.
- 1.03.00 The tenderer shall at all times work in close coordination with Engineer-in-charge supervisory personnel & afford them every facility to become familiar with the erection & maintenance of the equipment.
- 1.04.00 The tenderer shall arrange his schedule of work & method of operation to minimize inconvenience to other contractors at the project site. In case of any difference between contractors. The decision of the Owner shall be final & binding on all parties concerned.
- 1.05.00 In case of any hold up due to fault of other contractors or for any other reason, the tenderer shall bring it to the notice of the engineering-in-charge in writing without any delay. Otherwise any delay in completion of his work will be accounted for.
- 1.06.00 In case of any contradiction/ confusion with any other section/ sub-section of this specification, the same shall be referred to the Engineer-in-charge in this respect shall be final & binding.

2.00.00 REGULATIONS

The complete installation shall meet the requirements of the latest edition of the relevant Indian Standard & I.E. Rules.

3.00.00 DRAWINGS

The tenderer shall inform himself fully with the relevant Electrical layout single line diagram & schematic drawings enclosed with the package specification.

The tenderer shall furnish all erection drawings, catalogue data sheets, etc as required to cover specific information for all items.

4.00.00 TRANSPORTATION

The contractor shall be responsible for the transportation to the site of all equipment, materials & supplies to be provided by him according to terms of the contract. The contractor shall be responsible for arranging transportation as advised by Owner depending on requirement & to meet the completion schedule. In the event of the schedule requiring change in the mode of transportation the same shall be arranged by the contractor without any extra cost.

5.00.00 UNLOADING

The contractor shall arrange to unload equipment received at site & also arrange to transport the material from the unloading point to site.

The contractor shall make all necessary arrangement for tools & tackles, men & machinery for unloading of equipment at site & its transportation to site or storage. It is clearly understood that demurrage, whereas & other expenses incurred by the contractor due to delayed clearance of the material or for any other reason, shall be to the contractor's account.

6.00.00 STORAGE AT SITE

The contractor shall provide coverage of the equipment & material, security arrangement & all other facilities required for proper & safe storage till completion of the work.

7.00.00 PROTECTION OF WORK

7.01.00 The contractor shall effectively protect his work at his own expense, equipment & material under his custody from theft, damage or tampering.

7.02.00 Finished work where required shall be suitably covered to keep it clean & free from defacement or injury.

7.03.000 For protection of his work contractor shall provide fencing & lighting arrangement connect up space heaters & provide heating arrangement as necessary or directed by Engineer-in-charge.

7.04.00 Contractor shall be responsible for any loss or damage to equipment & material until his work is fully & finally accepted.

8.00.00 OPENING OF CASE, CHECKING AND CLEANING OF PART

8.01.00 All packing cases or package shall be opened in presence of Owner's representative.

- 8.02.00 All equipment, accessories & materials i.e. Switchgear, transformer, bus duct, power & control cables etc after receipt at site shall be jointly inspected & checked with packing list & identified with erection drawings.
- 8.03.00 All claims against loss or damage in transit shall be lodged by the contractor under intimation to Owner. The contractor shall be responsible for processing and settlement of claim including furnishing any information that may be required in this connection.
- 8.04.00 The contractor shall ensure that insurance formalities are observed & any loss of claim due to the fault of the contractor shall be to the contractor's account.
- 8.05.00 All parts shall be thoroughly cleaned all rust removed & surface polished as required.
- 8.06.00 Cleaned & polished parts shall be coated with anti-corrosive paints where necessary & stored with care, ready for erection.

9.00.00 TESTING EQUIPMENT

The major testing equipment that are required to be arranged by the contractor are listed below :

a.) Insulation Tests :

- i) Power operated Meggar - 1 kV & 2.5 kV grade
- ii) Hand operated Meggar - 500 Volt / 1100 Volt grade
- b.) Hand driven earth Resistance Meggar, range 0-1/3/30 Ohms.
- c.) High potential testing set- roller mounted type
- d.) Tong testers of suitable ranges
- e.) Contact resistance measuring set for micro-ohms
- f.) Torque wrench of various sizes.
- g.) Multimeters, test lamp, field telephone with buzzer set, different gauges etc.

10.00.00 PAINTING

After completion of the erection, all equipment & materials supplied under this specification shall be given necessary protective painting. The colour of the final coat shall be approved by the Owner.

11.00.00 ERECTION

11.01.00 Method & materials

11.01.01 All work shall be installed in a first class, neat & workman like manner by mechanics skilled in the trade involve. All details on the installation shall be mechanically & electrically correct.

11.01.02 All materials shall be brand new & of best available quality without having imperfections & blemishes. Where two or more units of the same manufacture.

11.01.03 All conduits & equipment shall be installed in such a manner as to preserve access to any other equipment installed.

12.00.00 DETAILED REQUIREMENT OF INSTALLATION :

12.01.01 All alignment, leveling, grouting, base channel fixing & anchoring adjustments shall be carried out in accordance with manufacturer's instructions and install necessary floor steel for supporting the panels.

12.01.02 All connections, in switchgear shall be completed, checked and adjusted to ensure safety & satisfactory operation of the equipment.

12.01.03 In some cases minor modifications may have to be carried out at site in the wiring & mounting of the equipment to meet the requirement of desired control scheme & the contractor shall have to do the same at no extra cost.

12.02.00 Transformer

12.02.01 The contractor shall place the transformer on its foundation, assemble parts, fabricate & erect & supporting structure for detachable type cable chamber.

12.02.02 H.V. test of transformer oil shall be carried out taking a sample from individual transformer. If the result is not in satisfaction of the purchaser , oil conditioning of that particular transformer shall have to be carried out.

12.03.00 L.T. Bus duct shall be erected duly supported on the soffit on the building by structural member supplied along with the bus duct. The bus duct will pass through separate wall between transformer & switchgear & will rest on two flanges one each at the switchgear & The transformer end. The grounding of the bus duct shall be carried as per the relevant standard. The flanges supplied along with the bus duct shall be erected & terminals end equipment namely transformer & switchgear will be connected to the bus duct. The bus duct shall be erected in straight, vertical or horizontal formation as per the site requirement. The test like milli volt drop on the contacts, insulation resistance value & proper tightness shall be ensured by the contractor.

12.03.01 For draining out of oil a oil soak pit for transformer is to be erected of the suitable capacity.

12.04.00 Miscellaneous items :

12.04.01 The tenderer shall install miscellaneous minor items to complete the installation of equipment.

12.04.02 These equipment will be generally floor or wall mounted. The exact location will be as decided by the Owner at site or as shown in Final drawings.

12.04.03 All support & bracket needed for installation shall be fabricated & painted by the tenderer.

12.04.04 All welding, cutting, chipping & grouting as & when necessary shall be carried out by the contractor.

12.05.00 Handling of cable drum and cable

12.05.01 Rolling of drum shall be avoided as far practicable. For short distance, the drums may be rolled they are rolled slowly and in proper direction as marked on the drum. In absence of any identification, the drums may be rolled in the same direction as it was rolled during taking up the cable.

12.05.02 For unreeling the cable, the drum shall be mounted on jacks or on cable wheel. The spindle shall be strong enough to carry the weight without bending. The drum shall be rolled on the spindle slowly, so that cable should come out over the drum & not below the drum.

12.05.03 While laying cable, cable shall be used at an interval of 2 meters. The cable shall be pushed over the roller by a gang of people positioned in between rollers. The cable shall not be pulled from the end without laying intermediate pushing arrangement. Bending radius shall not be less than what is specified by manufacturer.

12.06.00 Cable laying :

Cables shall generally be installed in cable trays except for some short runs in buried formation or in conduit / pipe for protection or crossing. Multi core power cables laid on trays & riser shall be neatly dressed & clamped with fabricated 25 x 3 mm G.S. flat or cable tray at an interval of maximum 1 meter for vertical / inclined run & 1.50 meter for horizontal run. Control cables may be laid in single layer with touching formation. Power & control cables shall be claimed in separate group. Power & control cables shall not be laid in a common tray excepting in very special case where a gap of 150 mm shall be maintained between power & control cables.

12.06.01 H.T. & L.T. power cables shall be laid in cable tray in single layer & with spacing equal to the diameter of cable.

12.06.02 Control cables can be laid upto a maximum of three layers in each tray.

12.06.03 Both power & control cables shall be clamped to the tray rungs by means of clamp made up of 25 x 3 mm fabricated G.S. flat at an interval of 1500 mm for horizontal run & 1000 mm for vertical / inclined cable run.

12.06.04 The cable trays shall be run with a vertical spacing of 300 mm cable trenches. A minimum of 300 mm clearance shall be provided between the top of tray & beams, cold piping, 500 mm clearance for hot piping/ object to facilitate installation of cables in tray.

12.06.05 Adequate pull boxes shall be provided in conduit run to facilitate. Cable pulling in long runs & also to ensure that there will be no more than 270 degree bend between the pull points.

12.06.06 Cable tray shall be installed to accommodate cable manufacturer's recommended maximum pulling tension & minimum bending radius.

12.06.07 All openings in the floor & wall for cable access shall be sealed after installation of the cable system with non-inflammable materials.

12.06.08 All floor / wall openings for cable entry to the electrical equipment & accessories shall be sealed with non-inflammable material, after completion of cable installation. Thickness of such materials shall be equal to the thickness of floor / wall.

12.07.00 Cables-power & control :

12.07.01 The tenderer shall install & connect all power & control cable required for complete installation within his scope of work. Type & size of power & control cable shall be as specified & as supplied under a separate sub section for power & control cable.

12.07.02 In general all power & control cable shall be run in cable trays in cable trenches. Isolated runs of control cables shall be run in rigid conduit.

12.07.03 Jointing of power cable should be avoided as far as possible. However, if any splicing of control cable is required to carry out interlock it will be done in junction boxes not in the conduit or in the trays. Such junction boxes shall be in the scope of tenderer.

12.07.04 The contractor shall not install cables with different voltage grade in the same cable tray.

12.07.05 During cable installation care shall be taken so that the actual bending radius of each cable is not less than the one recommended by the cable manufacturer.

12.07.06 For cables buried directly underground there shall be as per CPWD norms for HT & LT cables, stone free sand cushion both above & below the cable run being held by brick protection after sand cushioning.

12.07.07 Cables shall be pulled into the trenches in strict accordance with the cable manufacture's instruction.

12.07.08 Tenderer shall furnish & install suitable solderless crimping type cable lugs at the termination of all wires & cables if not already furnished with the equipment.

12.07.09 All exposed conduits & armoured cables shall be tagged with the numbers that appear in the conduit & cable schedules as prepared by the tenderer. All conduits & armoured cables shall be tagged at their entrance and/ or exist from any piece of apparatus, junction box or pull box. Aluminium tags shall be used with the number engraved/ punched on the tag. Tag shall be suitable secured to the conduit or armoured cable.

The cable tags shall also be provided at all bends and at interval of 30 M on straight run of cable in order to facilitate the identification.

12.07.00 Laying termination & connection of all control cables for interlock, protection, indication & annunciation.

The tenderer shall prepare cable schedule & interconnection diagram & submit the same for approval of the Authority. Cable laying shall be started with the approval cable schedule & interconnection diagrams. Separate cables for each type of following services/ functions as applicable shall be used & laid along the run for each feeder.

a.) Power - designate as 'P'

b.) Control protection interlock, metering, indication & annunciation designate as 'C'.

13.00.00 FIELD TESTING :

13.01.00 Field Testing shall be required for all the equipment & accessories furnished, installed or connected by the tenderer to ensure proper installation, setting, connection & in accordance with the plans, specifications & manufacturer's recommendations.

Testing shall be conducted in presence of Owner's engineers with prior notice at least 2 weeks before commencement of any test.

13.02.00 Field testing work shall be done as per the latest edition of the relevant standards. All tests recommended by the equipment manufacturer shall be conducted. The tenderer shall submit

the list of all field tests to be conducted for all equipment & accessories for review / approval by the Owner.

13.03.00 Testing shall include any additional tests suggested by the Owner that he deems necessary because of field conditions to determine that equipment, materials & system meet requirements of the specification.

13.04.00 The tenderer shall depute qualified personal to conduit all testing & shall provide all labour & testing equipment required for & incidental to testing.

13.05.00 The tenderer shall be responsible for any damage to equipment & material due to improper test procedure or test apparatus & shall replace or restore to original condition of any damaged equipment or material.

13.06.00 The tenderer shall maintain in quadruplicate a written record of all tests showing date, personal making the tests, equipment or material tested, test performed & result. Two copies of test records shall be given to the Authority.

14.00.00 COMMISSIONING :

After the satisfactory test are performed the equipment & material shall be put on trial operation by the tenderer. After successful trial operation, the equipment shall be put on performance tests. Initially at no load condition & finally with different loading conditions.

SPECIFICATION FOR THE ELECTRICAL INSTALLATION WORK

The following specifications will apply under all circumstances to the equipment to be installed against this contract and it is to be ensured that the contractor shall obtain for himself at his own expense and on his own responsibility all the information which may be necessary for purpose of making the tender and for entering into a contract keeping in view the specification and inspection of site etc.

The tendered rates shall include for the cost of material erection, connection, commissioning, labour, supervision, tools, transport all taxes, contingencies, breakage, wastage, sundries, scaffolding, maintenance of installations for defect liability period i.e. they should be for an item complete in all respects.

The general specifications of electrical works for internal-2005 and general specifications for Sub-station works-2007 of CPWD shall be followed.

1. SITE CONDITIONS: the equipment to be erected and commissioned should be suitable for the site conditions, it is estimated that the maximum temperature as site will be 50°C.

2. L.S.SPECIFICATIONS:

The following Indians standard specifications will apply to the equipment and the contract unless specified otherwise.

a)	Transformer	IS 2026-1977 & 1981
b)	Low tension air-circuit breakers and MCCB	IS 2516-1965
c)	Switch fuse unit on cubicle switch boards etc.	IS 4047-1967
d)	Switch fuse unit on industrial boards etc	IS 4064-1967
e)	Switch gear bus bars	IS 375-1963
f)	HRC fuse links	IS 2208-1962
g)	Distribution fuse boards	IS 2675-1966
h)	Degree of protection provided by enclosure For low voltage switchgear	IS 2147-1962

i)	PVC cables.	IS 1954-1962
j)	11,000 volt paper insulated lead sheathed cables	IS 692-1965
k)	Tubular fluorescent lamps for general lighting Service.	IS 2418-1965
l)	Tungsten filament lamps for general service.	IS 418-1963
m)	Ceiling fans	IS 374-1966
n)	Flood light	IS 1947-1961
o)	Well glass flame proof electric light fitting	IS 2206-1962 Part-I
p)	XLPE cables	IS 7098-Part-II
q)	Industrial light fittings with metal reflectors.	IS 1971-1961
r)	Water tight electric light fittings	IS 3533-1966
s)	Fittings for rigid steel conduits	IS 2667-1964
t)	Rigid steel conduits for electrical wiring	IS 1958-1964
u)	Accessories for rigid steel conduit for electrical Wiring.	IS 3873-1966
v)	Switch socket outlets.	IS 4615-1963
w)	Three pin pug and socket outlets	IS 1233-1967
x)	Switches for domestic and similar purpose	IS 3858-1966
y)	AC electricity meters	IS 722-1977/1980+86

CODE FOR PRACTICE

Earthing	IS 3043-1966
Electrical wiring installations	IS 732-1963
Lighting protection	IS 2309-1969

7.3 List of Approved Makes for Electrical Works

S.No.	Items	Makes
1	MS Conduit (ISI marked) with heavy duty accessories	BEC/AKG/ RM CON /Steel Kraits
2	PVC/ XLPE insulated aluminium / copper conductor armoured unarmoured MV cables upto 1100 V (ISI Marked)	Havells / Finolex/ KEI/ Grandlay/ Polycab/Gloster
3	FRLS PVC insulated copper conductor stranded flexible wire i/c control cables (ISI Marked)	Havells/Finolex/KEI/ Grandlay/Polycab/Gloster
4	Cable Raceway floor/wall mounted and accessories	Legrand / MK (Honeywell) / OBO/Excel
5	Cable Tray & Accessories	Venus / MEM / BEC / RM CON/ Indeana/Excel
6	Modular Switch & Socket & Accessories	Legrand (Myrus)/M.K. (Element) /Schneider (Zencelo) / legrand (Arteor)/ ABB
7	Metal clad Industrial Socket outlet and sheet steel Enclosure for MCCB/ MCB	Legrand/Siemens/Schneider/Hager
8	Cable Glands	Dowells/Commet/Gripwell/Raychem
9	Lugs and end termination	Dowells/Commet/Braco
10	Change over switch	L&T / Socomac / ABB / Schneider
11	Distribution Boards	Siemens (Betagard), / Hager / Schneider (Acti9) / Legrand (Ekinox ³ / L&T (Exora / ABB (Elegence)
12	Protection Device (MCB/RCCB/RCBO/ELCB)	Siemens (5SL), Hager / Schneider (Acti9) / Legrand (DX 3) / ABB (S200M) / L&T
13	Current transformer / potential transformer	AEL / Gilbert & Maxwell / Pragati / Precise / L&T/ Kappa
14	Indicating Lamps LED type, Push Button	Siemens / L&T / Schneider / Legrand
15	Electronic Digital Meters	Schneider (conzerv) / L&T / Secure / Siemens / ABB / Legrand

16	MCCBs	Siemens (3VL) / L&T (D sine) / Schneider (CVS) / Legrand (DPX3) ABB (T max)
17	Power Contactor	L&T (MNX)/ Schneider (Tsys) / Legrand (CTX ³) ABB (Ax)
18	Surge Protection Devices	Siemens/L&T/Schneider / Legrand/ OBO
19	Selector Switch	Salzer/Seimens /BCH/ Kaycee / L&T
20	Auxiliary Relays	Siemens/L&T/Schneider/Legrand/ABB
21	LED Lighting Fixture	Philips/ Wipro/Havells/Crompton
22	Emergency Lighting/ Exit Sign boards	Bajaj / Prolite / Glo-Line
23	Ceiling Fan, Fresh Air Fan, Exhaust Fan	Havells/Crompton / Usha / Orient/ Atomberg
24	Paint	Nerolac/Asian/Berger/ICI
25	Lighting Protech System	OBO/ Cape Electric/ Infinite / APS/ Jeff Techno/ Axis
26	G.I Pipe	Tata, Jindal-Hissar, Prakash Surya
27	Rubber Mat (ISI Marked)	Jyoti / Deep Jyoti/ Premier
28	Fire Extinguisher	Minimax/ Life Guard / Cease Fire / Newage
29	CU/ GI Strip & GI wire for earthing	Jeff Techno/ Axis / OBO
30	MS Conduit (ISI marked)	BEC/AKG/NIC/ Steel craft/ M-Key, SK (E.R.W)
31	PVC Conduit and accessories	Polycab/ AKG / Asian
32	1.1 KV aluminium armoured XLPE insulated and PVC sheathed cable (LT cable)	Havells /KEI/ Finolex/ Grandlay/ Gloster
33	Modular Switch & Socket	Legrand (Mylus) MK (Element) Schneider (Zencelo India) / Havells/ ABB
34	Metal Clad Industrial Socket	Legrand / Siemens/Schneider/ C&S/ ABB
35	Cat-6 cable	Beldon/Siemon/Legrand/Penduit (Pannet)
36	Crimp Patch Cord	Beldon/Siemon/Legrand/Penuit (Pannet)
37	Panel Accessories	Siemenss/ L&T/ Schneider / Legrand / Tecnic/ ABB/ C&S/ Neptune
38	LED/ Metal Halide / Fluorescent Internal Lighting Fixtures	Philips/ Wipro/Havells/Crompton
39	External Lighting Fixture	Philips/ Wipro/Havells/Crompton

40	<i>Ceiling Fan (ISI marked & BEE rated 5 star)</i>	<i>Havells / Almonard/ Orient/ Usha/ Bajaj</i>
41	<i>Advance lighting protections System (Early Streamer Emission Type)</i>	<i>LPI (Australia)-by allied power/ SGI (Duval Messien/ Satellite(France) by SGI/ Bradlay (USA) -by JMV/ Erico (USA) by security shoppe/ ABB</i>
42	<i>Main LT Panels/ MCC Panel</i>	<i>(Main LT panel / MCC Panel board should be IEC 61439 part-I and II manufacturer has to produces the relevant test certificate as per IEC code for the same failing which panel shall be rejected). L&T /Siemens / Schneider/ ABB/ Legrand or their authorized channel partners for IEC 61439 compliant panels</i>
43	<i>Air Circuit Breaker</i>	<i>Siemens / Schneider/ L&T/ Legrand/ C&S/ ABB</i>
44	<i>Surge Voltage Protection</i>	<i>Siemens/L&T/Schneider / ABB</i>
45	<i>Earth fault module</i>	<i>Siemens/Schneider/L&T/Legrand</i>
46	<i>Protection relays</i>	<i>Siemens/ Areva/ L&T/ Legrand</i>
47	<i>C.Ts and PTs</i>	<i>Kappa / AE/ Matrix</i>
48	<i>Digital Meters</i>	<i>Siemens (PAC)/ Schneider/ (conzerv) / Secure Enersol / L&T/ Neptune</i>
49	<i>Indicating lamps</i>	<i>ESBEE/Schneider/Siemens/Vaishno/Neptune</i>
50	<i>Power capacitors</i>	<i>Epcos/ Neptune / Legrand /ABB/ L&T</i>
51	<i>Automatic Power factor correction relay/controller</i>	<i>Epcos/Siemens (PAC) /Schneider (Conzerv)/L&T/Neptune</i>
52	<i>Sealed Maintenance Free Batteries</i>	<i>Exide/Panasonic/Amara Raja/HBL</i>
53	<i>Battery charger</i>	<i>Caldyne/Chhabi Electricals/Statcon/Max Power</i>
54	<i>Cable Trays (Factory Fabricated/ Overhead & Floor Raceways</i>	<i>Legrand/MEM/OBO/ Milestone/ Neptune</i>
55	<i>HDPE underground cable duct</i>	<i>Rex Polyextrusion/ Tirpura/ Plasomatics/ Duraline</i>
56	<i>Insulation Mats</i>	<i>DL Miller & Co. Ltd.?Premier Polyfilm Ltd./RMG Polyvinyl India Ltd/Jyoti</i>
57	<i>Smoke/Heat detectors</i>	<i>Apollo/ System Sensor/ Agni</i>
58	<i>Manual Call point</i>	<i>PRD/System-Tek/ Simplex/ System Sensor/ Agni</i>
59	<i>Response indicators</i>	<i>PRD/System-Tek/ Simplex/ System Sensor /Agni</i>

60	Fire Exit Signs	System-Tek/ Simplex/ Agni
61	Fire Control Panel	System-Tek/ Morley /Agni
62	Speaker / Hooter	System-Tek/ Philips /Agni
63	Occupancy Sensors/ Movement Sensor	Legrand/ Philips/ Wipro
64	Flush type switch /socket	Anchor/ Kinjal/ SSK/ Havells Reo
65	Fuse switches unit / switch fuse unit /HRC fuse	L&T / Siemens/ Havells/ C&S
66	Exhaust fan	Almonard/ Alstom/ Crompton/ Havells
67	XLPE insulated HT cables	KEI/Havells/Polycab/ Grandlay
68	Cable lug	Ascon (Heavy gauge) Jainson Dowells
69	Telephone wires/Telephone Cable / jelly filled telephone cables	Finolex /Delton/Havell's
70	Telephone tag blocks	Krone/ Pouyet
71	Telephone outlet	MK Electric /Legrand (Mosaic)/Crabtree (Piccadilly)
72	GI raceways	Milestone Engineering /Legrand/ MDS/ Neptune Systems Pvt. Ltd./MK
73	PVC raceways	Legrand/ MK
74	Electronic ballast	Philips / Wipro/ Bajaj/ Decon/Crompton/Havells
75	DLP plastic trunking	Legrand/MK
76	Geysers	Recold /Venus /Usha Lexus /Sphere hot
77	Tower Light	Ligman/Simes/Bega
78	HT/LT transformers	ABB/Schneider /CGL (Crompton Greaves Ltd.)
79	HT SF-6 circuit breakers / VCB	Siemens/ ABB/ CGL / Schneider
80	Programmable Logic Controller (PLC)	Siemens /Allen-Bradley/ Schneider
81	Earthing (Chemical Earthing Plate Earthing)	JMV/ As per CPWD Norms
82	Octagonal Pole	Bajaj / Crompton / Philips
83	11 kV HT panel Incoming relay	CGL/Schneider/ABB/ Siemens
84	Control Relay Panel	CGL/Schneider/ABB
85	Lightning Arrestor	ABB/Alltec/JMV
86	Temp. Gauge	Guru

87	<i>Gate Valve</i>	<i>Leader/Sant</i>
88	<i>Electrical Backup</i>	<i>Spare hot/ Racold</i>
89	<i>PVC Tank</i>	<i>Syntex/ Polycon</i>
90	<i>Thermostat</i>	<i>ISI Marked</i>
91	<i>Flat Collector Plate</i>	<i>Solocrome/ Tata BP/ Racold</i>
92	<i>S.S Sheet</i>	<i>Jindal / National</i>
93	<i>HT/LT cable joints (Straight through/outdoor/indoor)</i>	<i>3M/ Denson/ M Seal/Raychem</i>
94	<i>Alternator</i>	<i>STAMFORD/Crompton Greaves/Kirlosker/Leroy Somer</i>
95	<i>DG set engine</i>	<i>Kirlosker/ Cummins/ Greaves Cotton/Baudouin/Caterpillar/Perkins</i>
96	<i>DG Set (Preferred makes)</i>	<i>Sterling Generator/ Kirlosker /Caterpillar/Cummins Power / Greaves Cotton/Jackson</i>
97	<i>Makes of accessories of HT / LT Panel / Transformers</i>	<i>As per standard practice of manufacturer/ Channel partner of L&T /Siemens / Schneider/ ABB/Legrand/Crompton Greaves</i>
98	<i>Bus Trunking</i>	<i>C&S / L&T/ Schneider as per standard practice of OEM manufacturer / channel partner</i>
99	<i>HT panel 11 KV</i>	<i>ABB/ Schneider/ CGL (Crompton Greaves Ltd.)</i>
100	<i>Bus Duct</i>	<i>Neptune / Milestone/ Tricolite</i>
101	<i>Lamp Holder (Brass)</i>	<i>Kay/ SSK/ Kinjal</i>
102	<i>UPS</i>	<i>APC(Schneider)/Vertiv/ABB/Numeric/Delta/Tmeic</i>
103	<i>AMF Panel</i>	<i>L&T/ Siemens/ ABB/ Excel Control/ Modern Switchgear</i>

8 Special Conditions of Contract

8.1 Special Conditions for the minor works under the contract

1. The contract will be used only to execute original works/ minor works/ repair works of urgent nature. It can also be used for any works of restoration as a result of a disaster in campus causing damage to institute infrastructure/ works related to emergency services/ works of institute importance/ works concerned to safety health and environment of campus community. The works undertaken through such contracts are categorized as time bound and should be executed as per Table 6.
2. The contractor should always keep his establishment ready to commence the work immediately after the issue of the work of any amount. The schedule for the issued works under the contract should be as per Table 6. Work requests of urgent nature shall be started at the earliest after receiving orders from the engineer-in-charge but it should be documented with photo and video evidence for all hidden items. Submission of this evidence is mandatory for all works executed without a pre-approved quantity take off sheets.
3. During the execution, the noise creation should be minimized to the extent possible and the works may be carried at odd hours and more than one shift as per requirement.
4. The performance of the instruments or tools to be used should be checked precise before using them on site.
5. The contractor and his/her personnel have to build a well-coordinated system with the users regarding execution of the works.

8.2 Timely Completion

1. All work components must be started simultaneously and has to be delivered together or early within the given time schedule.
2. The contractor has to deploy the labor and supervisory staff in shifts to meet the targeted completion date. The work may be executed in extended shifts or two shifts.
3. Number of days from the date of issue of letter of acceptance for reckoning date of start shall be as per Schedule. *If the Contractor commits default in commencing the execution of the work as aforesaid, the performance guarantee shall be forfeited.*
4. The contractor shall procure the required materials in advance so that there is sufficient time for testing of the materials and approval of the same before use in the work, as required.

8.3 Rates

1. Unless otherwise provided in the schedule of quantities of the work the rates tendered by the contractor shall be all inclusive and shall apply to all heights, lifts, leads and depths of the building (inclusive of GST) and nothing extra shall be payable to him on this account.
2. The rates for all items of work shall, unless clearly specified otherwise, include cost of all labours, materials and other inputs involved in the execution of the item irrespective of

whether they have been specifically mentioned in the tender document or not.

3. In case the same item (s) appear more than once in the schedule of work / BOQ under the same sub head or among the different subhead of works, the lowest rate quoted for that item (s) shall be considered for the particular item(s) wherever appeared in any part of BOQ / Schedule of works for the purpose of tender evaluation although web generated e-price bid may incorporate different quoted rate for same item(s) as per the quoting pattern of the tenderer. The tendered amount thus worked out shall be final & shall be binding on the contractor.
4. No double scaffolding is payable in single story houses including parapet wall. In multistory houses the payment of double scaffolding shall be made after 3.5 meter from plinth protected level. The necessary deductions for single scaffolding are made from the items. Contractors are advised to visit the site & quote the rates accordingly.
5. The rates quoted by the contractor will be deemed to be inclusive of any extra expenditure of this reason. The contractor has to increase the manpower or other tools etc. to do the work as per the quantum of work provided to him at his own expenses. Nothing shall be paid on this account.
6. The contractor shall provide at his own cost suitable weighing, surveying and leveling and measuring arrangements as may be necessary at site for checking. All such equipment shall be got calibrated in advance from laboratory, approved by the Engineer-in-Charge. Nothing extra shall be payable on this account.
7. Other agencies may also simultaneously execute and install the works and the contractor shall afford necessary facilities for the same. The contractor shall leave such recesses, holes, openings, trenches etc. as may be required for such related works (for which inserts, sleeves, brackets, conduits, base plates, clamps etc. shall be available as specified elsewhere in the contract) and the contractor shall fix the same at the time of casting of concrete, stone work and brick work, if required, and nothing extra shall be payable on this account.
8. All material shall only be brought at site as per program finalized with the Engineer-in-Charge. Any pre-delivery of the material not required for immediate consumption shall not be accepted and thus not paid for.
9. MCCB's, switches, sockets, wires, cable, light fixtures, earthing and other electrical items covered under the contract should conform to approved manufacturers specifications, where CPWD Specifications are not applicable. The contractor should get the materials (fixtures/fittings) tested from approved labs wherever required at his own cost.
10. The contractor shall be responsible for the watch and ward / guard of the buildings, safety of all fittings and fixtures including sanitary and water supply fittings and fixtures provided by him against pilferage and breakage during the period of installations and thereafter till the building is physically handed over to the client department. No extra payment shall be made on this account.
11. The rates quoted by the Contractor are deemed to be inclusive of site clearance, setting out work, profile, establishment of reference bench mark(s), taking spot levels, construction of all safety and protection devices, barriers, preparatory works, working during monsoon,

working at all depths, height, lead, lift and location etc until / unless specified otherwise and any other incidental works required to complete this work. Nothing extra shall be payable on this account.

12. The EPF & ESI contribution deposited against the contract workers shall be reimbursed on actual basis.
13. Goods and Service Tax on work contract as per prevailing notification of UP. Govt. shall be also be recovered from the contract bill.
14. Income tax shall be deducted as per prevalent law.

8.4 Quality and Workmanship

1. The contractor shall be entirely responsible and answerable for all the works done by him regarding quality, adherence to the laid down specifications, terms and conditions, warranty/guarantee etc. and he shall be liable to bear any compensation that may be levied by the department under any of the clauses of the agreement.
2. The materials having ISI mark shall have precedence over the one conforming to IS Specifications.
3. The proposed buildings are Institute housing and quality of work is paramount importance. Contractor shall have to engage well experienced skilled labour and deploy modern T&P and other equipment to execute the work.
4. Samples of all materials and fittings to be used in the work in respect of brand manufacturer and quality shall be approved from the Engineer-in-Charge, well in advance of actual execution and shall be preserved till the completion of the work.
5. All materials used in the work shall be new and of good quality, conforming to the relevant specifications as per good engineering practice. All the materials proposed to be used in the work should be approved from Engineer in Charge before use in work.
6. Articles bearing BIS certifications mark shall only be used unless no manufacturer has got BIS/ISI mark for the particular material. Any material/fitting whose sample has not been approved in advance and any other unapproved material brought by the contractor shall be immediately removed as soon as directed. Where the make of any particular material is not specified in the Contract document, the material shall be supplied as per makes desired by the engineer-in-charge.
7. It will be the responsibility of the contractor / bidder to ensure use of genuine materials in the work. The department reserves the right to get (any / all materials / components) inspected by the manufacturer or their authorized representatives at any stage of the execution of work. If any of the materials, supplied and used in work is found spurious at any stage, then the department reserves the right to ask the contractor to replace it by genuine one and make suitable recovery till it is done, even if any payment against that material is already made.
8. The contractor should get the make/TDS documents approved before procuring any material at site. The TDS/Make once approved shall not be changed without any valid recorded reasons. No material to be brought and used at site without the prior knowledge & approval

of Engineer-in-Charge.

9. The department may ask for any valid document like manufacturer's test certificate, document for purchase of the material, document for import/shipment of imported materials etc. as deemed fit by the engineer-in-charge to ascertain genuineness of material supplied by/used in the work by the contractor. The contractor shall remain bound to submit all such documents to the department failing which payment may not be made or if already paid may be recovered/ withheld from subsequent running account payment.
10. All equipment and their components, and all the materials to be used in the work shall be suitable for the environmental conditions at the location of the work.
11. The contractor shall ensure quality control measures on different aspects of construction including materials, workmanship and correct construction methodologies to be adopted. He shall have to submit quality assurance programme within two weeks of the award of work. The quality assurance programme should include method statement for various items of work to be executed along with check lists to enforce quality control.
12. The contractor shall get the source of all other materials, not specified elsewhere in the document, approved from the Engineer-in-Charge. The contractor shall stick to the approved source unless it is absolutely unavoidable. Any change shall be done with the prior approval of the Engineer-in-Charge for which tests etc. shall be done by the contractor at his own cost. Similarly, the contractor shall submit brand/ make of various materials not specified in the agreement, to be used for the approval of the Engineer-in-Charge along with samples and once approved, he shall stick to it.
13. Other Laboratories: The contractor shall arrange carrying out of all tests required under the agreement through the laboratory as approved by the Engineer-in-Charge and shall bear all charges in connection therewith including fee for testing. The said cost of tests shall be borne by the contractor/department in the manner indicated below.
 - (a) By the contractor, if the results show that the test does not conform to relevant CPWD Specifications / BIS code or specification mentioned elsewhere in the documents.
 - (b) By the department, if the results conform to relevant CPWD Specifications / BIS code or specification mentioned elsewhere in the documents.

If the tests, which were to be conducted in the site laboratory, are conducted in other laboratories for whatever the reasons, the cost of such tests shall be borne by the contractor.
14. Sample of materials fittings and other articles required for execution of work shall be got approved from the Engineer-in-Charge. Articles manufactured by companies of repute and approved by the Engineer-in-Charge shall only be used. Articles bearing BIS certification mark shall be used in case the above are not available, the quality of samples brought by the contractor shall be judged by standards laid down in the relevant BIS specifications. All materials and articles brought by the contractor to the site for use shall conform to the samples approved by the Engineer-in-Charge which shall be preserved till the completion of the work.
15. The contractor shall ensure quality construction in a planned and time bound manner. Any sub-standard material/work beyond set out tolerance limit shall be summarily rejected by the Engineer-in-Charge.

16. BIS marked materials except otherwise specified shall be subjected to quality test at the discretion of the Engineer-in-Charge besides testing of other materials as per the specifications described for the item/materials. Wherever BIS marked materials are brought to the site of work, the contractor shall if required, by the Engineer-in-Charge furnish manufacturers test certificate or test certificate from approved testing laboratory to establish that the material produced by the contractor for incorporation in the work satisfies the provisions of BIS codes relevant to the material and/or the work done. The contractor shall procure all the materials at least in advance so that there is sufficient time to testing and approving of the materials and clearance of the same before use in work.
17. All materials brought by the contractor for use in the work shall be got checked from the Engineer-in-Charge or his authorized representative of the work on receipt of the same at site before use.
18. The contractor shall be fully responsible for the safe custody of the materials issued to him even if the materials are in double lock and key system.

8.5 Natural calamity

No payment will be made to the contractor for any damage caused by rain, snow fall, floods, dampness, fire, sun or any other natural cause whatsoever during the execution of work. The damage to the work due to above reason, if any, shall have to be made good by the contractor at his own cost and no claim on this account shall be entertained.

8.6 Safety and Security

1. The contractor has to follow all safety norms as laid down in National Building Code of India. All the workers shall be equipped with the required safety gadgets while working at site such as ISI marked helmets, Shoes and safety belts, gumboots, gloves etc. The contractor, the authorized representative(s), workmen etc., shall strictly observe orders pertaining to fire precautions prevailing in the area.
2. The contractor shall be fully responsible for the safe custody of materials brought by him/ issued to him even though the materials may be under double lock key system.
3. Contractor will arrange proper metal ladders, M.S. double scaffolding (for working, painting, etc. at higher levels) at his own cost and will take all safety measures like double harness safety belt, mechanized electrically operated platform etc. If it is observed that work is proceeding without adequate safety precautions, work may be stopped by Engineer-in-charge and in such cases, contractor will be solely responsible for delay and its consequences thereof.
4. The contractor shall be responsible for the watch and ward/guard of the buildings, safety of all fittings and fixtures including sanitary and water supply fittings and fixtures provided by him against pilferage and breakage during the period of installations and thereafter till the building is physically handed over to the department. No extra payment shall be made on this account.
5. The contractor shall take all precautions to avoid accidents by exhibiting necessary caution

boards day and night speed limit boards red flags, red lights and providing barriers. He shall be responsible for all dangers and incidents caused to existing / new work due to negligence on his part. No hindrances shall be caused to traffic during the execution of the work.

6. It shall be ensured by the contractor that no electric live wire is left exposed or unattended to avoid any accidents in this regard.
7. The Institute shall not have any responsibility or liability in case of any accident injury to the personnel to the contractor at work site or to the general public at the work site due to mishandling equipment by the personnel of the contractor or any other similar reason. The responsibilities and liabilities for such accidents and incidents shall be borne by the contractor.

8.7 Approach to Site

1. The tenderer shall see the approaches to the site. In case any approach from main road is required at site or existing approach is to be improved and maintained for cartage of materials by the contractor, the same shall be provided, improved and maintained by the contractor at his own cost.
2. Contractor shall take all precautionary measures to avoid any damage to adjoining property. All necessary arrangement shall be made at his own cost.

8.8 Acts and Laws

1. The Contractor shall keep himself fully informed of all acts and laws of the Central & State Governments, all orders, decrees of statutory bodies, tribunals having any jurisdiction or authority, which in any manner may affect those engaged or employed and anything related to carrying out the work. All the rules & regulations and bye-laws laid down by Collector / MC etc. and any other statutory bodies shall be adhered to, by the contractor, during the execution of work.
2. The Contractor shall also adhere to all traffic restrictions notified by the local authorities.
3. All statutory taxes, levies, charges (including water and sewerage charges, charges for temporary service connections and / or any other charges, as applicable) payable to such authorities for carrying out the work, shall be borne by the Contractor.
4. The Contractor shall arrange to give all notices as required by any statutory / regulatory authority and shall pay to such authority all the fees that is required to be paid for the execution of work. He shall protect and indemnify the Institute and its officials & employees against any claim and /or liability arising out of violations of any such laws, ordinances, orders, decrees, by himself/herself or by his/her employees or his/her authorized representatives. Nothing extra shall be payable on these accounts.
5. The fee payable to statutory authorities for obtaining the various permanent service shall be borne by the Institute.

8.9 Labour and Laws

1. The Contractor shall display all permissions, licenses, registration certificates, bar charts, other statements etc. under various labour laws and other regulations applicable to the works, at his site office.
2. Huts for labour are not permitted within the premises of the Institute. No extra cost shall be payable even if the contractor provides such accommodation at a place as is acceptable to the local body.

8.10 Nondisclosure Agreement

1. The Agency shall take all precautions not to disclose, divulge and/or disseminate to any third party any confidential information, proprietary information on the Institute business or security arrangements (including but not limited to the Assignment instructions, Schedules and other subsequent Arrangements) and/or business of the Institute. The obligation is not limited to any Scope and the Agency shall be held responsible in case of breach of the confidentiality of Institute's information.
2. If the Agency receives enquiries from Press/Media/Radio/Television or other bodies /persons, the same shall be referred by the Agency to Institute immediately on receipt of such queries.

8.11 Indemnification:

1. The agency shall be directly responsible to indemnify the Institute against all charges, dues, claims, etc. arising out of the disputes relating to the dues and employment of the personnel deployed and further for any claim/compensation against all damages and accidents caused due to negligence on the part of the agents, employees and other personnel of the agency.
2. That the contractor shall keep the IITK indemnified against all claims whatsoever in respect of the employees deployed by the contractor. In case any employee of the contractor so deployed enters in dispute of any nature whatsoever, it will be the primary responsibility of the contractor to contest the same. In case IITK is made party and is supposed to contest the case, IITK will be reimbursed for the actual expenses incurred towards Counsel Fee and other expenses which shall be paid in advance by the Contractor to IITK on demand. Further, the contractor shall ensure that no financial or Any other liability comes on IITK in this respect of any nature whatsoever and shall keep IITK indemnified in this respect.

8.12 Force Majeure:

If at any time, during the continuance of this contract, the performance in whole or in part by either party of any obligation under this contract is prevented or delayed by reasons of any war, hostility, acts of public enemy, civil commotion, sabotage, fires, floods, explosion, epidemics quarantine restriction, strikes, lockouts or acts of god (hereinafter referred to as events) provided notice of happenings of any such event, is served by party seeking concession to the other as soon as practicable, but within 21 days from the date of occurrence and termination thereof. Provided the

Party satisfies Institute adequately of the measures taken by it. Neither party shall, by reason of such event, be entitled to terminate this contract, nor shall either party have any claim for damages against the other in respect of such non-performance or delay in performance. Further, the services under the contract shall be resumed as soon as practicable after such event has come to an end or ceased to exist and the decision of Institute as to whether the services have to resume or not shall be final and conclusive, provided further, that if the performance in whole or in part of any obligation under this contract is prevented or delayed by reason of any such event for a period exceeding 60 days, Institute may at his option, terminate the contract.

8.13 Dispute resolution

1. The institute reserves the right to amend rules whenever and wherever considered necessary and appropriate. The same shall be intimated to the agency in due course.
2. Any dispute arising out of and in relation to this agreement shall be referred to the arbitration by sole arbitrator to be appointed by Director of the Institute. The arbitration would be conducted and governed by and under the provisions of Arbitration Act, 1996 and its amendments. Any legal dispute will be subject to jurisdiction of Kanpur Courts only and no other court shall have the jurisdiction.
3. Any dispute arising out of and in relation to this agreement shall be referred to the arbitration by sole arbitrator to be appointed by Director of the Institute. The arbitration would be conducted and governed by and under the provisions of Arbitration Act, 1996. Any legal dispute will be subject to jurisdiction of Kanpur Courts only and no other court shall have the jurisdiction.

8.14 Arbitration

1. Except as otherwise provided anywhere in this Agreement, if any dispute, difference, the question of disagreement or matter, whatsoever, arises between the parties, as to the meaning, operation or effect of the Agreement or out of or relating to the Agreement or breach thereof, the same shall be referred to a Sole Arbitrator, to be appointment by the Director of the Institute at the time of the dispute.
2. If the Arbitrator, to whom the matter is originally referred, dies or refuses to act or resigns for any reasons from the position of arbitration, it shall be lawful for the Director of the Institute to appoint another person to act as Arbitrator in the manner aforesaid. Such person shall be entitled to proceed with the reference from the stage at which it was left by its predecessor, provided both the parties consent to this effect, failing which, the arbitrator shall be entitled to proceed on the matter de- novo.
3. It is a term of the Agreement that the party invoking the arbitration shall specify all disputes to be referred to arbitration at the time of invocation of arbitration under the clause.
4. It is a term of the contract that the cost of arbitration shall be borne by the parties themselves.
5. The place of the arbitration shall be Kanpur Nagar, Uttar Pradesh, India.
6. Subject as aforesaid, the provisions of the Arbitration and Conciliation Act, 1996 and any

statutory modifications, amendments or re-enactment thereof and rules made thereunder and for the time being in force, shall apply to the arbitration proceeding under this clause.

7. Except as otherwise provided anywhere in this Agreement, the Arbitration proceedings shall be conducted in English and the Agreement shall be constructed, interpreted and governed by the law of India, for the time being in force.

8.15 Jurisdiction of Courts

The court(s) in Kanpur Nagar, Uttar Pradesh shall have the exclusive jurisdiction to trial all the disputes(s) between parties arising out this agreement.

8.16 E&M Works

1. In interpreting the specifications, the following order of decreasing importance shall be followed in case of contradictions:
 - (a) Schedule of quantities
 - (b) Technical specifications of the NIT
 - (c) Approved Drawing (If any)
 - (d) CPWD General specification Part – I (Internal) 2014, BIS Codes amended up to date, practices
 - (e) CPWD General Specifications for Electrical Works–Part-II(External), 2014 amended up to date.
 - (f) Relevant IS or other international code in case IS code is not available.
 - (g) Indian Electricity Act 2003 and Indian Electricity Rules 1956 amended up to date.
 - (h) Local Fire Regulations applicable at the place of installation. Relevant and applicable foreign standards and specifications amended up to date.
 - (i) Any other relevant act or rules and local by-laws.
2. Contractor will identify one of the supervisors for taking care of implementation of Safety systems.
3. Smoking is strictly prohibited at workplace.
4. Nobody is allowed to work without wearing safety helmet. Chinstrap of safety helmet shall be always on. Drivers, helpers and operators are no exception.
5. No one is allowed to work at or more than three meters height without wearing safety belt and anchoring the lanyard of safety belt to firm support preferably at shoulder level.
6. No one is allowed to work without adequate foot protection.
7. Usage of eye protection equipment shall be ensured when workmen are engaged for grinding, chipping, welding and gas-cutting. For other jobs as and when site safety co-coordinator insists eye protection has to be provided.
8. All safety appliances like Safety shoes, Safety gloves, Safety helmet, Safety belt, Safety goggles etc. shall be arranged before starting the job. .
9. All excavated pits shall be barricaded & barricading to be maintained till the backfilling is done. Safe approach to be ensured into every excavation.
10. Adequate illumination at workplace shall be ensured before starting the job at night.
11. All the dangerous moving parts of the portable / fixed machinery being used shall be adequately guarded.
12. Ladders being used at site shall be adequately secured at bottom and top. Ladders shall not be used as work platforms.
13. Material shall not be thrown from the height. If required, the area shall be barricaded and one person shall be posted outside the barricading for preventing the trespassers from entering the area.

14. Other than electricians no one is allowed to carry out electrical connections, repairs on electrical equipment or other jobs related thereto.
15. All electrical connections shall be made using 3 or 5 core cables, having a earth wire.
16. Inserting of bare wires for tapping the power from electrical sockets is completely prohibited.
17. A tools and tackles inspection register must be maintained and updated regularly.
18. Debris, scrap and other materials to be cleared from time to time from the workplace and at the time of closing of work every day.
19. All the unsafe conditions, unsafe acts identified by contractors, reported by site supervisors and / or safety personnel to be corrected on priority basis.
20. No children shall be allowed to enter the workplace.
21. All the lifting tools and tackles shall be stored properly when not in use.
22. Clamps shall be used on Return cables to ensure proper earthing for welding works.
23. Return cables shall be used for earthing.
24. All the pressure gauges used in gas cutting apparatus shall be in good working condition.
25. Proper eye washing facilities shall be made in areas where chemicals are handled.
26. Connectors and hose clamps are used for making welding hose connections.
27. All underground cables for supplying construction power shall be routed using conduit pipes.
28. Spill trays shall be used to contain the oil spills while transferring / storing them.
29. Tapping of power by cutting electric cables in between must be avoided. Proper junction boxes must be used.
30. All the E&M works shall be carried out as per direction and to the satisfaction of the Engineer-in-charge.
31. If the specifications for any item or its component are not available in the CPWD specifications cited above, relevant BIS specification as amended up to date shall be followed, whether or not the specific reference of a particular BIS specification has been made in this specification/ tender document.
32. Wherever any reference to any Indian Standard specification occurs in the document relating to this contract the same shall be inclusive of all amendments issued there to or revisions thereof, if any, up to the date of opening of tenders.
33. All materials should conform to relevant BIS specifications wherever the same exists in absence of stipulation in this tender document.
34. Where manufacturers furnish specific instructions / recommendations relating to the materials used in this job and/or their installation, covering points not specifically mentioned in these documents, these instructions shall be followed in all cases and shall be deemed to be included in the schedule of work whether they have been specifically mentioned or not.

35. All chase cuttings in the wall, for recessed conduits & boxes and drilling the holes shall be done with power operated machines only. No chase shall be allowed to be cut manually with the use of hammer & chisel.
36. All cuttings in cement plaster and brick shall be made good by using cement mortar 1:3 (1 part cement, 3-part coarse sand) The cut surfaces shall be repaired by an experienced mason only so as to match the repaired plaster with the original. All such repaired surfaces shall be cured for 3 to 4 days to keep the surfaces wet, using water spray machine (hand/motor operated) and avoid unnecessary flooding of the area.
37. The structural and architectural drawings shall at all times be properly co-related before executing any work.
38. For the purpose of recording measurements and preparing running account bills, the abbreviated nomenclature indicated in the publications Abbreviated Nomenclature of Items of DSR 2025 shall be accepted. The abbreviated nomenclature shall be taken to cover all the materials and operations as per the complete nomenclature of the relevant items in the agreement and relevant specifications. In case of items for which abbreviated nomenclature is not available in the aforesaid publication and also in case of extra and substituted items for which abbreviated nomenclature are not provided for in the agreement, full nomenclature of item shall be reproduced in the measurement books and bill forms for running account bills. For the final bill, however, full nomenclature of all the items shall be adopted in preparing abstract in the electronic measurement books and in the bill forms.
39. The following drawings must be submitted to Executive Engineer seven days of award of work.
 - (a) G.A and schematic drawings of MV switchgear/distribution /conduit layout/wiring drawing, Fire Alarm panel showing material and size of sheet steel/bus bars / inter connections and make and ratings of switchgear i/c details of protection, metering, indicating and inter lock etc.
 - (b) Conduit layout for lights, fans, socket outlets, telephone outlets, network & fire alarm system and sub mains showing size of conduits, no. of wires and size of wires in each run, location and size of accessories like junction boxes, ceiling boxes for hooks, draw boxes and switch boxed etc.
 - (c) Cable routing drawings showing details of size, type and no. of cables and mode of installation.
40. On completion of works and before issuance of completion certificate, the contractor submit completion drawings in the form of three complete set of originals (reproducible).
 - (a) As built GA and schematic drawings of MV panels, distributions boards, wiring, cable laying with sizes, earthing details, fire alarm panels, etc. showing material and size of sheet steel/bus bars/ connections and make and rating of switchgear i/c details of protection, meter indicating and interlocks etc.
 - (b) Technical literature, test certificates and operation and maintenance manuals required
41. Works Inspection and Testing of Equipment: Prior to dispatch of equipment the Institute reserves the right to inspect the same at the manufacturer's works and the contractor shall provide and secure every reasonable access and facility at the manufacturers works for inspection, for witness of all acceptance and routine tests as per relevant Indian Standards.

Contractor shall give a reasonable notice of about 15 days for the purpose of test, and witness of all major equipment's.

42. Pre-commissioning test: All routine tests shall be carried out on the electrical equipment. Protective & measuring devices should be checked for calibration of MCCB's/MCB's, panel & cable meggering, earthing measurements etc.

8.17 SCOPE OF WORKS FOR O&M OF SUBSTATIONS:

Day to day round the clock (24X7 hr) operation of 33/11 KV substation (1 no.), 11/0.433KV substations (12 no's) and PLC & AMF panels, LT panels of all DG sets inside the IIT Kanpur campus.

- 1.0 The contract is for round the clock operation and maintenance of 33/11 KV substation (1 Nos.) & 11/0.433 kV substation (12 Nos.) installed at various location of IIT Kanpur campus and 11/0.433 kV substation (1 No.) at NOIDA Centre IIT K (only maintenance). However, the Institute may also include other zones such as Street lights, metering and solar PV panels, cleaning/maintenance as per the requirement of the work during the contract period without any additional costing.
- 2.0 The work shall be carried out on all days, including Sunday and gazette holidays (if required) as Approved by the Institute.
- 3.0 The contractor shall engage the following labours only for substations operation on all days in shift duty round the clock, accordingly duty chart shall be prepared in last week of every month and submit in the office of Engineer In Charge:

Skilled labour (Trained Electrician): 05 (Five) (5 x 313 days)

Semi-Skilled labour (Trained Electrician): 10 (Ten) (10 x 313 days)

Unskilled labour (Trained Helper): 05 (Six) (5 x 313 days)

- 4.0 The above required man power shall not be decreased in any working day and deduction will be made by the current rate of supply for less number of man power including the contractor's profit.
- 5.0 The contractor shall assign duties and prepare the duty chart in advance for each month of the operators in consultation with the respective Engineer in Charges/Zonal In Charge for O&M of all above sub stations, electrical maintenance of street lighting or other zonal areas, solar PV plant cleaning & maintenance, energy metering work in various buildings in the campus.
- 6.0 The contractor shall arrange all the equipment's related to the work at his/her own expenses as per the scope of the work and covered under tender.
- 7.0 The Competent Authority through SE/EE/ZIC, IWD shall take stock of the inventory once in a month. The cost of short fall of the stocks, if any shall be recovered from the contractor at the purchase price.
- 8.0 The recovered materials should be deposited in the enquiry and handed over to the respective Engineer In Charge/Zonal In Charge (JE/AE), once every month for further disposal.
- 9.0 The contractor shall engage only experienced, skilled & technically sound manpower in the concerned area i.e for O&M of substations electrical installations, wiring, Street lighting, Solar Power & energy metering works etc. to execute good quality work.

- 10.0 The contractor shall be held responsible if there is unusually high quantum of wastage of materials. The Competent Authority through SE/EE/ZIC, IWD shall determine the legitimate wastage and recover the cost of excess wastage if deemed necessary.
- 11.0 The contractor shall ensure that the site of work is left clean and free of debris after the completion of work. Any complaint on this account from the user shall be viewed seriously.
- 12.0 The complaint shall be attended on first come first serve basis.
- 13.0 The contractor shall maintain up-to-date complaint register, record of dockets, indent book and other records as may be required by the Engineer In Charges or further reporting to higher authority/SE/EE, IWD. The maintenance of record shall not be kept pending beyond the weekend.
- 14.0 The Competent Authority through SE/EE/ZIC, IWD shall have the right to assign any other duty or work at any other building, if so required under contingent circumstances.
- 15.0 The contractor has to provide a dress code for all his workers.
- 16.0 Mechanism for checking and follow-ups of day-to-day complaints in whole campus comprising of all zones covered under the contract, making records of breakdowns/complaints/rectification and reporting to ZIC.

8.18 SPECIAL CONDITIONS FOR MATERIAL

1. The contractor shall at his own expense procure and provide all materials
2. The contractor shall procure all the materials in advance so that there is sufficient time to testing and approving of the materials and clearance of the same before use in work.
3. All materials brought by the contractor for use in the work shall be got approved with technical datasheet and checked from the Engineer-in-Charge or his authorized representative of the work on receipt of the same at site before use.
4. The contractor shall also employ necessary watch and ward establishment for the safe custody of materials at his own cost.
5. The contractor has to take the workmen compensation policy of the workers not covered under ESI and this policy have to be submitted to the Institute before the commencement of this work.
6. The daily attendance of the workers deployed shall have to be submitted to the Institute.
7. The contractor shall be fully responsible for the safe custody of materials brought by him issued to him even though the materials are under double lock key system.
8. The contractor has to follow all safety norms as laid down in National Building Code of India. All the workers shall be equipped with the required safety gadgets while working at site such as ISI marked helmets, Shoes and safety belts, gumboots, gloves etc.
9. The contractor has to deposit monthly EPF & ESIC to the concerned departments and monthly reimbursement of the same shall be submitted to the department
10. The contractor have to purchase and provide all safety gadgets such as ISI marked helmets, Shoes and safety belts, gumboots, gloves etc. to the workers at the commencement of the work under the contract.
11. The value of work shall be inclusive of the wages of the workers & supervisor, cost of tools and implements i/c contingent expenditure incidental to the work etc. Nothing extra shall be payable in addition to the monthly value of the contract except.
 - i) The difference in minimum wages applicable to the labours are revised by Govt. of India, subsequent to the date of submission of tender shall be paid by the contractor to the labour and reimbursed by the institute on production of claim.

- ii) The contribution of EPF& ESIC by the contractor shall be reimbursed on production of the receipt of deposit of the same in the office of competent authorities. Administrative expenses deposited by the contractor shall not be reimbursed.
12. There shall be a penalty in case of short supply of manpower. A penalty of Rs.150.00 per man shift shall be liable in case there is a shortage of manpower for more than 5 man shifts a month and this penalty shall increase to Rs.300.00 per man shifts if the shortage is more than 30 man shifts a month. In case the situation does not improve the contract shall be rescinded

B. Annual maintenance of 33/11KV substation (1 No.) & 11/0.433 KV substations (13 Nos.) (SS No. 1,2,3,4,5,6,7,8,9,10,11,12 & 1no. at NOIDA Extension Centre IIT K)

1. For supervision of electrical items of work, technical representatives and trained electrician of the respective disciplines will be required to be deployed for 1 no. 33/11kv substation and 12 no's 11/0.433kv substations installed at different locations in campus and 1 no. 11/0.433Kv substation at NOIDA Extension Centre.

- i) *The Engineer in charge shall have the right to assign any other duty or work at any other building, if so required under contingent circumstances.*
- ii) *Only the qualified and experienced staff for maintenance of 33KV/11KV/0.433KV equipment's shall be engaged. The contractor shall deploy below mentioned man power or more as required during routine preventive maintenance, servicing, during shutdowns of 33/11 KV & 11/0.433 KV substation or during any severe breakdowns in addition to the manpower specified in BOQ.*

S. N	Category	Manpower	Qualification and Experience
1	Engineer	1 Nos.	Degree with 5-7 years" experience & diploma with 10-12 years" experience in operation and maintenance of 11 kV and above substations
2	Supervisor	2 Nos.	Degree/ Diploma in Electrical Engineering along with Having license issued by the Director electrical safety with experience 7-10 years.
3	Mechanics/	10 Nos.	ITI Electrical Engineering along

.	Wireman		Having license issued by the Director electrical safety with experience 10-12 years.
4.	Unskilled	Who are experienced in Electrical works/ substation works at least 3 years, number of workers needed as per site requirement	

2. The following equipment's are covered under the scope of Annual Maintenance Contract for 33kV Sub-station with terms & conditions of maintenance.

Annexure-1

Annual maintenance contract for 33Kv Sub-station			
S.No.	Description	Qty	Unit
1	Annual maintenance of following capacity ONAN type transformers with complete accessories i/c temperature, oil indicators and control wiring, transformer oil centrifuging, BDV report etc. as required complete.		
a)	10 /12.5 MVA, 33/11KV out door type (TR1,TR2,TR3) along with OLTC	3.00	Nos.
2	Following capacity out door type-36KV HT breaker and isolator		
a)	SF 6 breaker 36 Kv normal current 1600 amp-2000amp, 3φ 50Hz complete with all accessories. i/c CT's / PT's (Main i/c,TR1 i/c,TR2 i/c,TR3 i/c)	4.00	set
b)	36 Kv 400Amps, isolator 3φ 50Hz complete with all accessories.(Panki incomer, Jawaharpuram incomer,Main incomer,TR1 incomer,TR2 incomer,TR3 incomer)	6.00	set
3	Lightening arresters set 33 KV grade (one set consist 3 lightening arresters) (TR1,TR2,TR3)	3.00	set
4	Overhead bus bar and insulators including panther ACSR conductor, Disc insulators, connecting clamps, complete with all accessories (Complete 33 KV yard.)	1.00	set

5	Annual maintenance of 11KV / HT switch gear panel set consisting following SF6/VCB, 1250 A , 3 ϕ 50Hz breaker, complete with metering equipment's control switches, rectifier unit, CT, PT, indicating lamps etc.		
a)	Set of 13 breakers(SF6 TR1 i/c,SS7,SS8,SS4,B/CTR1 & TR2/TR3) (VCB TR2 i/c,TR3 i/c,SS1,SS2,SS5,SS10,Bus coupler between TR-2 & TR-3)	13.00	set
6	Relay and control panel installed for Item 1, 2, 3, 4, 5 complete with control wiring and A,V meter etc.	1.00	set
7	AC & DC, DB panel 415V, 3 ϕ 50Hz / 110V DC, complete with all accessories and RTU panel SCADA monitoring and metering system	1.00	set
8	Float cum boost battery charger 110 Volt DC, 80 AH with batteries 2V,55 no's	1.00	set

Note: The item/ equipment are not mentioned in the above list but necessary for smooth functioning of sub-station shall also be covered in the scope of work.

- HT and LT panels of different ratings including control and switchgears
- Relays & Control system, Multi-function meters fixed into the panel.
- Rectifier unit (installed into the HT panels)
- APFC panel of different capacity installed at all 11Kv/0.433Kv sub-stations.
- RTU Panels installed at different sub stations
- AMF & PLC panels of all DG sets installed at different sub stations/locations

Summary of Inventory Details covered under the scope of Annual Maintenance Contract for 11/0.433kV Sub-stations

Annexure-2

1	Annual maintenance of following capacity ONAN type transformers 11/0.433KV with complete accessories i/c temperature, oil indicators and control wiring, transformer oil centrifuging, BDV report etc. as required complete.	
a)	2.0MVA transformers (2no's@SS1,3no's@SS4,3 no's@SS7,2no's@SS8 and 2.5 MVA transformers 2 no's@SS1, 2 no's@SS12)	14.00
b)	1.0MVA transformers (1no@SS2,2no's@SS3,2no's@SS5, 2no's@SS6,1no@SS9,2no's@SS10,1no@SS11,2no's@SS Noida and - 1.6 MVA transformers (1 no.@ss2,1no@SS9)	15.00
2	Annual maintenance of 11 KV HT switch gear panel set consisting following SF6/VCB,1250 A , 3 ϕ 50Hz breaker, complete with metering equipment's control switches, rectifier unit, CT, PT, indicating lamps etc.	69.00

	1.Set of 11 breakers@SS1 2.Set of 8 breakers@SS2 3. Set of 5 breakers@SS3 4.Set of 9 breakers@SS4 5.Set of 5 breakers@SS5 6. Set of 4 breakers@SS6 7.Set of 7 breakers@SS7 8.Set of 5 breakers@SS8 9.Set of 5 breakers@SS10 10. Set of 1 breakers@SS11 11.Set of 5@SS12 12. Set of 4 breakers @SS Noida Extension	
3	Annual maintenance of following capacity capacitor panels including all accessories in the panel i.e. APFC relay, SFU/FCU, contactor ,all meters, exhaust fan, switches, controlling system, indicating lamps etc. as required.	
a)	225 KVAR to 300 KVAR , 433 V, 3Φ, 50 Hz.(2@SS7, 1@SS11,2@SS2,2@SS3,2@SS6,2@SS10)	11.00
b)	325 KVAR to 600 KVAR, 433 V, 3Φ, 50 Hz..(4@SS1, 3@SS4,1@SS7.2@SS9,2@SS12) (2@SS5,2@SS8,2@Noida SS).	18.00
4	Annual maintenance of LT switch gear panel set consisting of different capacity ACB's, MCCB's SFU/FSU 1φ/ 3φ 50Hz, as incomer/ out going/ BUSCOUPLER complete with metering equipment's control switches, their interlocking and controlling, rectifier unit, CT, PT, indicating lamps etc. LT panels (2 no's @SS1,1 no.@SS2,1 no.@SS3 1 no.@SS4,1no.@SS5,1 no.@SS6,1 no.@SS7,1 no.@SS8, 1 no.@SS9,1 no.@SS10, 1 no.@SS11,1 no.@SS12,1 no.@SS Noida Ext.)	14.00

33/11 KV SUBSTATION Details covered under AMC					
Sr. No.	Name of SS	Equipment	Make	Rating	Qty.
1	33 KV	33 KV SF6 Circuit Breaker	ABB	36KV, Main i/c 1250A-1no. TR-1 i/c 1800A-1no. , TR-2-i/c 2000A-1no., TR-3 i/c 800A-1no.	4
2		33KV/110V Potential Transformer			2
3		33Kv, 1250A, Rated Short circuit current 25KA for 3 sec. Double Break Manual Operated Isolator			2
3		33Kv, 400A, Rated Short circuit current 31.5 KA for 1 sec. Double Break Manual Operated Isolator, MAKE ELPRO INTERNATIONAL LIMITED, YEAR 2000			4
4		600-300-150/5 Current Transformer		JMP/jyoti CT	4
5		SURGE MONITOR, YEAR 1997, MAKE ELPRO INTERNATIONAL LIMITED, Discharge current rating 10KA @ TR-1			1
5		SURGE MONITEOR, Discharge current rating 10KA, YEAR 1997, MAKE OBLUM ELECTRICAL INDUSTRIES PVT LT. @ TR-2 and TR-3			2
6		TR1: 10/12.5 MVA Transformer (33/11)	Areva		1
7		TR2: 10/12.5 MVA Transformer (33/11)	Crompton Greaves		1
8		TR3: 10/12.5 MVA Transformer (33/11)	Crompton Greaves		1
9		IC1: 11 KV SF6 Circuit Breaker	ABB	12KV, 1250A	1
10		IC2: 11 KV Vaccum Circuit Breaker	Crompton Greaves	12KV, 1250A	1
11		IC3: 11 KV Vaccum Circuit Breaker	Crompton Greaves	12KV, 1250A	1
12		Bus Coupler VCB b/w IC2 and IC3	Crompton Greaves	12KV, 1250A	1
13		Bus Coupler SF6 b/w IC1 and IC3	ABB	12KV, 1250A	1
14		11 KV SF6 CB O/G to SS-4	ABB	12KV, 1250A	1
15		11 KV SF6 CB O/G to SS-7	ABB	12KV, 1250A	1
16		11 KV SF6 CB O/G to SS-8	ABB	12KV, 1250A	1
17		11 KV VCB O/G to SS-1	Crompton Greaves	12KV, 1250A	1
18		11 KV VCB O/G to SS-10	Crompton Greaves	12KV, 1250A	1
19		11 KV VCB O/G to SS-5	Crompton Greaves	12KV, 1250A	1
20		11 KV VCB O/G to SS-2	Crompton Greaves	12KV, 1250A	1
21		11 KV VCB O/G to SPARE	Crompton Greaves	12KV, 1250A	1
22		RTU Panel scada monitering & metering	Synergy Systems		1
23		415V battery Charger	Chabhi Electricals		1
24		2V Battery	Exide		55

11/.433 KV SUBSTATION Details covered under AMC						
Sr. No.	Name of SS	Equipment		Make	Unit	Qty.
1	SS-1A	11 KV 1250A VCB i/c-1: From 33KV S/s		Siemens		1
2		11 KV 1250A VCB For TR1		Siemens		1
3		11 KV 1250A VCB For TR2		Siemens		1
4		11 KV 1250A VCB For TR3		Schneider Electric		1
5		11 KV 1250AVCB For TR4		Schneider Electric		1
6		11 KV 1250A VCB to old HT panel @SS1		ABB		1
7		11 KV 1250A VCB i/c-2 From SS2				1
8		TR1: 2.5 MVA 11KV/415V		Crompton Greaves		1
9		TR2: 2.5 MVA 11KV/415V		Crompton Greaves		1
10		SS#1 Part-A LT panel				
11		Bus Coupler ACB 4000A		ABB	Milestone	1
12		4000A ACB For TR1		ABB	Milestone	1
13		4000A ACB For TR2		ABB	Milestone	
14		400A MCCB	biodisel plant	ABB	Milestone	1
15		630A MCCB	Hall 3	ABB	Milestone	1
16		400A MCCB	TA-201	ABB	Milestone	1
17		400A MCCB	Vacant	ABB	Milestone	1
18		1600A ACB	DG House PLC-	ABB	Milestone	1
19		400A MCCB	SPARE	ABB	Milestone	1
20		630A MCCB	Sudo Basement	ABB	Milestone	1
21		250A MCCB	Spare	ABB	Milestone	1
22		400A MCCB	BSBE 250 KVAR	ABB	Milestone	1
23		630A MCCB	Hall 2	ABB	Milestone	1
24		250A MCCB	central store	ABB	Milestone	1
25		400A MCCB	Sudo	ABB	Milestone	1
26		800A ACB	Capacitor Pane	ABB	Milestone	1
27		400A MCCB	SAMTEL Building	ABB	Milestone	1
28		1250A ACB	ACMS	ABB	Milestone	1
29		1600A ACB	New AC Plant 1	ABB	Milestone	1
30		1600A ACB	New AC Plant 2	ABB	Milestone	1
31		630A MCCB	DG Set 320 KVA	ABB	Milestone	1
32		630A MCCB	Workshop 2	ABB	Milestone	1
33		630A MCCB	Western Lab	ABB	Milestone	1
34		1600A ACB	New AC Plant C	ABB	Milestone	1
35		1600A ACB	Wind Tunnel	ABB	Milestone	1
36		250A MCCB	Hydraulic Lab	ABB	Milestone	1
37		400A MCCB	Nano Science	ABB	Milestone	1
38		800A ACB	Capacitor Pane	ABB	Milestone	1
39		250A MCCB	SIDBI Bank	ABB	Milestone	1
40		630A MCCB	Faculty Building	ABB	Milestone	1
41		400A MCCB	AC Plant Nano	ABB	Milestone	1
42		400A MCCB	JEE Building	ABB	Milestone	1
43		400A MCCB	120 Vacant	ABB	Milestone	1
44		400A MCCB	Vacant	ABB	Milestone	1
45		RTU Panel		Synergy	Milestone	1
46		Light DB		ABB	Milestone	1

11/.433 KV SUBSTATION Details covered under AMC							
Sr. No.	Name of SS	Equipment		Make	Unit	Qty.	
1	SS-1B	Adapter panel i/c From new HT panel SS-1		ABB		1	
2		11 KV 1250A SF6 to SS4		ABB		1	
3		11 KV 1250A SF6 to SS4		ABB		1	
4		11 KV 1250A SF6 to SS7		ABB		1	
4		11 KV 1250A SF6 to SS12		ABB		1	
		SS#1 part-B LT panel					
7		Bus Coupler ACB 4000A		L&T	Milestone	1	
8		4000A ACB for TR3		L&T	Milestone	1	
9		4000A ACB for TR4		L&T	Milestone	1	
10		250A MCCB	High Voltage Lab	L&T	Milestone	1	
11		400A MCCB	Workshop 1	L&T	Milestone	1	
12		800A MCCB	Feeder Pillar 6	L&T	Milestone	1	
13		400A MCCB	Ceramic Lab	L&T	Milestone	1	
14		250A MCCB	Structure Lab	L&T	Milestone	1	
15		1000A ACB	New AC Plant 4	L&T	Milestone	1	
16		2000A ACB	Vacant	L&T	Milestone	1	
17		2000A ACB	Vacant	L&T	Milestone	1	
18		1000A ACB	Flexible Electronics	L&T	Milestone	1	
19		630A MCCB	BSBE Building 2 Sour	L&T	Milestone	1	
20		250A MCCB	New Terrace WLE	L&T	Milestone	1	
21		1250A ACB	Capacitor Bank	L&T	Milestone	1	
22		630A MCCB	I/c Old Panel TF-2	L&T	Milestone	1	
23		630A MCCB	TYPE-I (Old)	L&T	Milestone	1	
24		400A MCCB	FP-16 Air Strip	L&T	Milestone	1	
25		400A MCCB	HYD Lab	L&T	Milestone	1	
26		630A MCCB	Vehicle Dynamic Lab	L&T	Milestone	1	
27		1250A ACB	Vacant	L&T	Milestone	1	
28		400A MCCB	Street Light	L&T	Milestone	1	
29		2000A ACB	Vacant	L&T	Milestone	1	
30		630A MCCB	WLE Extension	L&T	Milestone	1	
31		2000A ACB	CEM Building	L&T	Milestone	1	
32		250A MCCB	Ext Old Core Lab	L&T	Milestone	1	
33		1250A ACB	Vacant	L&T	Milestone	1	
34		1250A ACB	Cap -3	L&T	Milestone	1	
35		800A MCCB	Vacant	L&T	Milestone	1	
36		100A MCCb	Vacant	L&T	Milestone	1	
37		RTU Panel		Synergy		1	
38		Light DB		ABB		1	

11/.433 KV SUBSTATION Details covered under AMC					
Sr. No.	Name of SS	Equipment	Make	Unit	Qty.
1	SS-2	11 KV SF6 CB IC1: From 33KV S/s	ABB	1250 A	1
2		11 KV SF6 CB For TR1	ABB	1250 A	1
3		11 KV SF6 CB For TR2	ABB	1250 A	1
4		11 KV SF6 CB For SS-6	ABB	1250 A	1
5		11 KV SF6 CB For SS-5	ABB	1250 A	1
6		11 KV SF6 CB For SS-3	ABB	1250A	1
7		11 KV SF6 CB For SS-1	ABB	1250A	1
8		11 KV SF6 CB SPARE	ABB		1
9		TR1: 1.6 MVA 11KV/415V	crompton greav		1
10		TR2: 1 MVA 11KV/415V	Areva		1
		LT panel			
11		Bus Coupler ACB 3200A	ABB	415V 16	1
12		3200A ACB for TR1	ABB		1
13		3200A ACB for TR2	ABB		1
14		250A M OLD SAC	ABB		1
15		1000A A vacant	ABB		1
16		630A M FP57	ABB		1
17		400A M Library	ABB		1
18		400A M FP 42	ABB		1
19		400A M New DG Panel	L&T		1
20		630A M Visitor Hostel	L&T		1
21		400A M Outreach	L&T		1
22		100A M VFA Pump	L&T		1
23		60A MC Street lightning	L&T		1
24		800A AC Cap Bank 2	ABB		1
25		400A M FP-46	ABB		1
26		400A M Media Asia Lab-C	ABB		1
27		630A M Girls Hostel	ABB		1
28		630A M Southern Lab	ABB		1
29		630A M FP-58	ABB		1
30		1000A A vacant	ABB		1
31		800A AC Hall 1	ABB		1
32		800A AC GH Tower A	ABB		1
33		100A M director residence	ABB		1
34		100A M 33 kv s/s dg light	ABB		1
35		800A AC Cap Bank 1	ABB		1
36		400A M library	ABB		1
37		800A AC hall 4	ABB		1
38		250A M new media lab-B	ABB		1
39		250A M new media lab-A	ABB		1
40		100A M new AMF panel DG	ABB		1
41		100A M S/s Light 122	ABB		1
42		400A M FP-44	ABB		1
43		400A M FP-58	ABB		1
44		630A M AC Plant Media Lab Block-B	ABB		1
45		630A M type-3 block-A	ABB		1
46		630A M AC Plant OLD SAC	ABB		1
47		630A M PEB Old SAC	ABB		1

11/.433 KV SUBSTATION Details covered under AMC						
Sr. No.	Name of SS	Equipment		Make	Unit	Qty.
1	SS-3	11 KV VCB IC1: From SS-2		Crompton Greaves	1250 A	1
2		11 KV VCB IC2: From SS-4		Crompton Greaves	1250 A	1
3		11 KV VCB For TR1		Crompton Greaves	1250 A	1
4		11 KV VCB For TR2		Crompton Greaves	1250 A	1
5		11 KV VCB For SS-6		Crompton Greaves	1250 A	1
6		TR1: 1 MVA 11KV/415V		Areva		1
7		TR2: 1 MVA 11KV/415V		Areva		1
		LT panel				
8		Bus Coupler ACB 1600A		L&T	415V	1
9		1600A ACB for TR1		L&T		1
10		1600A ACB for TR2		L&T		1
11		800A ACB for AMF		L&T		1
12		400A MCCB	FP-25	L&T		1
13		200A MCCB	IWD Store	L&T		1
14		250A MCCB	FP-59	L&T		1
15		630A MCCB	FP-30	L&T		1
16		200A MCCB	IWD Office	L&T		1
17		200A MCCB	Type III FP HP359 Left Side	L&T		1
18		400A MCCB	FP 28	L&T		1
19		630A MCCB	Capacitor Panel 1(300KVAr)	Milestone		1
20		630A MCCB	FP-21A	L&T		1
21		400A MCCB	FP-21	L&T		1
22		200A MCCB	FP-3&4	L&T		1
23		250A MCCB	FP-23	L&T		1
24		200A MCCB	FP-1&2	L&T		1
25		630A MCCB	Capacitor Panel 2 (300KVAr)	Milestone		1
26		RTU Panel		Synergy		1
27		Light DB		ABB		1

11/.433 KV SUBSTATION Details covered under AMC						
Sr. No.	Name of SS	Equipment		Make	Unit	Qty.
		11 KV SF6 CB NSM TR-1@SS-11		ABB		1
1		11 KV SF6 CB IC1: From 33 KV S/s		ABB		1
2		11 KV SF6 CB IC2: From SS-1		ABB		1
3		11 KV SF6 CB For TR1 @SS9 (New AC Plant)		ABB		1
4		11 KV SF6 CB For TR2@SS9 (New AC Plant)		ABB		1
5		11 KV SF6 CB For SS-3		ABB		1
6		11 KV SF6 CB For TR1@SS4		ABB		1
7		11 KV SF6 CB For TR2@SS4		ABB		1
8		11 KV SF6 CB For TR3-CC		ABB		1
9		TR1: 2 MVA 11KV/415V		Crompton Greaves	Milestone	1
10		TR2: 2 MVA 11KV/415V		Crompton Greaves	Milestone	1
11		TR3: 2 MVA 11KV/415V		Areva	Milestone	1
		LT panel				
14		1600 A ACB CB for TR1(New AC Plant)		ABB	Milestone	1
15		1600 A ACB CB for TR2(New AC Plant)		ABB	Milestone	1
16		4000 A ACB CB for TR1		ABB	Milestone	1
17		4000 A ACB CB for TR2		ABB	Milestone	1
18		4000 A ACB CB for TR3		L&T	Milestone	1
19		Bus Coupler ACB 1600A		G.E.	Milestone	1
20		Bus Coupler ACB 1600A		G.E.	Milestone	1
21		800A ACB	CSEB	G.E.	Milestone	1
22		800A ACB	ACES & Rajeev Motwani	G.E.	Milestone	1
23		800A ACB	DG Kesa S/s-4	G.E.	Milestone	1
24		800A ACB	ME Extensio	G.E.	Milestone	1
25		630A MCCB	Lasser Lab R No.116	G.E.	Milestone	1
26		630A MCCB	Northern Lab NL-1	G.E.	Milestone	1
27		400A FSU	F.B. West	G.E.	Milestone	1
28		630A MCCB	Vacant	G.E.	Milestone	1
29		400A MCCB	Low Temp Lab	G.E.	Milestone	1
30		200A MCCB	Library AHU	G.E.	Milestone	1
31		2500A ACB	PAC New Stair Case	L&T	Milestone	1
32		2500A ACB	UPS	L&T	Milestone	1
33		4000A ACB	Bus Coupler Tie Feeder	L&T	Milestone	1
34		3200A ACB	DG Incomer	L&T	Milestone	1
35		1600A ACB	Capacitor Panel	L&T	Milestone	1
36		800A ACB	CC Basement PAC	L&T	Milestone	1
37		200A FSU	Helicopter 2 Source	G.E.	Milestone	1
38		200A FSU	Computer Centre	G.E.	Milestone	1
39		200A FSU	Liquid Nitrogen Plant	L&T	Milestone	1
40		200A MCCB	Library	G.E.	Milestone	1
41		400A FSU	A.E. Lab	G.E.	Milestone	1
42		400A MCCB	DTW-11	G.E.	Milestone	1
43		630A MCCB	Capacitor Panel	G.E.	Milestone	1
44		400A FSU	Env. AC Plant	G.E.	Milestone	1
45		400A FSU	F.B. East	G.E.	Milestone	1
46		630A MCCB	Western Building Ext.	G.E.	Milestone	1
47		400A MCCB	Southern Lab	G.E.	Milestone	1
48		630A MCCB	Chem Engg-2	G.E.	Milestone	1
49		400A FSU	Aero Lab	G.E.	Milestone	1
50		800A ACB	Rajeev Motwani 2Source	G.E.	Milestone	1
51		800A ACB	Core Lab	G.E.	Milestone	1
52		800A ACB	Nuclear Lab	G.E.	Milestone	1
53		400A FSU	To Auto C/o No.1	G.E.	Milestone	1
54		1250A ACB	Capacitor Panel-2	ABB	Milestone	
55		1250A ACB	Capacitor Panel-1	ABB	Milestone	
56		RTU Panel		Synergy		1
57		Light DB		C&S		1

11/.433 KV SUBSTATION Details covered under AMC						
Sr. No.	Name of S	Equipment		Make	Unit	Qty.
1	SS-5	11 KV SF6 CB IC1: From 33 KV S/s		ABB	Milestone	1
2		11 KV SF6 CB IC1: From SS-2		ABB	Milestone	1
3		11 KV SF6 CB For TR1		ABB	Milestone	1
4		11 KV SF6 CB For TR2		ABB	Milestone	1
5		11 KV SF6 CB For SS-8		ABB	Milestone	1
6		TR1: 1 MVA 11KV/415V		Alstom	Milestone	1
7		TR2: 1 MVA 11KV/415V		GEC-1996	Milestone	1
		LT panel				
8		1600A ACB for TR1		G.E.	Milestone	1
9		1600A ACB for TR2		G.E.	Milestone	1
10		Bus Coupler ACB 1600A		G.E.	Milestone	1
11		1250 A ACB	Multi. Res Hostel RA	L&T	Milestone	1
12		200A MCCB	DTW-9	L&T	Milestone	1
13		200A FSU	Street Light	G.E.	Milestone	1
14		1250A MCCB	Hall-8	Legrand	Milestone	1
15		400A FSU	Hall-3	ABB	Milestone	1
16		800A MCCB	Capacitor Panel 2	ESS AAR	Milestone	1
17		200A FSU	New Tube Well	G.E.	Milestone	1
18		400A MCCB	Hall-2	ABB	Milestone	1
19		400A FSU	Sports Complex Hall-1	G.E.	Milestone	1
20		63A FSU	C/O Switch Light	G.E.	Milestone	1
21		630A MCCB	ICICI Bank Hall-7	ABB	Milestone	1
22		400A FSU	Hockey Ground	G.E.	Milestone	1
23		630A FSU	To SS-8	ABB	Milestone	1
24		1250A ACB	Hall-9	L&T	Milestone	1
25		1250A ACB	Multi Res Flats	L&T	Milestone	1
26		400A FSU	R.A. Hostel	G.E.	Milestone	1
27		400A FSU	New SAC	G.E.	Milestone	1
28		315A FSU	Ganga Barrage Pump	G.E.	Milestone	1
29		400A FSU	Hall-7	G.E.	Milestone	1
30		400A FSU	SBRA Multistorey	G.E.	Milestone	1
31		315A FSU	Swimming Pool	G.E.	Milestone	1
32		630A FSU	FP-52	G.E.	Milestone	1
33		400A FSU	Hall-5	G.E.	Milestone	1
34		63A FSU	S/s Light	G.E.	Milestone	1
35		800A MCCB	Capacitor Panel 1	ESS AAR	Milestone	1
36		RTU Panel		Synergy		1
37		Light DB		ABB		1

11/.433 KV SUBSTATION Details covered under AMC						
Sr. No.	Name of SS	Equipment		Make	Unit	Qty.
1	SS-6	11 KV SF6 CB IC1: From SS-3		ABB	1250 A	1
2		11 KV SF6 CB IC1: From SS-2		ABB	1250 A	1
3		11 KV SF6 CB For TR1		ABB	1250 A	1
4		11 KV SF6 CB For TR2		ABB	1250 A	1
5		TR1: 1 MVA 11KV/415V		Crompton Greaves		1
6		TR2: 1 MVA 11KV/415V		Crompton Greaves		1
		LT panel				
7		2000A ACB Buscoupler		ABB	415V	1
8		2000A ACB for TR1		ABB		
9		2000A ACB for TR2		ABB		
10		630A MCCB	Capacitor Panel 1	G.E.		
11		200A FSU	New Marriage Hall	G.E.		
12		125A MCCB	RFID IIT Gate	ABB		
13		125A MCCB	Street Light Timer LT Panel	ABB		
14		800 A MCCB	Vacant	ABB		
15		630A MCCB	Interconnection SS-2	ABB		
16		630A MCCB	Type-II	ABB		1
17		400A FSU	FP-38	ABB		1
18		400A FSU	Fp-575	ABB		1
19		1600A ACB	Capacitor Panel 2	G.E.		1
20		400A FSU	ACES Type-II	ABB		1
21		200A FSU	Type-II Shops	ABB		1
22		400A FSU	ACES Type-III	ABB		1
23		400A FSU	Type III Old	ABB		1
24		400A MCCB	FP-40	L&T		1
25		250A MCCB	ACES Type-IV	L&T		1
26		250A MCCB	Booster Pump-7	L&T		1
27		250A MCCB	DG Supply for Street Light	ABB		1
28		800A MCCB	Type-II Multi Storeyed Fl	L&T		1
29		RTU Panel		Synergy		1
30		Light DB		ABB		1

11/.433 KV SUBSTATION Details covered under AMC						
Sr. No.	Name of SS	Equipment		Make	Unit	Qty.
1	SS-7	11 KV SF6 CB IC1: From 33 KV S/s		ABB	1250 A	1
2		11 KV SF6 CB IC1: From SS-1		ABB	1250 A	1
4		11 KV SF6 CB For TR1		ABB	1250 A	1
5		11 KV SF6 CB For TR2		ABB	1250 A	1
6		11 KV SF6 CB For TR3		ABB	1250 A	1
7		11 KV SF6 CB For SPARE		ABB	1250 A	1
8		11 KV SF6 CB For NWTF		ABB	1250 A	1
10		TR1: 2 MVA 11KV/415V		ArevA		1
11		TR2: 2 MVA 11KV/415V		ArevA		1
12		TR3: 2 MVA 11KV/415V		crompton greaves		1
		LT panel				
13		4000A ACB Buscoupler		L&T	415V	1
14		4000A ACB Buscoupler		L&T	415V	1
15		4000A ACB for TR1		L&T		1
16		4000A ACB for TR2		L&T		1
17		4000A ACB for TR3		L&T		1
18		2000A ACB	diamond Jublee Bld	L&T		1
19		1600A ACB	MicroAMF	L&T		1
20		400A MCCB	NWTF Suction	L&T		1
21		1600A ACB	SPare	L&T		1
22		630A MCCB	diamond Jublee Fire Panel	L&T		1
23		630A MCCB	Cap-3	L&T		1
24		1600A ACB	CPWD AeroEngg Lab Science	L&T		1
25		630A MCCB	hypersonic test faciloty	L&T		1
26		630A MCCB	SIDBI	L&T		1
27		1600A ACB	Aerosole	L&T		1
28		1250A MCCB	Earth Science	L&T		1
29		1250A ACB	Source 2 ECL	L&T		1
30		1250A ACB	Cap -2	L&T		1
31		1250A ACB	Cap-1	L&T		1
32		1600A ACB	Micro Building	ABB		1
33		1600A ACB	NWTF Suction	ABB		1
34		1600A ACB	Aerosol Building	ABB		1
35		800A ACB	SIDBI	ABB		1
36		1250A ACB	Env. Switch Room	ABB		1
37		800A ACB	Core Lab	ABB		1
38		630A MCCB	Aero Lab Speed	ABB		1
39		630A MCCB	Helicopter Building	ABB		1
40		630A MCCB	New Core Lab	ABB		1
41		630A MCCB	IME Switch Room	ABB		1
42		400A MCCB	ER Lab	ABB		1
43		400A MCCB	IME AC Plant	ABB		1
44		250A MCCB	S/S Light & TW	ABB		1
45		400A MCCB	250 Kvar APFC-1	ABB		1
46		800A ACB	Core Lab	ABB		1
47		400A MCCB	250 Kvar APFC-2	ABB		1
48		250A MCCB	NWTF-1	ABB		1
49		400A MCCB	Air Strip	ABB		1
50		400A MCCB	Env. AC Plant	ABB		1
51		630A MCCB	Aero Workshop	ABB		1
52		630A MCCB	Aero High Speed	ABB		1
53		RTU Panel				
54		Light DB				

11/.433 KV SUBSTATION Details covered under AMC						
Sr. No.	Name of SS	Equipment		Make	Unit	Qty.
1	SS-8	11 KV SF6 CB IC1: From 33 KV S/s		ABB		1
2		11 KV SF6 CB IC1: From SS-5		ABB		1
3		11 KV SF6 CB SPARE		ABB		1
4		11 KV SF6 CB For TR1		ABB		1
5		11 KV SF6 CB For TR2		ABB		1
6		TR1: 2 MVA 11KV/415V		crompton	Milestone	1
7		TR2: 2 MVA 11KV/415V		crompton	Milestone	1
		LT panel				
8		4000A ACB for TR1		L&T	Milestone	1
9		4000A ACB for TR2		L&T	Milestone	1
10		4000A ACB Buscoupler		L&T	Milestone	1
11		400A MCCB	From Solar S/s	L&T	Milestone	1
12		630A MCCB	FP-7	L&T	Milestone	1
13		400A MCCB	Storm Water Pump	L&T	Milestone	1
14		630A MCCB	interconnection SS-5	L&T	Milestone	
15		630A MCCB	Hall-10	L&T	Milestone	1
16		200A MCCB	S/L FP S/s DB	L&T	Milestone	1
17		800A ACB	Hall-8	L&T	Milestone	1
18		3200A ACB	SPARE	L&T	Milestone	
19		1250A ACB	Capacitor Panel 1	L&T	Milestone	1
20		3200A ACB	Hall 12A	L&T	Milestone	1
21		3200A ACB	Hall-12B	L&T	Milestone	1
22		630A MCCB	Hall-11	L&T	Milestone	1
23		3200A ACB	Hall-9	L&T	Milestone	1
24		200A MCCB	Street Light	L&T	Milestone	1
25		1250A ACB	Capacitor Panel 2	L&T	Milestone	1
26		400A MCCB	Solar Energy Enclave	L&T	Milestone	1
27		400A MCCB	Vacant	L&T	Milestone	1
28		400A MCCB	DTW-12	L&T	Milestone	1
29		400A MCCB	Vacant	L&T	Milestone	1
30		800A ACB	International Hosuing Building	L&T	Milestone	1
31		RTU Panel				1
32		Light DB				1

11/.433 KV SUBSTATION Details covered under AMC						
Sr. No.	Name of SS	Equipment		Make	Unit	Qty.
3	SS-9	TR1: 1.6 MVA 11KV/415V		Crompton	Milestone	1
4		TR2: 1 MVA 11KV/415V		Areva	Milestone	1
		LT panel				
5		1600A ACB Buscoupler		L&T	Milestone	1
6		1600A ACB	DG Incomer 2	ABB	Milestone	1
7		1250A ACB	Cond. Pump 4	L&T	Milestone	1
8		1250A ACB	Cond. Pump 2	L&T	Milestone	1
9		1250A ACB	Cond. Pump 1	L&T	Milestone	1
10		200A MCCB	Cond. Pump 3	L&T	Milestone	1
11		630A MCCB	CH. Pump 2	L&T	Milestone	1
12		200A MCCB	CH. Pump 1	L&T	Milestone	1
13		630A MCCB	CT-1	L&T	Milestone	1
14		630A MCCB	CT-2	L&T	Milestone	1
15		630A MCCB	CT-3	L&T	Milestone	1
16		630A MCCB	Shoftning Plant	L&T	Milestone	1
17		630A MCCB	CH. Pump 4	L&T	Milestone	1
18		630A MCCB	COND-3	L&T	Milestone	1
19		630A MCCB	Plant DB	L&T	Milestone	1
20		400A MCCB	Switchroom DB	L&T	Milestone	1
21		400A MCCB	CH. Pump 3	L&T	Milestone	1
22		630A MCCB	Cond. Pump 3	L&T	Milestone	1
23		800A MCCB	Unit 1	L&T	Milestone	1
24		800A MCCB	Unit 4	L&T	Milestone	1
25		630A MCCB	Capacitor Panel 1	ESS AAR	Milestone	1
26		630A MCCB	Main LT Panel	L&T	Milestone	1
27		630A MCCB	Vacant	L&T	Milestone	1
28		1600A ACB	Nursery 3	L&T	Milestone	1
29		630A MCCB	Type-1 Old AC Plan	L&T	Milestone	1
30		800A MCCB	CH-Pump 5	L&T	Milestone	1
31		800A MCCB	COND. Pump 5	L&T	Milestone	1
32		1600A ACB	CT-5	L&T	Milestone	1
33		630A MCCB	CT-4	L&T	Milestone	1
34		800A MCCB	IWD office -II	L&T	Milestone	1
35		800A MCCB	FP-60	L&T	Milestone	1
36		1600A ACB	DG Incomer 1	L&T	Milestone	1
37		630A MCCB	Capacitor Panel 2	L&T	Milestone	1
38		800A MCCB	AC Plant Unit-3	L&T	Milestone	1
39		800A MCCB	AC Plant Unit-2	L&T	Milestone	1
40		RTU Panel		Synergy	Milestone	1
41		Light DB		ABB	Milestone	1

11/.433 KV SUBSTATION Details covered under AMC						
Sr. No.	Name of Ss	Equipment		Make	Unit	Qty.
1	SS-10	11 KV 1250A VCB I/C1: From 33 KV S/s		Crompton Greaves		1
3		11 KV 1250A VCB For TR1		Crompton Greaves		1
4		11 KV 1250A VCB For TR2		Crompton Greaves		1
2		11 KV 1250A VCB SPARE for i/c-2		Crompton Greaves		1
2		11 KV 1250A VCB SPARE		Crompton Greaves		1
5		TR1: 1 MVA 11KV/415V		Crompton Greaves		1
6		TR2: 1 MVA 11KV/415V		Crompton Greaves		1
		LT panel				
7		2000A ACB for TR1		C&S	Milestone	1
8		2000A ACB for TR2		C&S	Milestone	1
9		2000A ACB Buscoupler		C&S	Milestone	1
10		1250A ACB	RA Tower	C&S	Milestone	1
11		1250A ACB	New RA Tower	C&S	Milestone	1
12		200A MCCB	New Smart City	C&S	Milestone	1
13		630A MCCB	SBRA AA+Z Block	C&S	Milestone	1
14		200A MCCB	S/s Light	C&S	Milestone	1
15		630A MCCB	Multistorey C+D	C&S	Milestone	1
16		630A MCCB	Cap. Panel 1	C&S	Milestone	1
17		630A MCCB	C/O Switch S/s	C&S	Milestone	1
18		630A MCCB	Vacant	C&S	Milestone	1
19		630A MCCB	Vacant	C&S	Milestone	1
20		630A MCCB	Vacant	C&S	Milestone	1
21		630A MCCB	Vacant	C&S	Milestone	1
22		400A MCCB	Vacant	C&S	Milestone	1
23		400A MCCB	Vacant	C&S	Milestone	1
24		200A MCCB	Vacant	C&S	Milestone	1
25		200A MCCB	Vacant	C&S	Milestone	1
26		400A MCCB	Vacant	C&S	Milestone	1
27		400A MCCB	Vacant	C&S	Milestone	1
28		630A MCCB	Vacant	C&S	Milestone	1
29		630A MCCB	Vacant	C&S	Milestone	1
30		630A MCCB	Vacant	C&S	Milestone	1
31		1250A ACB	SPARE 1	C&S	Milestone	1
32		1250A ACB	SPARE 2	C&S	Milestone	1
33		800A ACB	HALL-6 GH	C&S	Milestone	1
34		630A MCCB	Multistorey A+B	C&S	Milestone	1
35		630A MCCB	Multistorey D	C&S	Milestone	1
36		630A MCCB	Cap. Panel 2	C&S	Milestone	1
37		RTU Panel		Synergy		1
38		Light DB		C&S		1

11/.433 KV SUBSTATION Details covered under AMC						
Sr. No.	Name of SS	Equipment		Make	Unit	Qty.
1	SS-11	11 KV 1250A VCB i/c From SS-4 & o/g to TR-1		crompton	milestone	1
3		TR1: 1 MVA 11KV/415V		crompton	milestone	1
		LT panel				
4		2000A ACB for TR1		ABB	milestone	1
5		2000A ACB Buscoupler		ABB	milestone	1
6		800A ACB	DG-1 Incomer 500KVA	ABB	milestone	1
7		800A ACB	DG-2 Incomer 500KVA	ABB	milestone	1
8		2000A ACB	New Data Centre NSM	ABB	milestone	1
9		800A ACB	Cap. Panel	ABB	milestone	1
10		800A ACB	To/ From SS-9	ABB	milestone	1
11		PLC			milestone	2
12		Light DB		C&S		1

11/.433 KV SUBSTATION Details covered under AMC						
Sr. No.	Name of SS	Equipment		Make	Unit	Qty.
1	SS-12	11 KV 1250A VCB i/c 1 From SS-1		Crompton		1
3		11KV 1250A VCB for TR1		Crompton		1
4		11KV 1250A VCB for TR2		Crompton		1
5		11KV 1250A VCB for SPARE		Crompton		1
2		11 KV 1250A VCB spare for i/c-2		Crompton		1
6		TR1: 2.5 MVA 11KV/415V		Crompton		1
7		TR2: 2.5 MVA 11KV/415V		Crompton		1
8		5000A 415V ACB CB For TR-1		legrand	Neptune	1
9		5000A 415V ACB CB For TR-2		legrand	Neptune	1
10		5000A 415V ACB CB For Buscoupler		legrand	Neptune	1
11		1250A MCCB	Capacitor Panel 1	legrand	Neptune	1
12		250A MCCB	SPARE	legrand	Neptune	1
13		630A MCCB	Chiller Pump AC-1	legrand	Neptune	1
14		400A MCCB	SPARE	legrand	Neptune	1
15		400A MCCB	SPARE	legrand	Neptune	1
16		800A ACB	DG Panel Secondary Chilled	legrand	Neptune	1
17		1600A ACB	Chiller Plant AC-3	legrand	Neptune	1
18		1600A ACB	Chiller Plant	legrand	Neptune	1
19		1600A ACB	Chiller Plant-1	legrand	Neptune	1
20		1600A ACB	Ext. Fire Dynamic Lab	legrand	Neptune	1
21		1600A ACB	Chiller Plant 3A	legrand	Neptune	1
22		1250A ACB	Chiller Plant 4	legrand	Neptune	1
23		800A ACB	SPARE	legrand	Neptune	1
24		400A MCCB	SPARE	legrand	Neptune	1
25		400A MCCB	CT Fan	legrand	Neptune	1
26		630A MCCB	Condensor Water Pump	legrand	Neptune	1
27		1250A MCCB	Capacitor Panel 2	legrand	Neptune	1
29		Light DB				1

11/.433 KV SUBSTATION Details covered under AMC						
Sr. No.	Name of SS	Equipment		Make	Unit	Qty.
1	SS- NOI DA Centre	11 KV VCB IC from UPPCL meter panel		SIEMENS	SIEMENS	1
3		11 KV VCB O/G to TR- 1		SIEMENS	SIEMENS	1
4		11 KV VCB O/G to TR- 2		SIEMENS	SIEMENS	1
2		11 KV VCB spare		SIEMENS	SIEMENS	1
2		TR- 1 1 MVA 11KV/ 433V		Crompton		1
5		TR- 1 1 MVA 11KV/ 433V		Crompton		1
6		2000 Amp ACB for TR-1		ABB	RST	1
		2000 Amp ACB for TR-2		ABB	RST	1
7		2000 Amp ACB for Bus coupler		ABB	RST	1
8		1000 Amp ACB for I/C from AMF panel		ABB	RST	1
9		1250 Amp ACB for	O/G to Innovation block Main panel supply	ABB	RST	1
10		1250 Amp ACB for	Spare	ABB	RST	1
11		800 Amp ACB for	O/G to Guest house main panel	ABB	RST	1
12		800 Amp ACB for	O/G to Innovation block A. C panel supply	ABB	RST	1
13		800 Amp ACB for	O/G to office block (N.T.A) Main panel	ABB	RST	1
14		100 Amp TP MCCB	O/G to SIIC office UPS supply	ABB	RST	1
15		200 Amp TP MCCB	O/G to SIIC office A.C DB supply	ABB	RST	1
16		200 Amp TP MCCB	O/G to SIIC office Main supply	ABB	RST	1
17		630 Amp TP MCCB	O/G to Capacitor panel-1 350 KVAR	ABB	RST	1
18		100 Amp TP MCCB	Sub station panel	ABB	RST	1
19		200 Amp TP MCCB	O/G to Offgrid Lab	ABB	RST	1
20		200 Amp TP MCCB	O/G to Street light panel	ABB	RST	1
21		400 Amp TP MCCB	O/G to office block (N.T.A) A.C panel	ABB	RST	1
22		100 Amp TP MCCB	Spare	ABB	RST	1
23		200 Amp TP MCCB	Spare	ABB	RST	1
24		200 Amp TP MCCB	O/G to main Fire Panel Basement	ABB	RST	1
25		630 Amp TP MCCB	O/G to Capacitor panel-2 350 KVAR	ABB	RST	1
26		100 Amp TP MCCB	Spare	ABB	RST	1
27		400 Amp TP MCCB	O/G-1 to Main pump panel	ABB	RST	1
28		400 Amp TP MCCB	O/G-2 to Main pump panel	ABB	RST	1
29		400 Amp TP MCCB	Spare	ABB	RST	1
30		350 KVAR PANEL		EPCOS	RST	2
31		AMF PANEL			RST	1
32		800 Amp FP MCCB	Incomer from mains	ABB	RST	1
33		800 Amp FP MCCB	DG Incomer	ABB	RST	1
34		800 Amp FP MCCB	133	ABB	RST	
35		24 V DC Battery charger			RST	

Summary of Inventory Details covered under the scope of Annual Maintenance Contract for PLC Panel, AMF Panel and LT Panels of DG sets

Annexure-3

S.No.	Description	Quantity	Unit
1	Annual maintenance of PLC panels of DG and its LT distribution panels installed at all the sub-stations and installed at various locations in IIT Kanpur campus and Noida extension centre. complete Details of PLC panel and AMF panel with its LT panel total 16 no's details as per below.		
a)	SS#1 :1 No. PLC panel with LT distribution of 2x320KVA DG, 1 no. AMF with LT distribution panel of 1x320KVA DG ,1 no. AMF with LT distribution panel of 1x250KVA DG and 1x500 KVA.		
b)	SS#2 :2 No. AMF with LT distribution panel of 2x500KVA DG		
c)	SS#3 :1 No. AMF with LT distribution panel of 1x250KVA DG		
d)	SS#4 :1 No. PLC panel with LT distribution of 3x500KVA DG, 1 no AMF panel with LT distribution of 3x320KVA DG ,1 no. AMF with LT distribution panel of 1x500KVA DG		
e)	Advance Imaging centre:1 no. AMF with LT distribution panel of 1x250KVA DG		
f)	SS#9 :2 No. AMF with LT distribution panel of 2x750KVADG.		
g)	SS#11 :1 No. PLC panel with LT distribution of 2x500KVA DG, 1 no. AMF with LT distribution panel of 1x500KVA DG		
h)	RA tower:1 No. AMF panel with LT distribution of 1x200KVA DG		
i)	Hall12:1 No. AMF panel with LT distribution of 1x250KVA DG		
j)	Tyep-2 Apatrment:1 No. AMF panel with LT distribution of 1x50KVA DG, 1 no. AMF panel with LT		
k)	Studio Apartment:1 No. AMF panel with LT distribution of 1x250 KVA DG,		
l)	Noida Extension Centret:1 No. AMF panel with LT distribution of 1x500KVA DG,	19	Set

NOTE: Any item / instrument not mentioned above but necessary for smooth functioning of sub-stations shall be covered in the scope of work.

3. Schedule for Maintenance

1	Transformers	weekly	Clean the transformer with cotton rags. 2. Check that temperature rise is reasonable. 3. Check the oil level of transformer. 4. Check that air passages are free check colour of silica gel if required replace silica gel or breather 5. Buchholz relay oil level , leakage
---	---------------------	--------	---

		Monthly	1. HT and LT Bushing: Examine for cracks and dirt deposits, clean or replace. 2. Oil in Transformer: Check for dielectric strength and water content. 3. Cooling fan bearings, motors and operating mechanism: Lubricate bearings, Examine contacts, check manual control and interlocks. 4 Check oil leakage at HT bushings and cleaning 5 Check relay settings of HT & LT breakers and note down the relay setting values in the report.
		Half yearly	1. Oil cooler : Test for pressure, leakage 2. Oiling and greasing of operating mechanism etc
		yearly	1. Oil in Transformer: Check for acidity and sludge, filter if required. 2. Gasket joints: Tighten the bolts evenly to avoid uneven pressure. 3. Cable boxes: Check for sealing arrangements for filling holes. Examine: compound for cracks. Replace the gasket if leaking. 4. Relay, Alarms, their circuits etc.: Examine relay and alarm contacts, their operation, fuse : etc, check relay accuracy etc. Clean the components and: replace contacts and fuses if necessary. 5. Earth resistance: Record the value of earth resistance of earth pits. 6. Silica gel: Replacement of silica gel and cup oil. 7. Buchholz relay magnetic oil gauge: Check its operation, control circuit and repair/replace required.
2	Out door type SF 6 Breaker and isolators	weekly	1. Checking of Indicating lamps, gas pressure, earthing connection etc. 2. Cleaning of metallic enclosure.
		Monthly	1. Checking of operation. 2. Checking of SF6 pressure checking. 3. Cleaning of polycons of breaker. 4. Check relay settings of HT & LT breakers and note down the relay setting values in the report.
		Half yearly	1. Cleaning of contacts of isolators, and inserting petroleum jelly in contacts, 2. Oiling and greasing of operating mechanism etc
		yearly	Checking of control circuits and its accessories i.e.

			<i>aux contactors, coils, repair/ replace if required.</i>
3	Lightening arresters	weekly	1. Visual check, leakage current counter reading to be recorded.
		Monthly	Cleaning of external insulations.
		Half yearly	checking and tightness of connections, checking earthing connections,
		yearly	Checking earthing connection up to earth pit and recording the earth pit value.
4	Overhead busbar	weekly	Visual checks for external damage of OH bus bar, connecting clamps, insulators etc.
		Monthly	Damaged clamps, insulators and nut bolts etc. shall be replaced
		Half yearly	Checking of over head structure earth connections and tighten them.
		yearly	1 Sagging of over head bus bar if required including tightening of clamps. 2. Testing of earth pit value of structure earthing pits. 3. Cleaning of insulator string.
5	HT switch gear panel indoor type	weekly	1. Cleaning of panel externally. 3. Check for proper closing of panel so that no space should be left which may allow to enter the lizard or insects.
		Monthly	1. Checking of indicating lamps, Ammeter, voltmeter along with selector switches i/c replacement of defective ones. 2. Checking of Operation of breakers for trip/ close. 3. Cleaning of panel internally.
		Half yearly	1. Checking of interlocking. 2. Checking of control circuit and its accessories (I.E. aux contacts, connections, coils etc.) 3. Visual check of earth connections and tightening if reqd.

		yearly	1. Checking, tightening and up keeping the insulation of main bus bar and cable connection. 2. Oil and greasing of operating mechanism. 3. Cleaning of contacts with CTC, indicating devices, voltmeter, a meter, selector switch etc. and replace if required. 4. Checking of CT and PT's etc. 5. Checking of SF 6 gas pressure switch operation. 6. Checking and recording of earth resistance value.
6	Relay and control panel & RTU panel	weekly	1. Cleaning of panels externally 2. Checking and replacement of indicating lamps if required.
		Monthly	1. Cleaning of panel internally with vacuum cleaner. 2. Checking of Aux contractor. 3. Check all fuses and contracts replace / repair if required.
		Half yearly	1. Checking of Earth connection of panels. 2. Check operation of auxiliary contractors. 3. Checking CTs & PTs connections.
		yearly	1. Checking and tightening of all connections. 2. Checking and servicing of all contactors and relays, repair/ replace if required. 3. Checking of earth resistance value. 4. Checking calibrating and repairing of all meters/relays. 5. To check contacts of fuses, repair / replace if required.
7	AC DB Panel	weekly	1. Cleaning of panel externally 2. Visual check of panel meters. 3. Checking indicating lamps replace/ repair if required.
		Monthly	1. Cleaning of the panel internally with vacuum cleaner. 2. Check of switch contacts 3. Checks all fuses and contacts replace / repair if required.

		Half yearly	1. Checking of Earth connection of panels. 2. Checking and repairing of operating mechanism of SFU/ MCCB etc.
		yearly	1. To check of all switches, contacts, tighten the connection, cleaning of contacts and insert petroleum jelly. 2. Checking of earth resistance value.
8	Battery charger	weekly	1. Cleaning of battery charger and performing visual inspection for any abnormality. 2. Checking of batteries i.e. electrolyte levels, sulphation of contracts. 3. Checking indicating lamps, replace/ repair if required.
		Monthly	1. To check Voltage of each battery and record. 2. To check operation of charger (Boost + float.)
		Half yearly	1. To check value of specific gravity of electrolyte of each battery 2. To remove sulphation and insert petroleum jelly. 3. Connection tighten of battery charger
		yearly	1. Internally cleaning with vacuum cleaner. 2. Tightening of all connections. 3. Checking of the operation of all switches.

Weekly Checking

1. Transformers :

Checking of oil level (topping if reqd.), oil leakage, colour of silica gel (Breather) (heating if reqd.), Vent diaphragm, Tap position of transformer, neutral earthing connections up to earth pit etc.

2. **HT Panel (11kv Switchgear) :**

To be checked, indicating lamps, Ammeter, voltmeter along with selector switches earthing connection of panels, cleaning of external panel, these should be closed properly and no space be left which may allow the lizard or insects to enter.

3. **Capacitor Panels :**

To be checked, indicating lamps, KWH meter, Ammeter, Voltmeter along with selector switches, earthing connection of panels, cleaning of external panel, these should be closed properly and no space should be left which may allow the lizard or insects to enter, visual inspection of contactors, SFU/ FSU, exhaust fan & APFC relay for any abnormality.

4. **LT Panel (0.433kv Switchgear) :**

To be checked, indicating lamps, Ammeter, Voltmeter along with selector switches, earthing connection of panels, cleaning of external panel, these should be closed properly and no space should be left which may allow the lizard or insects to enter, visual inspection of ACB's, MCCb's SFU/ FSU, all relays for any abnormality.

Monthly Checking

1 Trans formers :

- **HT and LT Bushing:** Open cable box LT side and examine cracks, oil leakage etc. terminal tighten nut & bolts and clean if required.
- **Silica gel :** Check condition of silica gel and replace if required, replace cup's oil.
- **Pressure relay :** To be checked mechanical indication and operating mechanism.
- **Earth resistance of neutral earthing :** Record value of resistance dry & wet condition of earth pit.
- **Breakdown test of transformer oil :**

1. BDV with 2.5mm gap.

(i.)	Top sample.	kV
(ii.)	Bottom sample.	kV
(iii.)	OTIC sample.	kV

2. BDV with 4mm gap (for with stand) One minute/ For Breakdown

(i.)	Top sample	KV
(ii.)	Bottom sample	KV

- **Magnetic oil level gauge & Buchholz relay.** :_Checks its operation, control circuit and repair if required.
- **IR value** : Checks its operation, control circuit and repair if required.

2 HT Panel (11kv Switchgear) :

- Internal & external cleaning of panel.
- Tightening of main connection bus bard and cable connection (outgoing)
- Checking interlocking system (if required)
- Oiling, greasing of operating mechanism.
- Auxiliary contacts, indicating devices, voltmeter, ammeter, KWH meter and selector switch etc. check and repair/replace if required.
- Instrument & potential transformer to be checked.
- To check setting the relay time and contacts of relay of each breaker and record.
- Servicing of breakers.
- Checking of panel's heater and thermostats.

3 Capacitor bank panel :

- Internal & external cleaning of panel
- Tightening of connection busbar and cable connection (outgoing)
- Checking of APFC relay for proper functioning.

- Auxiliary contacts, indicating devices, voltmeter, ammeter, and selector switch etc. check and repair/ replace if required.
- Instrument & current transformer to be checked.
- Checking of contactors and SFU/ FSU/ MCCB.

4 LT Panel (0.433kv Switchgear) :

- Internal & external cleaning of panel
- Tightening of connection busbar and cable connection (outgoing)
- Checking of interlocking system (if required)
- Oiling, greasing of operating mechanism.
- Auxiliary contacts, indicating devices, voltmeter, ammeter, and selector switch etc. check and repair/replace if required.
- Instrument & potential transformer to be checked.
- To check setting the relay time and contacts of relay of each breaker and record.
- Servicing of breakers.

AMF PANEL:

AMF panel following servicing repairing shall be done by specialized service engineer monthly and submit the report along with monthly running bill.

- *Servicing and maintenance of AMF panels and LT Panels installed in the DG room this include cleaning of panels, repairing all the indicating lamps & pumps in perfect working order, tightening of all the cable connections etc as reqd.*
- *AMF relay, V/A / KWH /F/PF meter checking, indicator, sector switch, connectors, ferruling*
- *Main DG contactor, checking cleaning, and LT cable connection & control circuit cable connection.*
- *Setting of AMF panel relays O/C and E/F etc. and repairing of relay.*
- *AMF panel checking, cleaning*
- *UPS battery supply connection, checking cleaning, fuse continuity and replacement*
- *Testing of AMF panel auto and manual on load operations*
- *Attending AMF panel during any breakdowns and preventive maintenance of DG sets*
- *Check earth connections and tightening of all terminals*

PLC PANEL

PLC DG synchronizing panel following servicing repairing shall be done by specialized service engineer monthly and submit the report along with monthly running bill.

- Servicing and maintenance of PLC panels installed in the DG rooms at various places in the campus
- PLC relay, V/A / KWH /F/PF/ RPM / KVA / KW/ KVAR checking and cleaning, repairing, indicator, sector switch, connectors, ferruling repairing of cable connection & control cable connection. etc as reqd.
- Main and DG supply operations in auto and manual mode Setting of PLC relay and repairing of relay.
- UPS battery supply connection, checking cleaning, fuse continuity and replacement,
- Testing of PLC panel auto and manual on load operations
- Attending PLC panel during any breakdowns and preventive maintenance of DG sets
- Check earth connections and tightening of all terminals

RTU PANEL

- Servicing and maintenance of RTU panels
- Panel indications
- PT connections of the sub stations
- Status of different signals available for monitoring in SCADA (such as auto trip, Spring Charge, MFM status, CB on remote, Transformer oil temp alarm, Transformer Buchholz alarm, winding temperature alarm)
- Control signals available on SCADA system(on/OFF)
- Power pack
- Communication signal/ethernet
- Earthing of RTU panel
- RTU panel cooling fan

Half Yearly

1. Transformer

- HT and LT Bushing:- To open cable box and examine cracks in bushing. Tighten bolts if reqd., measure IR value with 10,000 Volts megger.
- Silica Gel:- Replacement of silica gel and cup oil.
- Pressure Relay:- To check the mechanical indication and operating mechanism.
- (Earth resistance of neutral earthing):- Record value of resistance dry & wet condition of earth pit.
- Break down test of transformer oil:- BDV with 2.5mm gap
(i.) Top sample kV
(ii.) Bottom sample. kV

- *Cooling fan.- To check cooling fan operation (manual / auto) and all accessories (i.e. contacts, controlling circuit etc. remove fault or repair / replace damaged parts if required.*
- *Buchholze relay, magnetic oil gauge: - Check its operation, control circuit and repair replace as required.*
- *IR value.*

2 HT Panel (11kv Switchgear) :

- *Internal & external cleaning of panel.*
- *Tightening of main connection bus bar and cable connections*
- *Checking of interlocking system.*
- *Oiling greasing of operating mechanism*
- *Auxiliary contacts, indicating devices, voltmeter, ammeter, and selector switch etc. check and repair/replace if required.*
- *Instrument & potential transformer to be checked.*
- *To checking setting/ calibrating the relay time and contacts of relay of each breaker and record.*

3 Capacitor bank panel :

- *Internal & external cleaning of panel.*
- *Tightening of connection busbar and cable connection*
- *Checking of APFC relay for their function.*
- *Auxiliary contacts, indicating devices, voltmeter, ammeter, and selector switch etc. check and repair/replace if required.*
- *Instrument & potential transformer to be checked.*
- *Cleaning of main and auxiliary contact of contactors and overhauling of exhaust fans.*

4 LT Panel (0.433kv Switchgear) :

- *Internal & external cleaning of panel*
- *Tightening of connection busbar and cable connection*
- *Checking of interlocking system*

- Oiling and greasing of operating mechanism.
- Auxiliary contacts, indicating devices, voltmeter, ammeter, and selector switch etc. check and repair/ replace if required.
- Instrument & current transformer to be checked.
- To check setting the relay time and contacts of relay of each breaker and record.

Yearly Checking

1. Transformer :

- HT and LT Bushing:- To open cable box and examine cracks in bushing. Tighten bolts if reqd., measure IR value with 10,000 Volts megger.
- Silica gel:- Replacement of silica gel and cup oil.
- Pressure relay:- To check the mechanical indication and operating mechanism.
- Earth resistance of neutral earthing:- Record value of resistance dry & wet condition of earth pit.
- Break down test of transformer oil:- BDV with 2.5mm gap

(i.)	Top sample	kV
(ii.)	Bottom sample.	kV
- Buchholz relay & magnetic oil gauge:- Check its operation, control circuit and repair/replace as required.
- Centrifuging of transformer oil and check acidity: Sludge and submit test report.

(i.)	B.D.V. 4mm gap for 1 minute	3 sample.
(ii.)	(ii.) B.D.V 2.5mm gap for breakdown	3 sample
(iii.)	Sludge/Acidity value.	
(iv.)	IR Value	

2 HT Panel (11kv Switchgear) :

- Servicing of SF6/VCB 36 k v breaker.
- Operation checking of breaker.
- Control circuit and its accessories i.e aux Contactors, connection, coils etc). repair/ replace if required.
- Check gas pressure and record heating system and its operation to be checked.

- *Cleaning of circuit*

3 Capacitor bank panel :

- Cleaning of panel internal & external.
- Checking of APFC relay for their function.
- Auxiliary contacts, indicating devices, voltmeter, ammeter, and selector switch etc. check and repair/ replace if required.
- Servicing of contactors, FSU/SFU.
- Checking and replacing of defective capacitors.

4 LT Panel (0.433kv Switchgear) :

- Servicing of ACB"s & MCCB"s.
- Operation checking of ACB,s & MCCB,s
- Auxiliary contacts, indicating devices, voltmeter, ammeter, and selector switch etc. check and repair/ replace if required.
- Instrument & current transformer to be checked.
- To check setting the relay time and contacts of relay of each breaker and record.

3. Terms and conditions of maintenance under above scope of works

- i) *The installation shall be maintained in the existing original condition/position. The installation is running quite satisfactory at present. The contractor shall be solely responsible for maintenance and upkeep of the equipment in good conditions.*
- ii) *The supplying and topping up of transformer oil as and when required, filtration and centrifuging of oil shall be as per required, BOQ and as per instruction of the Engineer in charge in a year, changing of gasket as and when required and with required quantity of material for maintenance such as tools & instruments, CTC, cloth, sand paper, nut and bolts with washer (S.S.), petroleum jelly, lubricating oil greases, HRC fuses for control supply & indication lamps shall also be covered in scope of work.*

- iii) *The preventive maintenance schedule shall be prepared and submitted by the contractor in advance to Engineer In Charge concerned. The necessary shutdown may be taken with prior permission of the Institute.*
- iv) *Performa for weekly, monthly, half yearly & yearly checking should be filled up after doing preventive maintenance/inspection of equipment. The maintenance records shall be checked & verified by the competitive authority i.e. Engineer in charge and finally submitted to Engineer In Charge. (Weekly, monthly, half yearly and yearly maintenance & repair chart / Performa shall be as per Appendix A or shall be provided by Institute from time to time)*
- v) *A suitable complete shutdown shall be given once in a year for preventive maintenance of the complete system. All the equipment's should be thoroughly checked & maintained for proper functioning/operations of the equipment. All relays have to be checked and calibrated once a year.*
- vi) *All major structures, cable supports and steel frames shall be painted once in a year with approved colour.*
- vii) *Replacement of indicating lamp/ LED type lamp and panel locks, including supply of the same as and when found defective.*
- viii) *Cleaning of complete yard (33/11 KV SS) including painting of structure of complete yard along with fencing and screening of sand and screen concrete and spread the same once in a year and grass root removing four times in a year as required.*
- ix) *All the other repair works except given in the contract, will be carried out by the Institute on his own cost.*
- x) *The payment against operation and maintenance during the contact period shall be made against quarterly running bills of the accepted amount for AOMC subject to satisfactory maintenance of the installation and submission of all formats such as weekly, monthly, quarterly & yearly as provided by the Institute duly filled and accepted by Engineer In Charge of the work.*
- xi) *The adequate team of manpower shall be available at site as per quantum of the work. Also it is responsibility of the contractor to provide the manpower within 2-3 hours on call by any representative of the Institute in case of breakdown.*
- xii) *There shall be a penalty in case of short supply/fail to supply the man power at the time of maintenance/breakdown. A penalty of Rs.2000/- shall be liable on first occasion and the*

same shall be increased to Rs.4000/- for second occasion further on wards. In case the situation does not improve, the contract shall be rescinded.

- xiii) *A list of spares (which are usually used) for each equipment shall be submitted by the contractor to the dept. along with the rates and price list.*
- xiv) Complete transformer yard cleaning should be done once in every three months“ time i/c removing of grass roots as other work etc. or as reqd. at all 11/.433 KV substations covered under the contract
- xv) Testing, calibrating & setting of all the relays, kWH meters installed at different sub-stations has to be done ones in year and report has to be submitted by the contactor in the office of Engineer In Charge of the work.
- xvi) He/she shall prepare a docket, in prescribed proforma, for each complaint and allocate the work to the respective skilled/semi-skilled workers. The worker shall carry the docket while entering the premises of the complaints.
- xvii) The recovered materials should be deposited in the enquiry and handed over to the respective Engineer In Charge, once every month for further disposal.
- xviii) The contractor shall engage only experienced, skilled & technically sound manpower in the concerned area i.e for electrical installations, wiring, energy metering works etc. to execute good quality work.
- xix) The contractor shall arrange all the equipment’s related to the work at his/her own expenses.
- xx) The Competent Authority shall take stock of the inventory once in a month. The cost of short fall of the stocks, if any shall be recovered from the contractor at the purchase price.
- xxi) The contractor shall be held responsible if there is unusually high quantum of wastage of materials. The Competent Authority shall determine the legitimate wastage and recover the cost of excess wastage if deemed necessary.
- xxii) The Competent Authority shall have the right to assign any other duty or work at any other building, if so required under contingent circumstances.
- xxiii) The contractor has to provide a dress code for all his workers.
- xxiv) Mechanism for checking and follow-ups of day-to-day complaints in whole campus comprising of all zones covered under the contract, making records of breakdowns/complaints/rectification and reporting to ZIC.
- xxv) Monthly reports as per Appendix A shall have to be prepared and produced to the competent authority monthly at the time of billing.

Monthly Maintenance of Report of 33/11 KV Substation to be submitted along with the monthly running bills

Appendix-A						
S.No.	SF-6 Breaker-33 KV Outdoor -1	Observations	Material Change	SF-6 Breaker-33 KV Out door-2	Observations	Material Change
i)	Motor charging			Motor charging		
ii)	Remote / Local			Remote / Local		
iii)	DC/ AC supply			DC/ AC supply		
iv)	Triping / closing coil			Triping / closing coil		
v)	GAS Pressure			GAS Pressure		
	SF-6 Breaker - 33 KV Outdoor-3			SF-6 Breaker-33 KV Out door-4		
i)	Motor charging			Motor charging		
ii)	Remote / Local			Remote / Local		
iii)	DC/ AC supply			DC/ AC supply		
iv)	Triping / closing coil			Triping / closing coil		
v)	GAS Pressure			GAS Pressure		
	Transformer 10 MVA No.-1			Transformer 10 MVA No.-2		
i)	Breather			Breather		
ii)	Oil level / Oil Leakage			Oil level / Oil Leakage		
iii)	Cleaning			Cleaning		
iv)	Winding / Oil Temp			Winding / Oil Temp		
	11 KV Breaker Indoor			Lighting Arrester		
i)	Indicator			Cleaning & service		
ii)	Volt meter			C.T & P.T		
iii)	Ampere Meter			Cleaning		
iv)	KWH Meter			Insulator		
v)	Motor charging			Cleaning		
vi)	Breaking oil Gressing					
vii)	Relay					
viii)	33 KV Isolator-I			33 KV Isolator-I		
ix)	Contacts health			Contacts health		
x)	Moving parts			Moving parts		
xi)	Fixed parts			Fixed parts		
xii)	Earthing			Earthing		
xiii)	Moter			Moter		

	Battery / Battery Charger			AC/ DC Distribution panel		
i)	Indicator			Indicator		
ii)	Volt meter / Amp Meter			Voltmeter / Amp Meter		
iii)	Busbar Status			SFU, MCCB, MCB		
iv)	Cleaning					
	Control Panel and RTCC Panel			RTU Panel		
i)	Selector Switch			Indicator		
ii)	Heater Switch			UPS		
iii)	AVR Relay			Terminal Conectivity		
iv)	Indicator			Smart meter working		
v)	Cleaning			Inspection , cleaning		
				Data cable connection		
	Technician Remark			Technician Name & Signature		
	Engineer Incharge Comments					
				Engineer Incharge Signature		

Monthly Maintenance Report of 11/0.433 KV Substation to be submitted along with the monthly running bills						
	Substation Number					
S.No.	TR-1	Observations	Material Change	TR-2	Observations	Material Change
i)	Breather			Breather		
ii)	Oil Level			Oil Level		
iii)	Oil Leakage			Oil Leakage		
iv)	Cleaning			Cleaning		
v)	Buchhloz relay			Buchhloz relay		
vi)	Redaitor cleaning			Redaitor cleaning		
vii)	Bay masrshelling Kiosk Tempreature			Bay masrshelling Kiosk Tempreature		
viii)	Setting value of			Setting value of		
a	winding alarm			winding alarm		
b	winding trip			winding trip		
c	oil alarm			oil alarm		
d	oil trip			oil trip		
	TR-3			TR-4		
i)	Breather			Breather		
ii)	Oil Level			Oil Level		
iii)	Oil Leakage			Oil Leakage		
iv)	Cleaning			Cleaning		
vi)	Redaitor cleaning			Redaitor cleaning		
vii)	Bay masrshelling Kiosk Tempreature			Bay masrshelling Kiosk Tempreature		
viii)	Setting value of			Setting value of		
a	winding alarm			winding alarm		
b	winding trip			winding trip		
c	oil alarm			oil alarm		
d	oil trip			oil trip		
	HT Panel 11 KV			vii) Cable Status		
i)	Indicator			viii) Charging Motor		
ii)	KV Meter			ix) AC/DC Supply		
iii)	KWH Meter			x) Relay VCB Status		
iv)	CT			xi) Volt Selector		
v)	PT			xii) Amp Selector		
vi)	Bus Bar Status			xiii) Cleaning of HT panel		
				ix) Relay setting value of		
				a) over current		
				b) earth fault current		
				c) Instantaneous current		

	LT Panel-1			LT Panel-2		
i)	TNC Switch			TNC Switch		
ii)	Relays			Relays		
iii)	A/V/KWH Meters			A/V/KWH Meters		
iv)	Indicator			Indicator		
v)	Cable Connection			Cable Connection		
vi)	Busbar Status			Busbar Status		
vii)	SF-6 / VCB / ACB /MCCB Switches any breakdown Status			SF-6 / VCB / ACB /MCCB Switches any breakdown Status		
	Cleaning of LT Panel			Cleaning of LT Panel		
	APFC Panel-1			APFC Panel-2		
i)	APFC Relay			APFC Relay		
ii)	Capacitors Status			Capacitors Status		
iii)	Cable Connection			Cable Connection		
iv)	Busbar			Busbar		
v)	Indicator			Indicator		
vi)	Cleaning of APFC Panel			Cleaning of APFC Panel		
vii)	power factor			power factor		
viii)	KVAR			KVAR		
	PLC / AMF Panel			RTU Panel		
i)	Relay			Relays		
ii)	Voltage/Current/PF/frequency			Indicator		
iii)	A/V/KWH Meters			UPS		
iv)	Indicator			Terminal Conectivity		
v)	Control Cable Connections			Smart meter working		
vi)	UPS					
vii)	Contactors			Data cable connection		
	Cleaning of AMF Panel			Inspectrion, Cleaning of RTU Panel		
	Cleaning of Substations (Internal & External)					
	Technician Remark			Technician Name & Signature		
	Engineer Incharge Comments					
				Engineer Incharge Signature		

8.19 SPECIAL CONDITIONS OF CONTRACT

The contract for, “Annual Operation and Maintenance Contract (AOMC) of 1 no.33/11 KV substation, 13 no’s 11/0.433 KV substations and PLC Panel, AMF panels & LT panels of all DG set and petty electrical works of substations, underground distribution system, feeder pillars installed in the campus including supply of day to day manpower for maintenance of street light & for metering works at campus of IIT Kanpur & Outreach Centre NOIDA”.

- 1.0 The time allowed for carrying out the entire work will be Twelve (12) months from the date of start as defined in schedule “F” or from the first date of handing over of the site, whichever is later, in accordance with the phasing as detailed in special condition of contract in the bid document. However, It may be extended for 2nd, 3rd & 4th year provided the maintenance / operation is proper / satisfactory on the same rate, terms & conditions, defined by the Institute. However, IIT Kanpur will not be bound to extend the period and reserves its right.
- 2.0 The performance guarantee shall be refunded within 6 (six) months from the date of completion of contract, without any interest. In the event of failure to provide satisfactory performance, the security deposit shall be absolutely forfeited.
- 3.0 The contractor shall provide the manpower as per the scope of work to IIT Kanpur and shall allocate duty to the workers in consultation with the Engineer In Charge/Zonal In Charge and shall monitor the maintenance works. The deployed manpower shall have required necessary experience as defined in the scope of works for attending electrical complaints, wiring work, cabling, energy metering work and other electrical maintenance works.
- 4.0 No part of the contract shall in any manner or degree be transferred assigned or sublet by the contractor directly or indirectly to any person or firm. Violation of this condition shall render the contractor liable for panel action including termination of the contract and forfeiture of security deposit.
- 5.0 If the contractor does not commence any work in the manner described in the contract document or if at any time in the opinion of the Engineer-in-charge,
 - i) Fails to carryout the works in conformity with the contract document.
OR
 - ii) Substantially suspends the work without authority from the Institute.
OR
 - iii) Fails to carryout and execute the works to the satisfaction of the Institute.
OR
 - iv) Commits or permits breach of any other kind, or observes or persists in any of the above mentioned breaches of the contract, after notice in writing shall have been given to the contractor by the Institute requiring such breach to be remedied.
 - v) If the contractor shall abandon the works.

Then in any such case, the Institute shall have the power to enter upon the premises, take possession thereof, to rescind the contract and to carry on with the works by the

contractor's workmen the supervisor, as the Institute in its absolute discretion may think proper, without making any payment to the contractor.

- 6.0 The contractor shall make its own arrangement for transportation of the staff to and from to the campus and to the site of work.
- 7.0 If the contractor fails to commence the work on any day due to any reasons whatsoever, a penalty @ one fifteenth of the monthly contract value per day of default shall be deducted from the monthly bill. However if the services are disrupted for two consecutive days, the contract will be rescinded without any notice and the security deposit shall be absolutely forfeited.
- 8.0 If the manpower is found short due to any reason, the contractor shall have to redistribute the work among the reporting staff and continue to maintain the services in normal conditions.
- 9.0 The contractor shall furnish to the controlling officer, bill in respect of the monthly charges for providing services under the contract, in the last week of every month. The Institute shall ensure payments within 10 (ten) working days from the date of submission of bill. The contractor shall ensure that the wages are paid to its employees before 7th of every month.
- 10.0 The controlling officer shall endorse the following certificate on the monthly bills, before recommending it for payment to Engineer-in-charge.
- 11.0 "Certified that the contract during the period of the bill have been carried out as per the scope of work, terms & condition of the contract and to his entire satisfaction"
- 12.0 The contractor shall submit the bill along with the proof of having paid due wages to all the workmen engaged on the job during the preceding month. The wages shall be disbursed to the workmen in their bank account/account payee cheques only. The proof of deposition in the bank account shall be submitted at the time billing.
- 13.0 The employees of the contractor shall carry personal identity cards issued by the contractor, while on duty. In addition to this the contractor shall furnish from time to time a complete list of employees, along with passport size photographs and their residential address, to the security officer of the Institute. Alternately the contractor will issue numbered brass tokens to his workers and furnish to the controlling officer, a list of workers and the token number issued to them.
- 14.0 If and whenever any of the contractor's employees shall, in the opinion of the officer-in-charge of the Institute, be guilty of any misconduct or be incompetent or insufficiently qualified or negligent in the performance of their duties or that it is undesirable for administrative reasons for such persons to be employed in the work comprised in the contract, the contractor if so directed, shall remove such person from employment within a reasonable time. Any persons so removed from the work shall be immediately replaced at the expense of the contractor by a qualified and competent substitute.

- 15.0 The contractor shall be responsible for the proper behavior of all the staff employed on the work and shall exercise a proper degree of control over them. In particular and without prejudice to the said generality, the contractor shall be bound to prohibit and prevent any employee from trespassing / action in any way detrimental or prejudicial to the interests of the community or of the Institute of all consequent claims or actions for damages or injury whatsoever. The decision of the Institute upon any matter arising under this clause shall be final binding on the contractor.
- 16.0 Payment, due to the contractor, under contract shall be made by the Institute through electronic mode. The contractor shall present the bill duly pre-receipted on proper revenue stamp. All efforts shall be made by the Institute to make the payment within 10 working days.
- 17.0 Payment of final bill shall be made to the contractor within 30 days from the expiry / termination of the contract, provided:
- 18.0 It is accompanied with the wage register for the entire period of contract, duly authenticated by the controlling officer or his authorized representative.
- 19.0 No person below the age of 18 (eighteen) years shall be employed on the work. Similarly, no women staff shall be employed since the duty involves working in odd hrs.
- 20.0 The contractor shall not pay to persons engaged by him on the work, less than minimum wages prescribed by labour commissioner (central), Kanpur from time to time. The current minimum wages applicable as per the central government chief labor commissioner (C) New Delhi (Office Order F. No. 1/6(3) 2025-LS –II dated 30.03.2026) applicable to IIT Kanpur is as following:**
- | Description | Minimum Wage/day |
|--------------------|-------------------------|
| Skilled | Rs. 1008/- |
| Semiskilled | Rs. 918/- |
| Unskilled | Rs. 827/- |
- Experience:**
- Skilled in the associated area & required experience at least 10 years
- Semiskilled in the associated area & required experience at least 6 years
- Unskilled in the associated area & required experience at least 3 year
- 21.0 The contractor shall, at their own expense, comply with all labour laws and keep the Institute indemnified in respect thereof.
- 22.0 The contractor shall be registered with Regional Labour Commissioner (Central) and obtain license as per contract labour Act. 1976, within 1 month from the date of award of work or minimum reasonable time.

- 23.0 The contractor shall be solely responsible as regards to payment of wages / salary, service conditions and terms & conditions of employment. In this connection he shall maintain requisite records and comply with all laws / enactment's, rules, regulations and orders applicable to the contractor's employees in general and in particular laws / enactment's, rules & regulations & orders dealing with employment of contract labour, payment of minimum wages, fire & safety regulations, security arrangements and such other rules & regulations as may be applicable at present or made applicable hereafter.
- 24.0 Drinking liquor within the Institute campus is strictly prohibited. Violation of this rule by the employees of the contractor shall render them liable for prosecution as per law and automatically disqualify them from deployment on the work
- 25.0 The Institute shall not be liable for any damage or compensation payable in respect of or in consequence of any accident or injury to any person in the employment of the contractor, save and except an accident or injury resulting from any act or default of the Institute. The contractor shall indemnify and keep indemnified the Institute against all such damage and compensation whatsoever in respect of or in relation their to.
- 26.0 The contractor's staff not be treated as the Institute staff for any purpose whatsoever. The contractor shall be responsible for strict compliance of the statutory provisions of relevant labour laws applicable from time to time, in carrying out the service contract. The Institute shall not be liable to any penalty for which the contractor is responsible under the law. However if the Institute is forced to pay any cost of any nature on account of contractor's liabilities, the said cost shall be recovered from the payments due to the contractor.
- 27.0 The contractor shall be responsible for fulfilling the requirement of all statutory provisions of relevant enactment's viz minimum wages Act payment of wages Act, Industrial Dispute Act, Contract Labour (Regulation & Abolition) Act and all other labour & industrial enactment's at their own risk and cost in respect of all staff employed by them. The Institute shall be indemnified for any action brought against it for any violation / non-compliance of any of the provisions of any of the Acts etc. The contractor shall maintain all records required to be maintained under the statutory enhancements. The controlling officer shall be entitled to inspect all such records at any time.
- 28.0 The workers shall report to Contractor and register their daily attendance and same the attendance copy submitted to Engineer In-charge.
- 29.0 The value of work shall be inclusive of the wages of the workers & supervisor, cost of tools and implements i/c contingent expenditure incidental to the work etc. Nothing extra shall be payable in addition to the monthly value of the contract except.
- [
- 1) The difference in minimum wages applicable to the labour are revised by Govt. of India, subsequent to the date of submission of tender shall be paid by the contractor to the labour and reimbursed by the institute on production of claim. Profit @ 3.85% shall be paid on this wages difference claim.
 - 2) The contribution of EPF& ESIC by the contractor shall be reimbursed on production of the receipt of deposit of the same in the office of competent authorities. Administrative expenses deposited by the contractor shall not be reimbursed.

- 3) The successful bidder / contractor has to cover all of its Technicians / workers, under workers' compensations insurance, who are not covered under ESIC. Bidder has to quote accordingly; no additional charges shall be paid on the account of workers' compensation insurance.
- 4) Rates shall be quoted inclusive of GST.
- 5) Labour License: The lowest bidder has to submit the labour License within one month date of award of work.

The contractor shall make all arrangements such as tools and plants, nut & bolts, screws, thread, PVC tape, thimbles, PVC insulated flexible copper wire, cotton rags, soot safeda/Teflon , washers, nails, etc. required for proper completion of the assigned job. The manpower provided by the contractor may be deployed at any location inside IIT Kanpur campus for carrying out the Electrical maintenance/operation works. The Institute may arrange for the electrical items such as wires, switches, sockets, cables , meters, panels, fans, heaters, geysers or any other items for installation or day to day repair and maintenance at site by the contractors manpower's. The ZIC's may assign any required work related to the electrical maintenance to the manpower's and they have to execute timely and with devotion. The contractor shall be liable for any lapse in the assigned work by the Engineer In charges to the provided manpower's.

- 30.0 The contractor shall have to work under the overall control of the Competent Authority through the Superintending Engineer, IWD.
- 31.0 The contractor shall have to appoint a qualified person with a B.Tech degree with 08 years' experience/ Diploma with 10 years of experience of Electrical work who should be able to develop a complete plan for respective zones for every 6 months, should be able to present innovative/sustainable ideas to upgrade the institute with give necessary training to the workers, supervise the work and also efficiently deploy manpower for improved productivity.
- 32.0 If penalty is imposed three times by the Institute during the contract period. The process for termination of contract shall be initiated.
- 33.0 All the work should be carried out as per CPWD specifications for Electrical works and as per CPWD Maintenance manual or as directed by the Engineer in Charge appointed by SE, IWD through approval of competent authority.
- 34.0 All guidelines issued by Government of India time to time related to covid shall have to be followed and implemented by the contractor at work site. The contractor have to quote the rates accordingly, no claim on this account shall be entertained at all the stage.
- 35.0 Mechanism to lodge and respond to complaints: The agency will provide an effective mechanism to respond to the complaints by students/staff/faculty/guest etc. lodged through the complaint management mechanisms of institute and will resolve the complaints within 2 hours of receipt

of complaint. A penalty of Rs 1000/- will be imposed on any pending complaints beyond 24 hours.

- 36.0 The agency must also create and deploy an Immediate Response Strategy for all types of complaints pertaining to Electrical work, within IIT Campus.
- 37.0 Assessment of Performance: Performance of the agency will be assessed on the basis of: Feedback of students/staff/faculty/guests/hall in charge with respect to level of cleanliness in the campus at all times etc. Time taken to respond and resolve the complaints etc. Efficiency of the complaint redressed system etc. Rating given by an internal committee to assess the performance based on predefined parameters.
- 38.0 Area under contract must be maintained as per the standards and scope of work and nothing extra will be paid for maintaining beyond the scope.
- 39.0 Any fault regarding Civil, Electrical and Air Conditioning as noticed at these areas including leaking pipes should be informed to the concerned Engineer In-charge of the area.
- 40.0 The agency will facilitate providing information required for preparation/ updating the detailed landscape map of areas/locations to be with color fill legends for each item. This map will also serve as a bench mark of performance assessment.
- 41.0 The contract shall be drawn for a period of 12 calendar months from the date of commencement of work. However, in case of unsatisfactory performance of the contractor found frequently, the contract may be terminated on the basis of performance report of the Competent Authority through the Superintending Engineer, IWD.
- 42.0 Safety devices and equipment shall be provided by the contractor to all his workmen on duty as required.
- 43.0 Maintenance of records : Daily log of manpower, equipment deployed, consumables used should be maintained, Meticulously maintained logs accessible to Institute officers. All bills related to procurement must be part of the log and the register must be submitted along with bill copies for verification by institute officers at the time of bill claims.
- 44.0 Training of workers: The quarterly training of the Electrician/mechanic is mandatory and same shall be conducted by the agency. The duly signed sheet by the workers shall have to be submitted to the Institute.
- 45.0 The contractor have to make own arrangement for keeping all machines & attachment inside the campus including its safety and security. The Institute will provide temporary open space inside the campus.
- 46.0 The rates quoted shall be inclusive of all charges of safety tools, machines/equipment i.e. labour, T&P etc. including its Maintenance (routine, preventive and breakdown) of machines shall have to be made by the contractor.

- 47.0 The agency must also create and deploy an Immediate Response Strategy for all types of complaints related to the work within IIT Campus.
- i. All activities are come under control of competent authority through Superintending Engineer, IWD of the Institute. The contractors have to take the daily instructions from him. 100% manpower as per agreed deployment should be made available at all time.
 - ii. Personnel grooming should be as per acceptable standards.
 - iii. All employed staff should be above 18 years of age.
- 48.0 Daily log of deployment of machines, equipment, consumables & manpower used should be maintained by the contractor with the daily checking by the competent authority through SE, IWD.

Pre-Contract Integrity Pact
(Applicable for all tenders of the value above Rs.1 Crore)

General

This pre-bid pre-contract Agreement (hereinafter called the Integrity Pact) is made on _____ day of the month of _____ 202____.

BY AND BETWEEN

The Indian Institute of Technology Kanpur represented through "The Registrar", having its office located at G.T. Road, Kalyanpur, Kanpur, Uttar Pradesh – 208016 (hereinafter called the "BUYER", which expression shall mean and include, unless *the* context otherwise requires, his successors in office and assigns) of the **First Part**;

AND

M/s _____
a company incorporated under the Companies Act, 2013 through its representative/authorized signatory (insert name and designation of the officer) vide resolution dated _____ passed by the Board of Directors, having its registered office at _____

(hereinafter referred to as "The Bidder(s)/Contractor(s)" which terms or expression shall, unless excluded by or repugnant to the subject or context, mean and include its successor-in-office, administrators or permitted assignees) of the **Second Part**;

WHEREAS, the Institute/Buyer has floated the Tender bearing No. _____ (hereinafter referred to as "Tender/Bid") and intends to award, under laid down organization procedures, contract(s) for _____

_____(Name of the work/goods/ services). The Institution values full compliance with all relevant laws of the land, rules, regulations, economic use of resources and of fairness/transparency in its relations with its Bidder(s) and/or Contractor(s).

AND WHEREAS, the BIDDER is a private company/public company/Government undertaking/partnership/registered export agency, constituted in accordance with the relevant law in the matter and the BUYER is a body corporate and has been established under the provisions of the Institutes of Technology Act, 1961.

AND WHEREAS, in order to achieve these goals, in consultation with the CVC, the Govt. of India, Ministry of Education has appointed Independent External Monitors (IEMs), who will monitor the tender process and the execution of the contract for compliance with the principles mentioned above.

U.S.S.

NOW, THEREFORE, to avoid all forms of corruption by following a system that is fair, transparent and free from any influence/prejudiced dealings prior to, during and subsequent to the currency of the contract to be entered into with a view to:-

Enabling the BUYER to obtain the desired said stores/equipment at a competitive price in conformity with the defined specifications by avoiding the high cost and the distortionary impact of corruption on public procurement, and

Enabling BIDDERS to abstain from bribing or indulging in any corrupt practice in order to secure the contract by providing assurance to them that their competitors will also abstain from bribing and other corrupt practices and the BUYER will commit to prevent corruption, in any form, by its officials by following transparent procedures.

The parties hereto hereby agree to enter into this Integrity Pact and agree as follows:

Commitments of the BUYER

- 1.1 The BUYER undertakes that no official of the BUYER, connected directly or indirectly with the contract, will demand, take a promise for or accept, directly or through intermediaries, any bribe, consideration, gift, reward, favour or any material or immaterial benefit or any other advantage from the BIDDER, either for themselves or for any person, organisation or third party related to the contract in exchange for an advantage in the bidding process, bid evaluation, contracting or implementation process related to the contract.
- 1.2 The BUYER will, during the pre-contract stage, treat all BIDDERS alike, and will provide to all BIDDERS the same information and will not provide any such information to any particular BIDDER which could afford an advantage to that particular BIDDER in comparison to other BIDDERS.
- 1.3 All the officials of the BUYER will report to the appropriate Government office any attempted or completed breaches of the above commitments as well as any substantial suspicion of such a breach.
2. In case any such preceding misconduct on the part of such official(s) is reported by the BIDDER to the BUYER with full and verifiable facts and the same is prima facie found to be correct by the BUYER, necessary disciplinary proceedings, or any other action as deemed fit, including criminal proceedings may be initiated by the BUYER and such a person shall be debarred from further dealings related to the contract process. In such a case while an enquiry is being conducted by the BUYER the proceedings under the contract would not be stalled.

Commitments of BIDDERS

3. The BIDDER commits itself to take all measures necessary to prevent corrupt practices, unfair means and illegal activities during any stage of its bid or during any pre-contract or post-contract stage in order to secure the contract or in furtherance to secure it and in particular commit itself to the following:-

U.S.

- 3.1 The BIDDER will not offer, directly or through intermediaries, any bribe, gift, consideration, reward, favour, any material or immaterial benefit or other advantage, commission, fees, brokerage or inducement to any official of the BUYER, connected directly or indirectly with the bidding process, or to any person, organisation or third party related to the contract in exchange for any advantage in the bidding, evaluation, contracting and implementation of the contract.
- 3.2 The BIDDER further undertakes that it has not given, offered or promised to give, directly or indirectly any bribe, gift, consideration, reward, favour, any material or immaterial benefit or other advantage, commission, fees, brokerage or inducement to any official of the BUYER or otherwise in procuring the Contract or forbearing to do or having done any act in relation to the obtaining or execution of the contract or any other contract with the Government for showing or forbearing to show favour or disfavour to any person in relation to the contract or any other contract with the Government.
- 3.3 The Bidder(s)/Contractor(s) of foreign origin shall disclose the name and address of the Agents/representatives in India, if any. Similarly, the Bidder(s)/Contractor(s) of Indian Nationality shall furnish the name and address of the foreign entity or associates, if any. Further details as mentioned in the "Guidelines of Indian Agents of Foreign suppliers" shall be disclosed by the Bidders(s)/Contractor(s). Further, as mentioned in the Guidelines all payments made to the Indian Agent/representative have to be in Indian Rupees only.
- 3.4 BIDDERS shall disclose the payments to be made by them to agents/brokers or any other intermediary, in connection with this bid/contract.
- 3.5 The BIDDER further confirms and declares to the BUYER that the BIDDER is the original manufacturer/integrator/authorised government sponsored export entity of the defence stores and has not engaged any individual or firm or company whether Indian or foreign to intercede, facilitate or in any way to recommend to the BUYER or any of its functionaries, whether officially or unofficially to the award of the contract to the BIDDER, nor has any amount been paid, promised or intended to be paid to any such individual, firm or company in respect of any such intercession, facilitation or recommendation.
- 3.6 The BIDDER, either while presenting the bid or during pre-contract negotiations or before signing the contract, shall disclose any payments he has made, is committed to or intends to make to officials of the BUYER or their family members, agents, brokers or any other intermediaries in connection with the contract and the details of services agreed upon for such payments.
- 3.7 The BIDDER will not collude with other parties interested in the contract to impair the transparency, fairness and progress of the bidding process, bid evaluation, contracting and implementation of the contract.

VIS.

- 3.8 The BIDDER will not accept any advantage in exchange for any corrupt practice, unfair means and illegal activities.
- 3.9 The BIDDER shall not use improperly, for purposes of competition or personal gain, or pass on to others, any information provided by the BUYER as part of the business relationship, regarding plans, technical proposals and business details, including information contained in any electronic data carrier. The BIDDER also undertakes to exercise due and adequate care lest any such information is divulged.
- 3.10 The BIDDER commits to refrain from giving any complaint directly or through any other manner without supporting it with full and verifiable facts.
- 3.11 The BIDDER shall not instigate or cause to instigate any third person to commit any of the actions mentioned above.
- 3.12 If the BIDDER or any employee of the BIDDER or any person acting on behalf of the BIDDER, either directly or indirectly, is a relative of any of the officers of the BUYER, or alternatively, if any relative of an officer of the BUYER has financial interest/stake in the BIDDER's firm, the same shall be disclosed by the BIDDER at the time of filing of tender. The term 'relative' for this purpose would be as defined in Section 2(77) of the Companies Act, 2013.
- 3.13 The BIDDER shall not lend to or borrow any money from or enter into any monetary dealings or transactions, directly or indirectly, with any employee of the BUYER.

Disqualification from tender process and exclusion from future contracts:

- 4.1 If the Bidder(s)/Contractor(s), before award or during execution has committed a transgression through a violation of Section 2, above or in any other form such as to put their reliability or credibility in question, the Institute/Buyer is entitled to disqualify the Bidder(s)/Contractor(s) from the tender process or take action as per the procedure mentioned in the "Guidelines on Banning of Business Dealing".
- 4.2 Any violation of Integrity Pact would entail disqualification of the bidder(s) and exclusion from future business dealings, as per the existing provisions of GFR-2017, PC Act, 1988 and other Financial Rules/Guidelines etc. as may be applicable to the organization concerned.

Compensation for Damages:

- 5.1 If the Institute/Buyer has disqualified the Bidder(s) from the tender process prior to the award according to Section 3, the Institute/Buyer is entitled to demand and recover the damages equivalent to Earnest Money Deposit/Bid Security.
- 5.2 If the Institute/Buyer has terminated the contract according to Section 3, or if the Institute/Buyer is entitled to terminate the contract according to Section 3, the Institute/Buyer shall be entitled to demand and recover from the Contractor liquidated

Visa

damages of the Contract value or the amount equivalent to Performance Bank Guarantee.

Previous Transgression

6.1 THE BIDDER(S) to disclose any transgressions with any other public/government organization that may impinge on the anti-corruption principle. The date of such transgressions, for the purpose of disclosure by the BIDDER(s) in this regard, would be the date on which cognizance of the said transgression was taken by the competent authority. The period for which such transgression(s) is/are to be reported by the bidders shall be the last **three years** to be reckoned from date of bid submission. The transgression(s), for which cognizance was taken even before the said period of three years, but are pending conclusion, shall also be reported by the BIDDERS.

6.2 The BIDDER agrees that if it makes incorrect statement on this subject, BIDDER can be disqualified from the tender process or the contract, if already awarded, can be terminated for such reason.

Equal Treatment of all Bidders/Contractors/Sub-Contractors:

7.1 In the case of sub-contracting, the principal/main Contractor shall take the responsibilities of adoption of the Integrity Pact by the Sub-contractor.

7.2 The BUYER will enter into agreements with the identical conditions as this one with all bidders and Contractors.

7.3 The BUYER will disqualify from the tender process all bidders who do not sign this Pact or violate its provisions.

Criminal Charges against violating Bidder(s)/Contractor(s)/Sub-Contractors:

8. If the Buyer obtains knowledge of the conduct of a Bidder, Contractor or Sub-contractor, or of an employee or a representative or an associate of a Bidder, Contractor or Sub-contractor which constitutes corruption, or if the Institute/Buyer has substantive suspicion in this regard, the Institute/Buyer will inform the same to the Chief Vigilance Officer.

Earnest Money (Security Deposit)

9.1 While submitting a commercial bid, the BIDDER shall deposit an amount of Rs. _____ (to be specified in RFP) as Earnest Money/Security Deposit, with the BUYER through any of the following instruments:

- (i) Bank Draft in the favour of The Registrar, IIT Kanpur.
- (ii) A confirmed guarantee by an Indian Nationalised Bank, promising payment of the guaranteed sum to the BUYER on demand within three working days

Visf.

without any demur whatsoever and without seeking any reasons whatsoever. The demand for payment by the BUYER shall be treated as conclusive proof of payment.

(iii) Any other mode or through any other instrument (to be specified in the RFP).

9.2 The Earnest Money (Security Deposit) should be valid up to a period of 45 days beyond the validity of the quote.

9.3 In case of the successful BIDDER a clause would also be incorporated in the Article pertaining to Performance Bond in the Purchase Contract that the provisions of Sanctions for Violation shall be applicable for forfeiture of Performance Bond in case of a decision by the BUYER to forfeit the same without assigning any reason for imposing sanction for violation of this Pact.

9.4 No interest shall be payable by the BUYER to the BIDDER on Earnest Money/Security Deposit for the period of its currency.

Sanctions for Violations

10.1 Any breach of the aforesaid provisions by the BIDDER or anyone employed by it or acting on its behalf (whether with or without the knowledge of the BIDDER) shall entitle the BUYER to take all or any one of the following actions, wherever required: -

- (i) To immediately call off the pre contract negotiations without assigning any reason or giving any compensation to the BIDDER. However, the proceedings with the other BIDDER(s) would continue.
- (ii) The Earnest Money Deposit (in pre-contract stage) and/or Security Deposit/Performance Bond (after the contract is signed) shall stand forfeited either fully or partially, as decided by the BUYER and the BUYER shall not be required to assign any reason, therefore.
- (iii) To immediately cancel the contract, if already signed, without giving any compensation to the BIDDER.
- (iv) To recover all sums already paid by the BUYER, and in case of an Indian BIDDER with interest thereon at 2% higher than the prevailing Prime Lending Rate of State Bank of India, while in case of a BIDDER from a country other than India with interest thereon at 2% higher than the LIBOR. If any outstanding payment is due to the BIDDER from the BUYER in connection with any other contract for any other stores, such outstanding payment could also be utilised to recover the aforesaid sum and interest.
- (v) To encash the advance bank guarantee and performance bond/warranty bond, if furnished by the BIDDER, in order to recover the payments, already made by the BUYER, along with interest.
- (vi) To cancel all or any other Contracts with the BIDDER. The BIDDER shall be liable to pay compensation for any loss or damage to the BUYER

U.S.F.

resulting from such cancellation/rescission and the BUYER shall be entitled to deduct the amount so payable from the money(s) due to the BIDDER.

- (vii) To debar the BIDDER from participating in future bidding processes of the Institute for a minimum period of two years, which may be further extended at the discretion of the BUYER.
- (viii) To recover all sums paid in violation of this Pact by BIDDER(s) to any middleman or agent or broker with a view to securing the contract.
- (ix) In cases where irrevocable Letters of Credit have been received in respect of any contract signed by the BUYER with the BIDDER, the same shall not be opened.
- (x) Forfeiture of Performance Bond in case of a decision by the BUYER to forfeit the same without assigning any reason for imposing sanction for violation of this Pact.

10.2 The BUYER will be entitled to take all or any of the actions mentioned at para 10.1 (i) to (x) of this Pact also on the Commission by the BIDDER or any one employed by it or acting on its behalf (whether with or without the knowledge of the BIDDER), of an offence as defined in Chapter IX of the Indian Penal Code, 1860 or Prevention of Corruption Act, 1988 or any other statute enacted for prevention of corruption.

10.3 The decision of the BUYER to the effect that a breach of the provisions of this Pact has been committed by the BIDDER shall be final and conclusive on the BIDDER. However, the BIDDER can approach the Independent Monitor(s) appointed for the purposes of this Pact.

Fall Clause

11. The BIDDER undertakes that it has not supplied/is not supplying similar product/systems or subsystems at a price lower than that offered in the present bid in respect of any other Ministry/Department of the Government of India or PSU and if it is found at any stage that similar product/systems or sub systems was supplied by the BIDDER to any other Ministry/Department of the Government of India or a PSU at a lower price, then that very price, with due allowance for elapsed time, will be applicable to the present case and the difference in the cost would be refunded by the BIDDER to the BUYER, if the contract has already been concluded.

Independent Monitors

12.1 The IEMs have been appointed by the Ministry of Education in consultation with the Central Vigilance Commission. The details of the IEMs are as follows:

- (a) Mr. Ranvir Singh, IEM1@iitk.ac.in
- (b) Mr. P.V.V. Satyanarayana, IEM2@iitk.ac.in

USE

- 12.2 The task of the Monitor shall be to review independently and objectively, whether and to what extent the parties comply with the obligations under this Pact.
- 12.3 The Monitor shall not be subject to instructions by the representatives of the parties and perform their functions neutrally and independently.
- 12.4 Both the parties accept that the Monitor has the right to access all the documents relating to the project/procurement, including minutes of meetings.
- 12.5 As soon as the Monitor notices, or has reason to believe, a violation of this Pact, he will so inform the Authority designated by the BUYER.
- 12.6 The BIDDER(s) accepts that the Monitor has the right to access without restriction to all Project documentation of the BUYER including that provided by the BIDDER. The BIDDER will also grant the Monitor, upon his request and demonstration of a valid interest, unrestricted and unconditional access to his project documentation. The same is applicable to Subcontractors. The Monitor shall be under contractual obligation to treat the information and documents of the BIDDER/Subcontractor(s) with confidentiality. The Monitor has also signed declarations on "Non – Disclosure of Confidential Information" and of "Absence of Conflict of Interest". In case of any conflict of interest arising at a later date, from an entity wherein he is or has been a consultant, the IEM shall inform the Director, IIT Kanpur and rescue himself/herself from that case.
- 12.7 The BUYER will provide to the Monitor sufficient information about all meetings among the parties related to the Project provided such meetings could have an impact on the contractual relations between the parties. The parties will offer to the Monitor the option to participate in such meetings.
- 12.8 The Monitor will submit a written report to the designated Authority of BUYER within 8 to 10 weeks from the date of reference or intimation to him by the BUYER / BIDDER and, should the occasion arise, submit proposals for correcting problematic situations.
- 12.9 A person signing the IP Pact shall not approach the Court while representing the matter to IEMs and shall await the decision in the matter.
- 12.10 The IP would be implemented through a panel of Independent External Monitors (IEMs), appointed by the Ministry. The IEM would review independently and objectively whether and to what extent parties have complied with their obligations under the Pact on receipt of any complaint by them from the Bidder(s).
- 12.11 Integrity Pact (IP), in respect of a particular contract, shall be operative from the date IP is signed by both the parties. The IEMs shall examine all the representations/grievances/complaints received by them from the bidders or their authorized representatives related to any discrimination on account of lack of fair play in modes of procurement and bidding systems, tendering method, eligibility conditions, bid evaluation criteria, commercial terms & conditions, choice of technology/specifications etc.

U.S.F.

12.12 For ensuring the desired transparency and objectivity in dealing with the complaints arising out of the tendering process, the matter should be examined by the full panel of IEMs jointly, who would look into the records, conduct an examination, and submit their joint recommendations to the Management. In case the full panel is not available due to some unavoidable reasons, the available IEM(s) will conduct examination of the complaints. Consent of the IEM(s), who may not be available, shall be taken on the records.

12.13 The word "**Monitor**" would include both singular and plural.

Facilitation of Investigation

13. In case of any allegation of violation of any provisions of this Pact or payment of commission, the BUYER or its agencies shall be entitled to examine all the documents including the Books of Accounts of the BIDDER and the BIDDER shall provide necessary information and documents in English and shall extend all possible help for the purpose of such examination.

Law and Place of Jurisdiction

14. This Pact is subject to Indian Law. The place of performance and jurisdiction is the seat of the BUYER i.e., Kanpur Nagar.

Other Provisions

15.1 The actions stipulated in this Integrity Pact are without prejudice to any other legal action that may follow in accordance with the provisions of the extant law in force relating to any civil or criminal proceedings.

15.2 Changes and supplements as well as termination notices need to be made in writing. Side agreements have not been made.

15.3 In case of a joint venture, all the partners of the joint venture should sign the Integrity Pact. In case of sub-contracting, the principal/main contractor shall take responsibilities of the adoption of IP by the sub-contractor. It is to be ensured that all sub-contractors also sign the IP. In case of sub-contractors, the IP will be tri-partite arrangement to be signed by the Institute/Buyer, the Contractor, and the sub-contractor.

15.4 Should one or several provisions of this Pact turn out to be invalid, the remainder of this Pact remains valid. In this case, the parties will strive to come to an agreement to their original intentions.

15.5 Issues like Warranty/Guarantee etc. shall be outside the purview of the IEMs.

15.6 In the event of any contradiction between the Integrity Pact and its Annexure, the clause in the Integrity Pact will prevail.

Validity

Uiff.

16.1 The validity of this Integrity Pact shall be from date of its signing and extend up to 5 years or the complete execution of the contract to the satisfaction of both the BUYER and the BIDDER/Seller, including warranty period, whichever is later. In case BIDDER is unsuccessful, this Integrity Pact shall expire after six months from the date of the signing of the contract.

16.2 Should one or several provisions of this Pact turn out to be invalid; the remainder of this Pact shall remain valid. In this case, the parties will strive to come to an agreement to their original intentions.

IN WITNESS WHEREOF, the parties hereunto set their hands and seals and executed this Integrity Pact as of the date/month/year first above written in the presence of following witnesses:

For & on behalf of
The Indian Institute of Technology Kanpur
(First Party)
Signed, Sealed and delivered by

For & on behalf of
The M/s
(Second Party)
Signed, Sealed and delivered by

Vishwa
Name: **Vishwa Ranjan**
Designation: **Registrar**
Address: **Indian Institute of Technology Kanpur**
(Authorized Signatory)
भारतीय प्रौद्योगिकी संस्थान कानपुर
INDIAN INSTITUTE OF TECHNOLOGY KANPUR
कानपुर - 208 016 (उ.प्र.) भारत
KANPUR - 208 016 (U.P.) INDIA

Name:
Designation:
Address:
(Authorized Signatory vide resolution
dated passed by the Board of
Directors)

In the presence of Witness:

1.(Indenter)
2.

1.
2.

केन्द्रीय लोक निर्माण विभाग
कार्यालय ज्ञापन

No. DG/MAN/410

ISSUED BY AUTHORITY OF DIRECTOR GENERAL, CPWD

NIRMAN BHAWAN, NEW DELHI

DATED: 22.10.2021

Subject: Addition of new Para 4.10.2 in CPWD Works Manual 2019 regarding testing charges to be borne by contractor.

It has been noticed that following provisions are sometimes being made in the NITs / Agreements by the NIT approving authorities:

"The cost of test shall be borne by contractor/ department in the manner as below:

- By the contractor, if the result shows that material does not conform to the relevant codes/ specification.
- By the department, if the results show that the material conforms to relevant codes/ specification."

It has been decided by the competent authority that testing charges shall be borne by the contractor in all cases. Accordingly following new para is added in CPWD Works Manual -2019.

Existing Provision	Modified Provision
4.10 Preparation of NIT	4.10 Preparation of NIT
4.10.2 No Provision	4.10.2 Testing charges to be borne by contractor
	Following provision shall be incorporated by the NIT approving authority in the NIT:
	All expenditure to be incurred for testing of samples e.g. packaging, sealing, transportation, loading, unloading etc. including testing charges shall be borne by the contractor. The NIT shall have list of approved laboratories for testing as approved by ADG / SDG.

This issues with the approval of competent authority.

(वी.पी. साहू) 22/10/2021

अधीक्षण अभियंता(सी.एंड एम.)

e-file 9116587

Issued from file No. CSQ/CM/16(1)/2021

प्रतिलिपि: सभी केलोनिवि तथा लोनिवि दिल्ली के अधिकारियों को आवश्यक सूचना एवं कार्यवाही हेतु। (केलोनिवि वेबसाईट के माध्यम से)।